

# Dell™ Photo All-In-One Printer 966 User's Guide

To order ink or supplies from Dell:

1. Double-click the icon on your desktop.



2. Visit Dell's website, or order Dell printer supplies by phone.

[www.dell.com/supplies](http://www.dell.com/supplies)

For the best service, make sure you have the Dell printer Service Tag available.

[Finding Information](#)

[About Your Printer](#)

[Understanding the Operator Panel Menus](#)

[Loading Paper and Originals](#)

[Printing](#)

[Printing From a Memory Card or USB Key](#)

[Copying](#)

[Scanning](#)

[Faxing](#)

[Understanding the Software](#)

[Installing the Dell 966 Internal Wireless/Ethernet Adapter](#)

[Maintenance](#)

[Troubleshooting](#)

[Specifications](#)


[Appendix](#)

[Licensing Notice](#)

---

## Notes, Notices, and Cautions

 **NOTE:** A **NOTE** indicates important information that helps you make better use of your printer.

 **NOTICE:** A **NOTICE** indicates either potential damage to hardware or loss of data and tells you how to avoid the problem.

 **CAUTION:** A **CAUTION** indicates a potential for property damage, personal injury, or death.

Information in this document is subject to change without notice.

© 2007 Dell Inc. All rights reserved.

Reproduction in any manner whatsoever without the written permission of Dell Inc. is strictly forbidden.

Trademarks used in this text: *Dell*, the *DELL* logo, *Dell Picture Studio*, and *Dell Ink Management System* are trademarks of Dell Inc.; *Microsoft* and *Windows* are registered trademarks of Microsoft Corporation in the United States and/or other countries. *Windows Server* and *Windows NT* are registered trademarks of Microsoft Corporation. *Windows Vista* is either a trademark or a registered trademark of Microsoft Corporation in the United States and/or other countries. *Bluetooth* is a registered trademark owned by Bluetooth SIG, Inc. and is used by Dell Inc. under license. *EMC* is a registered trademark of EMC Corporation.





Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Dell Inc. disclaims any proprietary interest in trademarks and trade names other than its own.


### UNITED STATES GOVERNMENT RESTRICTED RIGHTS


This software and documentation are provided with RESTRICTED RIGHTS. Use, duplication or disclosure by the Government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.227-7013 and in applicable FAR provisions: Dell Inc., One Dell Way, Round Rock, Texas, 78682, USA.



# Finding Information

What are you looking for?	Find it here
<ul style="list-style-type: none"><li>• Drivers for my printer</li><li>• My <i>User's Guide</i></li></ul>	<p><i>Drivers and Utilities CD</i></p>  <p>If you purchased your Dell computer and printer at the same time, documentation and drivers for your printer are already installed on your computer. You can use the CD to uninstall/reinstall drivers or access your documentation. Readme files may be included on your CD to provide last-minute updates about technical changes to your printer or advanced technical reference material for experienced users or technicians.</p>
How to set up my printer	<p><i>Setting Up Your Printer poster</i></p> 
<ul style="list-style-type: none"><li>• Safety information</li><li>• How to set up and use my printer</li><li>• Warranty information</li></ul>	<p><i>Owner's Manual</i></p> 
Express Service Code and Service Tag number	<p>Express Service Code and Service Tag number</p>  <p>This label is located on the printer (see below).</p>



<ul style="list-style-type: none"> <li>• Latest drivers for my printer</li> <li>• Answers to technical service and support questions</li> <li>• Documentation for my printer</li> </ul>	<p>Dell Support Website: <a href="http://support.dell.com">support.dell.com</a></p> <p>The Dell Support website provides several online tools, including:</p> <ul style="list-style-type: none"> <li>• Solutions—Troubleshooting hints and tips, articles from technicians, and online courses.</li> <li>• Upgrades—Upgrade information for components, such as memory</li> <li>• Customer Care—Contact information, order status, warranty, and repair information</li> <li>• Downloads—Drivers</li> <li>• Reference—Printer documentation and product specifications</li> </ul>
<ul style="list-style-type: none"> <li>• How to use <i>Windows</i><sup>®</sup> XP</li> <li>• Documentation for my printer</li> </ul>	<p>Windows XP Help and Support Center</p> <ol style="list-style-type: none"> <li>1. Click <b>Start</b><sup>®</sup> <b>Help and Support</b>.</li> <li>2. Type a word or phrase that best describes your problem, and then click the <b>arrow</b> icon.</li> <li>3. Click the topic that describes your problem.</li> <li>4. Follow the instructions shown on the screen.</li> </ol>
<ul style="list-style-type: none"> <li>• How to use Windows Vista<sup>™</sup></li> <li>• Documentation for my printer</li> </ul>	<p>Windows Vista Help and Support Center</p> <ol style="list-style-type: none"> <li>1. Click  <b>Help and Support</b>.</li> <li>2. Type a word or phrase that best describes your problem, and then click the <b>arrow</b> icon.</li> <li>3. Click the topic that describes your problem.</li> <li>4. Follow the instructions shown on the screen.</li> </ol>

# Faxing

- [Setting Up the Printer With External Devices](#)
- [Sending a Fax](#)
- [Receiving a Fax](#)
- [Changing the Fax Setup](#)
- [Using Speed Dial](#)
- [Blocking Faxes](#)
- [Creating Fax Activity Report](#)

Use your printer to send and receive faxes without having to connect to a computer.


In addition, the Dell Fax Solutions Software is bundled in the *Drivers and Utilities* CD and should have been installed when you installed your printer driver. You can also use this faxing software to send and receive faxes.

Equipment	Benefits	See this section
<ul style="list-style-type: none"><li>• printer</li><li>• phone cord (provided)</li></ul>	Make copies and send and receive faxes without the use of a computer.	<a href="#">Connecting Directly to a Telephone Wall Jack</a>
<ul style="list-style-type: none"><li>• printer</li><li>• telephone (sold separately)</li><li>• two phone cords (one provided)</li></ul>	<ul style="list-style-type: none"><li>• Use the fax line as a normal telephone line.</li><li>• Set up your printer wherever your telephone is.</li><li>• Make copies and send and receive faxes without the use of a computer.</li></ul>	<a href="#">Connecting to a Telephone</a>
<ul style="list-style-type: none"><li>• printer</li><li>• telephone (sold separately)</li><li>• answering machine (sold separately)</li><li>• three phone cords (one provided)</li></ul>	Receive both incoming voice messages and faxes.	<a href="#">Connecting to an Answering Machine</a>
<ul style="list-style-type: none"><li>• printer</li><li>• telephone (sold separately)</li><li>• computer modem (sold separately)</li><li>• three phone cords (one provided)</li><li>• USB cable (sold separately)</li></ul>	Increase the number of phone connection outlets.	<a href="#">Connecting to a Computer Modem</a>

---


## Setting Up the Printer With External Devices

### Connecting Directly to a Telephone Wall Jack



1. Connect one end of the phone cord to the FAX connector (FAX—upper connector).
2. Connect the other end of the phone cord to an active telephone wall jack.

## Connecting to a Telephone




1. Connect a phone cord from the FAX connector (FAX—upper connector) on the printer to an active telephone wall jack.
2. Remove the blue protective plug from the PHONE jack connector (PHONE—bottom connector).
3. Connect a phone cord from the telephone to the PHONE jack connector (PHONE—bottom connector).

**NOTE:** If phone communication is serial in your country (such as Germany, Sweden, Denmark, Austria, Belgium, Italy, France, and Switzerland), remove the blue plug from the PHONE jack connector (PHONE—bottom connector), and insert the supplied yellow terminator for your fax to work correctly. You will not be able to use this port for additional devices in these countries.

## What if I have a Digital Subscriber Line (DSL)?

DSL delivers digital data to a computer through a telephone line. Your printer is designed to work with analog data. If you are faxing over a telephone line connected to a DSL modem, install a DSL filter to avoid interference with the analog fax modem signal.

**NOTE:** ISDN (integrated services digital network) and cable modems are not fax modems and are not supported for faxing.



1. Connect the DSL filter to an active telephone line.
2. Connect the printer directly to the output on the DSL filter.


**NOTE:** Do not install any splitters between the DSL filter and the printer. Contact your DSL service provider if you need more help.

## Connecting to an Answering Machine



1. Connect a phone cord from the FAX connector (FAX—upper connector) on the printer to an active telephone wall jack.
2. Remove the blue protective plug from the PHONE jack connector (PHONE—bottom connector).
3. Connect a phone cord from the answering machine to a telephone.
4. Connect a phone cord from the answering machine to the PHONE jack connector (PHONE—bottom connector).



**NOTE:** If phone communication is serial in your country (such as Germany, Sweden, Denmark, Austria, Belgium, Italy, France, and Switzerland), you must remove the blue plug from the PHONE jack connector (PHONE—bottom connector), and insert the supplied yellow terminator for your fax to work correctly. You will not be able to use this port for additional devices in these countries.

## Connecting to a Computer Modem





1. Connect a phone cord from the FAX connector (FAX—upper connector) on the printer to an active telephone wall jack.



























2. Remove the blue protective plug from the PHONE jack connector (  —bottom connector).
3. Connect a phone cord from the computer modem to the PHONE jack connector (  —bottom connector).
4. Connect a phone cord from the computer modem to a telephone.

 **NOTE:** If phone communication is serial in your country (such as Germany, Sweden, Denmark, Austria, Belgium, Italy, France, and Switzerland), you must remove the blue plug from the PHONE jack connector (  —bottom connector), and insert the supplied yellow terminator for your fax to work correctly. You will not be able to use this port for additional devices in these countries.

## Sending a Fax

### Entering a Fax Number

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**.
2. Enter a fax number.



Task	Method
Sending to a fax number	Use the keypad to enter a number. You can enter a maximum of 64 digits in a fax number.
Sending a fax to an entry in the Phone Book	<ul style="list-style-type: none"> <li>• Enter the number that corresponds to the speed dial number of the contact.</li> <li>• Use the <b>Phone Book</b> menu.               <ol style="list-style-type: none"> <li>a. Press the up or down <b>Arrow</b> button   to scroll to <b>Fax</b>, and then press the <b>Select</b> button .</li> <li>b. Press the up or down <b>Arrow</b> button   to scroll to <b>Phone Book</b>, and then press the <b>Select</b> button .</li> <li>c. Press the up or down <b>Arrow</b> button   to scroll to <b>Name Search</b>, <b>Phone Number Search</b>, or <b>Group Search</b>, and then press the <b>Select</b> button .</li> <li>d. Press the up or down <b>Arrow</b> button   to scroll to the name or number you want to send the fax to.</li> </ol> </li> </ul>
Sending a fax to an extension number	Press the asterisk (*) and pound (#) signs, and then use the keypad to enter the extension number.
Sending a fax to an outside line	<p>Set a dial prefix:</p> <ol style="list-style-type: none"> <li>a. From the main menu, press the up or down <b>Arrow</b> button   to scroll to <b>Fax</b>, and then press the <b>Select</b> button .</li> <li>b. Press the up or down <b>Arrow</b> button   to scroll to <b>Fax Setup</b>, and then press the <b>Select</b> button .</li> <li>c. Press the up or down <b>Arrow</b> button   to scroll to <b>Dialing and Sending</b>, and then press the <b>Select</b> button .</li> <li>d. Press the up or down <b>Arrow</b> button   to scroll to <b>Dial Prefix</b>, and then press the left or right <b>Arrow</b> button   to scroll to <b>Create</b>.</li> <li>e. Press the <b>Select</b> button .</li> </ol> <p><b>NOTE:</b> If you are changing the dial prefix, scroll to <b>Modify</b>.</p> <ol style="list-style-type: none"> <li>f. Use the keypad to enter the dial prefix. You can enter a maximum of eight digits for the prefix.</li> <li>g. Press the <b>Select</b> button .</li> </ol>
Dialing a fax extension while listening to a telephone line	Dial an additional 0 for a two-digit extension or an additional 0 0 for a one-digit extension. For example, to dial extension 12, enter 120. If the extension is 2,



## Sending a Fax Using the Operator Panel

1. Make sure your printer is on and connected to an active telephone line.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load the original document.



4. Press the up or down **Arrow** button  to scroll to Fax.
5. Use the keypad to enter a fax number or a speed dial number. For more information, see [Entering a Fax Number](#).
6. Press the **Start** button .

## Sending a Fax Using the Dell All-In-One Center

1. Turn on your printer and computer, and make sure they are connected. Make sure your computer modem is connected to an active analog telephone line. If you have DSL broadband service on the same phone line that you are using to fax, you must also have a DSL filter installed. Contact your Internet Service Provider for information.
2. Load your original document.



3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
- b. Click **Dell Printers**.

c. Click **Dell Photo AIO Printer 966**.

4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.


5. In the Dell All-In-One Center, you can either:

- In the **Scan** or **Fax** section, send a single- or multiple-page fax. First, customize your fax job by answering the questions that appear on your screen.

To send a single-page fax, click **Fax Now**.

To send a multiple-page fax, click **Advanced**, select the **Scan multiple items before output** check box, and then click **OK**.

- In the **Productivity Tools** section, click **Fax an image**, and follow the instructions on the screen.

 **NOTE:** One of the questions on the screen asks if there is more than one page. If there are multiple pages in your fax, you should choose **Yes, prompt me for each page**.

## Faxing Electronic Documents

1. With the file open, click **File® Print**.

The **Print** dialog box opens.

2. In the printer list, select **DellFax**.

3. Click **OK**, and then follow the instructions on the screen.

## Sending a Broadcast Fax

A broadcast fax allows you to send the same fax to multiple recipients at once. You can enter up to 30 different numbers.

1. Make sure your printer is on and connected to an active telephone line.

2. Load your original document.



3. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button





4. Use the keypad to enter the fax number. For more information, see [Entering a Fax Number](#).

5. Press the down **Arrow** button  to go to the next fax number field.


6. Use the keypad to enter the next fax number.

7. Repeat this process until you have entered all phone numbers to which the fax needs to be sent.

 **NOTE:** You can also use the **Phone Book** or **Redial History** option to select phone numbers. Each number you select or enter is added to the fax list until you press the **Start** button .

8. Press the **Start** button .








After you initiate the fax, the printer dials the first number, establishes a connection, sends the fax, breaks the connection, and moves to the next number on the list. This continues until the list has been completed. If the printer is unable to make a connection to a fax number, the printer moves to the next number on the list. The number to which a connection was not established is moved to the end of the list, and it is tried again when the rest of the list has been completed.

 **NOTE:** Fax numbers to which the printer could not establish a connection are retried based on the number of retries specified in the **Dialing and Sending** menu.

## Manually Dialing a Fax While Listening to a Telephone Line (On Hook Dial)

1. Make sure your printer is on and connected to an active telephone line.
2. Load an original document.



3. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .
4. Press the up or down **Arrow** button   to scroll to **On Hook Dial**.
5. Press the **Select** button  to make the printer go off hook.
6. Enter the number to which you want to send a fax. For more information, see [Entering a Fax Number](#).
7. Press the **Start** button  when you are ready to send a fax.








## Sending a Delayed Fax

1. Make sure your printer is on and connected to an active telephone line.
2. Load your original document.



3. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then enter a fax number. For






more information, see [Entering a Fax Number](#).


4. Press the **Select** button .
5. Press the up or down **Arrow** button  to scroll to **Delay Sending Fax**, and then press the **Select** button .
6. Use the keypad to specify the hour, and then press the right **Arrow** button .
7. Use the keypad to specify the minutes, and then press the right **Arrow** button .
8. Use the keypad to specify **AM** (1), **PM** (2), or **24Hr** (3).
9. Press the **Select** button .
10. Press the **Start** button .

At the designated time, the fax number is dialed, and the fax is transmitted to the designated fax number. If the fax transmission is unsuccessful, the unsuccessful number is tried again based on the redial settings.


## Creating a Fax Cover Page

### Using the Operator Panel

1. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Edit Fax Settings**, and then press the **Select** button.
3. From the Cover Page menu item, press the left or right **Arrow** button  to scroll to **Yes**, and then press the **Menu** button .
4. Use the keypad to enter or change information on the Cover Page screen.

 **NOTE:** You can also enter or change information on the Cover Page using the **Printer Setup Utility**. For more information, see [Using the Computer](#).

### Using the Computer

1. With the Dell Fax Solutions open, select **Select Settings**.
2. Click the **Sending Faxes** tab.
3. From the Cover Page area, click **User Information**.
4. Enter information about the sender.  
  
 **NOTE:** You may have already specified this information when you used the Dell Fax Solutions for the first time.
5. Click **OK**.
6. From the Cover Page area, click **Configure Cover Page**.
7. Click **Next** or **Preview** to choose a template for your cover page.
8. Add a company logo, if necessary.
  - a. Click **Change**.
  - b. Click **Browse**.













- c. Browse for an image of your company logo, and click **Open**.
  - d. Adjust your logo, if necessary.
  - e. Click **OK**.
9. Click **OK**.

## Sending a Color Fax

 **NOTE:** The fax machine of the recipient should also support color faxes.

1. Make sure your printer is on and connected to an active telephone line.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load the original document. Faxing color documents uses a lot of the printer's memory. We recommend that you limit the outgoing fax to two pages.









4. Press the up or down **Arrow** button   to scroll to **Fax**.
5. Press the **Select** button .
6. Press the up or down **Arrow** button   to scroll to **Edit Fax Settings**, and then press the **Select** button .
7. Press the up or down **Arrow** button   to scroll to **Color**, and then press the left or right **Arrow** button   to scroll to **Color**.
8. Press the **Back** button  twice to go back to the main menu.
9. Use the keypad to enter a fax number. For more information, see [Entering a Fax Number](#).
10. Press the **Start** button .






## Using Auto Fax Convert

If you are faxing a high-resolution document to a fax machine that prints at a lower resolution, the printer can automatically adjust the fax you send.

 **NOTE:** If you turn off **Auto Fax Convert** and you attempt to send a fax that is not compatible with the receiving fax machine, the fax is not sent and an **Unsupported Mode** error is displayed.
















**Auto Fax Convert** is on by default. To turn off **Auto Fax Convert**:

1. On the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button   to scroll to **Fax Setup**, and then press the **Select** button .

3. Press the up or down **Arrow** button  to scroll to **Dialing and sending**, and then press the **Select** button .
  4. Press the up or down **Arrow** button  to scroll to **Auto Fax Conversion**, and then press the left or right **Arrow** button  to scroll to **Off**.
  5. Press the **Back** button .
- 

## Receiving a Fax


### Receiving a Fax Automatically

1. Make sure your printer is on and connected to an active telephone line.
2. Make sure **Auto Answer** is turned on or is currently within the scheduled on period.
  - a. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
  - b. Press the up or down **Arrow** button  to scroll to **Auto Answer**.
  - c. Press the left or right **Arrow** button  to scroll to **On** or **Scheduled**, and then press the **Select** button .
  - d. If you selected **Scheduled**, the **Auto Answer Schedule** screen appears. Use the keypad to specify the time you want **Auto Answer** to be turned on and turned off.
  - e. Press the **Back** button .
3. Set the number of rings the printer should allow before answering the incoming fax.
  - a. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
  - b. Press the up or down **Arrow** button  to scroll to **Fax Setup**, and then press the **Select** button .
  - c. Press the up or down **Arrow** button  to scroll to **Ring and Answering**, and then press the **Select** button .
  - d. Press the up or down **Arrow** button  to scroll to **Pick-up On**.
  - e. Press the up or down **Arrow** button  to select the number of rings you want to allow before the printer receives the fax.
  - f. Press the **Back** button .





When the number of set rings is detected, the printer automatically receives the fax.


### Receiving a Fax Manually

1. Make sure your printer is on and connected to an active telephone line.
2. Make sure **Auto Answer** is turned on or is currently within the scheduled on period.
  - a. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and then press the **Select**









button 




- b. Press the up or down **Arrow** button  to scroll to **Auto Answer**.
  - c. Press the left or right **Arrow** button  to scroll to **On** or **Scheduled**, and then press the **Select** button 
  - d. If you selected **Scheduled**, the **Auto Answer Schedule** screen appears. Use the keypad to specify the time you want **Auto Answer** to be turned on and turned off.
  - e. Press the **Select** button 
3. When the telephone rings, pick up the telephone, and listen for the fax calling tone.
  4. If you hear the fax calling tone, press **DELL# (3355#)** on the printer operator panel.

 **NOTE:** **DELL#** is the default answer code. However, you can change this to any code. For more information, see [Changing the Pickup Code](#).

## Changing the Pickup Code

1. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button 
2. Press the up or down **Arrow** button  to scroll to **Fax Setup**, and then press the **Select** button 
3. Press the up or down **Arrow** button  to scroll to **Ring and Answering**, and then press the **Select** button 
4. Press the up or down **Arrow** button  to scroll to **Manual Pickup Keycode**, and then press the **Select** button 
5. Use the keypad to specify a new one- to seven-digit keycode.


 **NOTE:** Valid characters for the pickup code are 0–9, pound (#), and star (\*). Any other characters entered are ignored.

6. Press the **Select** button 








## Receiving a Fax Using Dell Fax Solutions

1. Click **Start® Programs** or **All Programs ® Dell PC Fax® Dell PC Fax**.

For Windows Vista:







- a. Click  **® Programs**.
  - b. Click **Dell PC Fax**.
  - c. Click **Dell PC Fax**.
2. From **Receiving Faxes**, choose how you want to receive the fax. Select **Automatically** if you want the software to receive faxes, or **Manually** if you want to decide when to answer incoming faxes. If you choose to manually receive the fax, you have to click **Answer Now** whenever someone is attempting to send you a fax.
  3. Select the check box beside **Print incoming faxes** if you want all incoming faxes printed upon receipt.

## Printing a Long Fax

1. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button  to scroll to **Fax Printing**, and then press the **Select** button .
4. From the **If Too Big** menu item, press the left or right **Arrow** button  to choose an option.
5. Press the **Back** button .

If you have purchased and installed the optional paper tray, you can load paper of different sizes in the trays. For example, you can load letter size plain paper in Tray 1 and load legal size paper in Tray 2. The printer automatically picks the paper that will match the size of the incoming fax. For more information, see [Understanding Tray Linking](#).

## Printing a Fax on Both Sides of the Page

1. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button  to scroll to **Fax Printing**, and then press the **Select** button .
4. From the **2-Sided Print** menu item, press the right or left **Arrow** button to scroll to **2 Sided Print**.
5. Press the **Back** button .

---

## Changing the Fax Setup

### Using the Operator Panel


If you are using your printer as a standalone fax machine, you can change the fax settings from the **Edit Fax Settings** menu and **Fax Setup** menu. Changes made on the **Edit Fax Settings** menu are temporary and are cleared after the fax has been sent or cancelled. On the other hand, changes on the **Fax Setup** menu are permanent and are applicable to all fax jobs. For more information, see [Edit Fax Settings Menu](#) and [Fax Setup Menu](#).

### Using the Computer

You can access the **Printer Setup Utility** if you want to configure the printer's fax settings from your computer.

1. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click ® **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Printer Setup Utility**.



On this tab:	You can:
Dialing and Sending	<ul style="list-style-type: none"> <li>• Specify a dial method.</li> <li>• Enter a dial prefix.</li> <li>• Set the dial volume.</li> <li>• Enter your fax number and your name.</li> <li>• Specify the number of times you want the machine to redial and the time between those attempts if the fax cannot be sent on the first try.</li> <li>• Choose whether to scan the entire document before or after dialing the number.</li> <li>• Specify a maximum send speed and a print quality for outgoing faxes.</li> <li>• Convert the fax automatically to be compatible with the receiving fax machine regardless of the send settings.</li> </ul>
Ringing and Answering	<ul style="list-style-type: none"> <li>• Specify the number of rings before the machine receives the incoming fax.</li> <li>• Specify a distinctive ring if your phone line has distinctive ring service activated.</li> <li>• Set the ring volume.</li> <li>• Choose whether to use error correction.</li> <li>• Choose a Caller ID pattern (1 if telephones in your country have a detection pattern using FSK or 2 if telephones in your country have a detection pattern using DTMF). The Caller ID detection pattern is determined by the country or region you selected during initial setup. If phones in your country use two detection patterns, call your telecommunications company to know which pattern it subscribes to.</li> <li>• Specify a manual answer code. The default code is <b>DELL# (3355#)</b>.</li> <li>• Choose whether you want to answer incoming faxes automatically or at a scheduled time.</li> <li>• Specify the time when incoming faxes are answered automatically.</li> <li>• Select whether you want to forward a fax, or print it and then forward it.</li> <li>• Specify a fax number to which faxes are forwarded.</li> <li>• Manage blocked faxes.</li> </ul>
Fax Printing/Reports	<ul style="list-style-type: none"> <li>• Choose to automatically resize oversize faxes so they print on one page, or keep the oversized fax to scale and print on two pages.</li> <li>• Choose whether you want to print a footer (date, time, and page number) on each page.</li> <li>• If an optional second paper tray is installed, choose from which tray the printer picks paper. Choose <b>Auto</b> if you want the printer to pick the paper that matches the size of the incoming fax.</li> <li>• If an optional duplex is installed, choose if you want to print on both sides of the page.</li> <li>• Specify when to print a fax activity report.</li> <li>• Specify when you want to print a fax confirmation.</li> </ul>
Speed Dial	Add to, create, or edit the speed dial or group dial speed dial lists.
Cover Page	<ul style="list-style-type: none"> <li>• Specify if you want to send a cover page for outgoing faxes.</li> <li>• Edit or update the information that will appear on your cover page.</li> <li>• Choose a priority for your outgoing fax.</li> <li>• Include a short message.</li> </ul>



## Using Speed Dial




To make sending faxes easier, you can assign a speed dial number to 89 individual contacts and 10 groups that can hold up to 30 phone numbers each.


## Creating a Speed or Group Dial List


### Adding an Entry to the Speed Dial List

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .








2. Press the up or down **Arrow** button  to scroll to **Phone Book**, and then press the **Select** button .


- ^ v 
3. Press the up or down **Arrow** button  to scroll to **Add Entry**, and then press the **Select** button .
  4. Use the keypad to enter a Name and Fax Number.


 **NOTE:** The lowest possible speed dial number is automatically assigned to this contact. You cannot change the speed dial number.

5. Press the **Back** button .




## Adding an Entry to the Group Dial List


1. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Phone Book**, and then press the **Select** button .
3. Press the up or down **Arrow** button  to scroll to **Add Group**, and then press the **Select** button .
4. Use the keypad to assign a name and fax numbers to the group. Press the down **Arrow** button  to enter another number. You can also use the **Name Search**, **Phone Number Search**, or **Redial History** option to select phone numbers. Each number you select or enter is added to the group dial list.

 **NOTE:** The lowest possible group dial number is automatically assigned to this contact. You cannot change the speed dial number.

5. Press the **Back** button .

## Using a Speed or Group Dial List









1. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
2. Use the keypad to enter the two-digit speed dial number.
3. Press the **Start** button .

 **NOTE:** When you are entering numbers, if you only enter two numbers and an entry corresponds to this number, the printer assumes you are entering a speed dial entry. If the number you entered does not correspond to any entry in the Phone Book, the printer assumes you are entering an extension number.

---

## Blocking Faxes

### Create a Blocked Fax List

1. From the main menu, press the up or down **Arrow** button  to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button  to scroll to **Fax Blocking**, and then press the **Select** button .
4. Press the up or down **Arrow** button  to scroll to **Blocked Fax Add Entry**, and then press the **Select** button .



5. Use the keypad to specify a name.
6. Use the keypad to enter a fax number, and then press the **Select** button

**NOTE:** The lowest possible blocked fax number is automatically assigned to this contact. You cannot change the blocked fax number.

## Turning on Fax Blocking

1. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button to scroll to **Fax Blocking**, and then press the **Select** button .
4. From the **Blocked List** menu item, press the left or right **Arrow** button to choose **On**.
5. Press the **Select** button .

If the printer detects a fax from one of the numbers on the Blocked Fax List, the transmission is disconnected.

## Blocking Faxes Without Caller ID

1. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and press the **Select** button.
2. Press the up or down **Arrow** button to scroll to **Fax Setup**, and press the **Select** button.
3. Press the up or down **Arrow** button to scroll to **Fax Blocking**, and press the **Select** button.
4. Press the left or right **Arrow** button to choose **On** from **Block No-ID**.
5. Press the **Select** button.

If the printer detects a fax from a machine without Caller ID, the transmission is disconnected.

---

## Creating Fax Activity Report

### Using the Operator Panel


1. From the main menu, press the up or down **Arrow** button to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button to scroll to **History and Reports**, and then press the **Select** button .
4. From the **History and Reports** menu, you can view or print your fax activity.

# Using the Computer

## Creating a Report for Sent or Outgoing Faxes

1. Click **Start® Programs** or **All Programs® Dell PC Fax® Dell PC Fax**.


For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell PC Fax**.
  - c. Click **Dell PC Fax**.
2. From **Sending Faxes**, click **Create Report**.
  3. Select a date range for your report.
  4. Click the print button in the upper-left corner of the dialog to print the fax report.

## Creating a Report for Received and Incoming Faxes

1. Click **Start® Programs** or **All Programs® Dell PC Fax® Dell PC Fax**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell PC Fax**.
  - c. Click **Dell PC Fax**.
2. From **Receiving Faxes**, click **Create Report**.
  3. Select a date range for your report.
  4. Click the print button in the upper-left corner of the dialog to print the fax report.


# About Your Printer

- [Understanding the Printer Parts](#)
- [Understanding the Operator Panel](#)

You can use your printer to do a variety of things. A few important things to note:


- If the printer is connected to a computer, you can use either the printer operator panel or the printer software to produce quality documents.
- You *do* need to connect your printer to a computer to print, scan, or use the **Save Photos to Computer** function or the **Print Files** mode.
- You *do not* need to connect your printer to a computer to make photocopies, send faxes, or print from memory cards or a PictBridge-enabled camera.

 **NOTE:** The printer (whether it is connected to a computer or not) must be connected to a telephone line before you can send a fax.

 **NOTE:** If you use a DSL modem for your computer, you must install a DSL filter on the telephone line attached to your computer.


---

## Understanding the Printer Parts




Number:	Part:	Description:
1	Automatic Document Feeder (ADF)	Part that feeds original documents into the printer.
2	Printer unit	Unit you lift to gain access to the ink cartridges.
3	Operator panel	Panel on the printer you use to control copying, scanning, faxing, and printing. For more information, see <a href="#">Understanding the Operator Panel</a> .
4	Paper tray	Tray that holds blank paper.
5	Optional paper tray	Tray that you can purchase separately to increase the amount of blank paper that your printer can hold.
6	Paper exit tray	Tray that holds the paper as it exits the printer. <b>NOTE:</b> Pull the paper exit tray stop straight out to extend it.

7	PictBridge connector	The connector you use to connect your PictBridge-enabled digital camera or a USB key to your printer.
8	Memory card slots	Slots into which you insert a memory card containing digital pictures. <b>NOTE:</b> The LCD only displays JPG files found on the memory card. To view other image types stored on the memory card, open the Memory Card Manager. For more information, see <a href="#">Using Memory Card Manager</a> .
9	Top cover with integrated ADF exit tray	Top of printer that holds your document or photo flat while you scan it. You can also pick up your original document after it has gone through the ADF here.
10	ADF input tray	Tray that holds original documents. Use it to scan, copy, or fax multiple-page documents.




11	Express Service Code	<ul style="list-style-type: none"> <li>Identify your printer when you use <a href="http://support.dell.com">support.dell.com</a> or contact technical support.</li> <li>Enter the Express Service Code to direct your call when contacting technical support.</li> </ul> <p><b>NOTE:</b> The Express Service Code is not available in all countries.</p>
12	Supplies Reorder Label	To order ink cartridges or paper, visit <a href="http://www.dell.com/supplies">www.dell.com/supplies</a> .








13	FAX connector ( <small>FAX</small> — upper connector)	Slot into which you plug an active telephone line to send and receive faxes. <b>NOTE:</b> Do not connect additional devices to the FAX connector ( <small>FAX</small> — upper connector), and do not connect a DSL (digital subscriber line) or ISDN (integrated services digital network) to the printer without using a digital line filter.
14	PHONE jack connector ( <small>PHONE</small> — bottom connector)	Slot on your printer into which you plug additional devices, such as a data/fax modem, telephone, or answering machine. Remove the blue plug before use. <b>NOTE:</b> If the phone communication is serial in your country (such as Germany, Sweden, Denmark, Austria, Belgium, Italy, France, and Switzerland), you must remove the blue plug from the PHONE jack connector ( <small>PHONE</small> — bottom connector), and then insert the supplied yellow terminator for faxing to work correctly. You will not be able to use this port for additional devices


		in these countries.
15	USB connector	Slot into which you plug the USB cable (sold separately). The other end of the USB cable plugs into your computer.
16	Rear access door (beneath the optional duplex unit)	Part that you have to open to clear paper jams.
17	Optional duplex unit	Part that you can purchase separately to print on both sides of the paper.
18	Optional Dell 966 Internal Wireless/Ethernet Adapter	A networking device that you can purchase separately to set up your printer on a wireless network.
19	Power cord connector	Connects printer power supply to the power outlet using the supplied country-specific power cord.
20	Power supply	Supplies power to the printer.  <b>NOTE:</b> The power supply is removable. When the power supply is removed from the printer, but remains plugged into a power outlet, an LED is illuminated to notify you that power is present.  <b>NOTE:</b> If the power is off when you unplug your printer, the power will be off when you plug it back in.
21	Back cover	Cover that you have to remove to install the Dell 966 Internal Wireless/Ethernet Adapter.



## Understanding the Operator Panel



Number	Use the:	To:
1	LCD display	Display scanning, copying, faxing, and printing options as well as status and error messages.
2	Menu button 	Enter a menu or a submenu.
3	Arrow buttons 	<ul style="list-style-type: none"> <li>Navigate menus and menu items.</li> <li>Decrease/increase the number of copies.</li> <li>Change the selected modes.</li> <li>Navigate photos on a memory card or digital camera.</li> <li>Increase or decrease the values when setting the date and time.</li> </ul>
4	Start button 	Initiate a copy, scan, or fax.
5	Select button 	<ul style="list-style-type: none"> <li>Select a menu item.</li> <li>Select an image to be printed (in Photo mode).</li> <li>Initiate a paper feed by holding the button for three seconds.</li> </ul>
6	Power button 	Turn your printer on or off.  <b>NOTE:</b> Do <i>not</i> unplug your printer from the electrical outlet when not in use. Your

printer needs power to perform regular maintenance on cartridges.

**NOTE:** To conserve power, press and hold the **Power** button  to put your printer on a 1 Watt–Off State. Your printer consumes minimal power at this state.

7	Cancel button 	<ul style="list-style-type: none"><li>• Cancel a scan, print, or copy job in progress.</li><li>• Cancel a copy job (using only the printer), and eject the page.</li><li>• Exit a menu, and return to the default settings.</li></ul>
8	Back button 	<ul style="list-style-type: none"><li>• Return to the previous menu or screen.</li><li>• Save the changes made on a sub-menu temporarily.</li></ul>
9	Keypad	Enter numerical data or text.



# Understanding the Software

- [Using the Dell All-In-One Center](#)
- [Using the Dell Fax Solutions Software](#)
- [Using Printing Preferences](#)
- [Using Memory Card Manager](#)
- [Dell Ink Management System](#)
- [Removing and Reinstalling Software](#)

The printer software includes:

- **Dell All-In-One Center**– Allows you to perform various scan, copy, fax, and print operations with newly scanned and previously saved documents and images.
- **Dell Fax Solutions Software**– Allows you to fax electronic or scanned documents.
- **Printing Preferences**– Allows you to adjust printer settings.
- **Memory Card Manager**– Allows you to display, manage, edit, print, and scan photos from your memory card or USB memory key to your computer.
- **Dell Ink Management System™**– Warns you when your printer is running low on ink.

---

## Using the Dell All-In-One Center



The **Dell All-In-One Center** allows you to:

- Scan, copy, fax, and use productivity tools.
- Select where you want to send the scanned image.
- Select the quantity and color of your copies.
- Access troubleshooting and maintenance information.
- Preview images you want to print or copy.


- Manage photos (copy them to folders, print them, perform creative copying).

 **NOTE:** You cannot scan over a network using the Dell All-In-One Center.

To access the **Dell All-In-One Center**:

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
- b. Click **Dell Printers**.
- c. Click **Dell Photo AIO Printer 966**.

2. Select **Dell All-In-One Center**.


The Dell All-In-One Center includes four main sections:

In this section:	You can:
Preview Now	<ul style="list-style-type: none"> <li>• Select a portion of the preview image to scan or copy.</li> <li>• View an image of what will be printed or copied.</li> </ul>
Scan and Fax	<ul style="list-style-type: none"> <li>• Select the program where you want to send the scanned image.</li> <li>• Select the type of image being scanned.</li> <li>• Select a quality setting for your scan.</li> <li>• Select <b>Scan Now</b>.</li> <li>• Select <b>Fax Now</b>.</li> </ul> <p><b>NOTE:</b> Click <b>See More Scan Settings</b> to view all settings.</p>
Copy	<ul style="list-style-type: none"> <li>• Select the quality and color of your copies.</li> <li>• Select a quality setting for your copies.</li> <li>• Specify the blank paper size.</li> <li>• Specify the size of the original document being copied.</li> <li>• Lighten or darken your copies (this can also be accomplished using the operator panel).</li> <li>• Enlarge or reduce your copies.</li> </ul> <p><b>NOTE:</b> Click <b>See More Copy Settings</b> to view all settings.</p>
Productivity Tools	<ul style="list-style-type: none"> <li>• Fax using PC modem.</li> <li>• E-mail an image or document.</li> <li>• Repeat an image several times on one page.</li> <li>• Enlarge or reduce an image.</li> <li>• Print an image as a multi-page poster.</li> <li>• Save an image on your computer.</li> <li>• Edit text found in a scanned document (Optical Character Recognition).</li> <li>• Modify an image with a photo editor.</li> </ul>

For more information, click **Help** in the **Dell All-In-One Center**.

---

## Using the Dell Fax Solutions Software




The Dell Fax Solutions Software allows you to:

- Send and receive faxes.
- Manage your phonebook.
- Create a cover page.
- View fax history.
- Create a fax report.
- Adjust other fax settings.

To access the Dell Fax Solutions Software:

1. Click **Start® Programs** or **All Programs® Dell PC Fax**.
2. Select **Dell PC Fax**.

For Windows Vista:

- a. Click  **Programs**.
- b. Click **Dell PC Fax**.
- c. Click **Dell PC Fax**.


The Dell Fax Solutions Software has two main sections. When you save the settings, they apply to every fax you send or receive.

In this section:	You can:
Sending Faxes	<ul style="list-style-type: none"> <li>• Send a new fax.</li> <li>• Manage your phonebook.</li> <li>• Set a template for your cover page.</li> <li>• Specify information for the cover page.</li> <li>• View a list of sent and outgoing faxes.</li> <li>• Create a report on sent and outgoing faxes.</li> <li>• Specify if you want to use a fax header.</li> <li>• Specify the number of times the printer attempts to send the fax when a transmission fails.</li> <li>• Specify the driver you want to use in scanning the document you want to fax.</li> </ul>
Receiving Faxes	<ul style="list-style-type: none"> <li>• Specify how you want incoming calls to be answered.</li> <li>• Choose to print incoming faxes.</li> </ul>

- View a list of received and incoming faxes.
- Create a report of received and incoming faxes.
- Set the number of rings before a call is answered.
- Block junk faxes.

You can view more options when you click **Sending Settings** or **Received Settings**. Click on each tab, and change the settings as necessary.

## Using Printing Preferences



You can change your printer settings in Printing Preferences depending on the type of project you want to create.

To access Printing Preferences when a document is open:

1. Click **File® Print**.

The **Print** dialog box opens.

2. Click **Preferences, Properties, Options, or Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

To access Printing Preferences when a document is not open:

1. *In Windows XP*, click **Start® Settings® Control Panel® Printers and Other Hardware® Printers and Faxes**.

*In Windows 2000*, click **Start® Settings® Printers**.

*In Windows Vista*:

- a. Click **Control Panel**.
- b. Click **Hardware and Sound**.
- c. Click **Printers**.


2. Right-click the printer icon, and then select **Printing Preferences**.

**NOTE:** Changes made to the printer settings from the **Printers** folder become the default settings for most programs.

Tab	Options
Print Setup	Quality/Speed — Select <b>Automatic, Draft, Normal, or Photo</b> depending on your desired output quality.

	Draft is the fastest option but should not be selected if you have a photo cartridge installed.
	Media Type — Allows you to set the paper type manually, or have the printer detect the paper type automatically.
	Paper Size — Select the size of your paper.
	Print in black and white — Print your color images in black and white to save the ink in your color cartridge.
	<b>NOTE:</b> You cannot select this setting if you have selected <b>Use Color Cartridge for all Black Printing</b> .
	Borderless — Select the check box if you want to print borderless photos.
	Orientation — Select how the document is arranged on the printed page. You can print using portrait or landscape orientation.
	Envelope — Select the check box if you want to print an envelope. The Paper Size area lists the envelope sizes available for printing.
	Copies — Customize how the printer prints several copies of a single print job: <b>Collated</b> , <b>Normal</b> , or <b>Print Last Page First</b> .
Advanced	2-sided printing — Select this to print on both sides of the paper. Select from <b>Automatic</b> , <b>Manual</b> , or <b>Print Duplex</b> .
	Layout — Select <b>Normal</b> , <b>Banner</b> , <b>Mirror</b> , <b>N-up</b> , <b>Poster</b> , <b>Booklet</b> , or <b>Borderless</b> .
	Automatic Image Sharpening — Automatically select the best image-sharpening level based on image content.
	Dell Customer Experience Improvement Program — Allows you to access information about, and change your status in, the Dell Customer Experience Improvement Program.
	More Options — Allows you to specify <b>Appearance Mode</b> and <b>Complete-A-Print</b> settings. You can also view the paper type that the printer detects.
Maintenance	Install Ink Cartridges
	Clean Ink Cartridges
	Align Ink Cartridges
	Print a Test Page
	Network Support

## Using Memory Card Manager




Memory Card Manager allows you to display, manage, edit, print, and save photos from your memory card or USB

memory key to your computer.


To launch Memory Card Manager:

1. Insert a memory card into the memory card slot or a USB memory key into the PictBridge port on the front of the printer.

 **NOTICE:** Do not remove the memory card or USB key, or touch the printer near the area of the memory card or USB key while actively reading, writing, or printing from these devices. Data corruption can occur.

2. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
3. Select **Memory Card Manager**.

---

## Dell Ink Management System

Each time you print a job, a printing progress screen appears, which shows the progress of the print job as well as the amount of ink remaining and the approximate number of pages remaining in the cartridge. The page counter is hidden during the first 50 pages of cartridge use, until printing habits are learned and a more accurate count can be given. The number of pages remaining changes as a result of the type of print jobs the printer completes.

When your ink cartridge levels are low, a **Low Ink Warning** appears on your screen when you try to print. This warning is displayed every time you print until you install a new ink cartridge. For more information, see [Replacing Ink Cartridges](#).

When one or both of your ink cartridges are empty, the **Reserve Tank** window appears on your screen when you try to print. If you continue printing, the print job may not print as you expect.

If your black ink cartridge is out of ink, you can choose to print black from the color ink cartridge (Process Black) by selecting **Complete-A-Print** before clicking the **Continue Printing** button. If you select **Complete-A-Print** and click **Continue Printing**, Process Black is used for all black printing until the black cartridge is replaced, or the option is cleared from **More Options**, located on the **Advanced** tab of the **Printing Preferences**. The **Reserve Tank** dialog does not display again until after the low ink cartridge has been replaced. The **Complete-A-Print** check box is automatically reset when a new or different cartridge is installed.



If your color ink cartridge is out of ink, you can choose to print color documents in grayscale by selecting **Complete-A-Print** before clicking the **Continue Printing** button. If you select **Complete-A-Print**, and click **Continue Printing**, all color documents will print in black and white until the color cartridge is replaced or the option is cleared from **More Options**, located on the **Advanced** tab of the **Printing Preferences**. The **Reserve Tank** dialog does not display again until after the low ink cartridge has been replaced. The **Complete-A-Print** check box is automatically reset when a new or different cartridge is installed.


---

# Removing and Reinstalling Software


If your printer does not function properly, or communication error messages appear when using your printer, you can remove and reinstall the printer software.

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Click **Uninstall Dell Photo AIO Printer 966**.
  3. Follow the instructions on the screen.
  4. Restart your computer.
  5. Insert the *Drivers and Utilities* CD, and then follow the instructions on the screen.

If the installation screen does not appear:

- a. *In Windows XP*, click **Start® My Computer**.  
*In Windows 2000*, double-click **My Computer** from your desktop.  
*In Windows Vista*, click  **Computer**.
- b. Double-click the **CD-ROM drive** icon, and then double-click **setup.exe**.
- c. When the printer software installation screen appears, click **Personal Installation** or **Network Installation**.
- d. Follow the instructions on your screen to complete the installation.

# Understanding the Operator Panel Menus

[Copy Mode](#)

[Setup Mode](#)

[Photo Mode](#)

[Maintenance Mode](#)

[Print Files Mode](#)

[PictBridge Mode](#)




[Fax Mode](#)




[Bluetooth Mode](#)

[Scan Mode](#)


## Copy Mode

To view or change the **Copy Mode** menu:

1. From the main menu, use the up or down **Arrow** button   to scroll to Copy.
2. Press the **Select** button .

Copy menu item	Settings
Color	<ul style="list-style-type: none"><li>• Color*</li><li>• Black &amp; White</li></ul>
Copies	1–99
Reduce/Enlarge	<ul style="list-style-type: none"><li>• 50%</li><li>• 100%*</li><li>• 200%</li><li>• Custom%</li><li>• Fit to Page</li><li>• 2 x 2 Poster</li><li>• 3 x 3 Poster</li><li>• 4 x 4 Poster</li></ul>
Quality	<ul style="list-style-type: none"><li>• Draft</li><li>• Normal</li><li>• Photo</li><li>• Auto*</li></ul>
Lighter/Darker	Press the left or right <b>Arrow</b> button   to adjust the brightness.
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a> .
Collate	<ul style="list-style-type: none"><li>• Off*</li><li>• On</li></ul>
2-Sided Copies	<ul style="list-style-type: none"><li>• 1-Sided Original, 1-Sided Copy*</li><li>• 1-Sided Original, 2-Sided Copy</li><li>• 2-Sided Original, 1-Sided Copy</li></ul>



	2-Sided Original, 2-Sided Copy
N-up	<ul style="list-style-type: none"> <li>• 1-up*</li> <li>• 2-up</li> <li>• 4-up</li> </ul>
Layout	<ul style="list-style-type: none"> <li>• 1 Per Page*</li> <li>• 4 Per Page</li> <li>• 9 Per Page</li> <li>• 16 Per Page</li> </ul>
Content Type	<ul style="list-style-type: none"> <li>• Text &amp; Graphics*</li> <li>• Photo</li> <li>• Text Only</li> <li>• Line Drawing</li> </ul>
Change Default Settings	Press the <b>Select</b> button  to enter the <b>Copy Default Settings</b> menu. For more information, see <a href="#">Copy Default Settings Menu</a> .
* <b>Factory default setting</b>	


## Photo Mode

Most digital cameras use a memory card to store photos. Your printer supports the following digital media:

- CompactFlash Type I and II
- Memory Stick
- Memory Stick PRO
- Memory Stick Duo (with adapter)
- Microdrive
- Secure Digital
- Mini SD (with adapter)
- MultiMedia Card
- xD-Picture Card



To view or change the Photo mode settings:








1. Insert a memory card. The printer automatically switches to **Photo** mode after the card is read.

 **NOTICE:** Do *not* remove the memory card or touch the printer in the area of the memory card while the light is blinking.


2. Press the **Select** button .





### Photo Card Mode menu

Menu item	Settings
View Slideshow	Press the <b>Select</b> button  to enter the <b>Slideshow</b> menu where you can specify the speed of the slideshow of the photos on the memory card. Highlight the speed you want, and then press the <b>Select</b> button  to

	start the slideshow.
Browse and Print Photos	Press the <b>Select</b> button  to enter <b>Photo Preview</b> mode. Press the left or right <b>Arrow</b> button  to browse photos, or press the <b>Start</b> button  to print photos directly from the preview screen.
Print All Photos	Press the <b>Select</b> button  to enter the <b>Print All Photos</b> screen where you can specify the number of photos printed on a page.  <b>NOTE:</b> Only photos stored in the JPG format can be printed directly from the memory card. If you want to print photos stored on the memory card in a different file format, the photos must be transferred to your computer before printing.
Save Photos to Computer	Press the <b>Select</b> button  to enter <b>Save to PC</b> mode. You can save the photos on the memory card to your computer.
Change Default Settings	Press the <b>Select</b> button  to enter the <b>Photo Default Settings</b> menu. For more information, see <a href="#">Photo Print Settings Menu</a> or <a href="#">Photo Default Settings Menu</a> .
Print Camera Selection	Press the <b>Select</b> button  twice to display the selections that you made using your camera. For more information, see <a href="#">Camera Selection Preview</a> .  <b>NOTE:</b> This item is displayed only if there is a DPOF (Digital Print Order Format) selection in your memory card.









## Photo More Options Menu

The **Photo More Options** menu is accessed by pressing the **Menu** button  while you have selected a photo in the **Photo Preview** mode.

Menu item	Settings
Edit Photo	Press the <b>Select</b> button  to enter the <b>Photo Edit Mode</b> menu. For more information, see <a href="#">Photo Edit Mode Menu</a> .
View Full Screen	Press the <b>Select</b> button  to view the photo full-screen.
Change Print Settings	Press the <b>Select</b> button  to enter the <b>Photo Default Settings</b> menu. For more information, see <a href="#">Photo Print Settings Menu</a> or <a href="#">Photo Default Settings Menu</a> .
Print Preview	Press the <b>Select</b> button  to see a preview of the print job for the selected photo.

## Photo Edit Mode Menu


You can access the **Photo Edit Mode** menu by selecting **Edit Photo** from the **Photo More Options** menu.

Menu item	Settings
Brightness	Press the left or right <b>Arrow</b> button  to specify a darkness setting (middle setting is default).
Rotate	<ul style="list-style-type: none"> <li>Clockwise *</li> <li>Counter Clockwise </li> </ul>
Crop	Press the <b>Select</b> button  , and then press the left or right <b>Arrow</b> button  to choose between <b>Shrink</b> or <b>Expand</b> option  . Press the left or right <b>Arrow</b> button  repeatedly to shrink or expand the area of interest box.
Pan	Press the <b>Select</b> button  , and then use the <b>Arrow</b> buttons until the portion that you want to crop is outside the area of interest box.
Remove Red Eye	<ul style="list-style-type: none"> <li>No*</li> <li>Yes</li> </ul>

\* Factory default setting



## Photo Print Settings Menu or Photo Default Settings Menu



You can access the **Photo Print Settings** menu by selecting **Change Default Settings** from the **Photo Card Mode** main menu or by selecting **Change Print Settings** from the **Photo More Options** menu.

Menu item	Settings
Photo Size	<ul style="list-style-type: none"><li>• Automatic</li></ul> <p><b>NOTE:</b> The setting changes to Automatic if the selected photo size cannot fit onto the layout specified.</p> <ul style="list-style-type: none"><li>• Hagaki</li><li>• L</li><li>• 2L</li><li>• 60x80 mm</li><li>• A6</li><li>• 10x15 cm</li><li>• A5</li><li>• B5</li><li>• A4</li><li>• 13x18 cm</li><li>• 3.5x 5"</li><li>• 4x6"</li><li>• 5x7"</li><li>• 8x10"</li><li>• 8.5x11"</li></ul>
Layout	<ul style="list-style-type: none"><li>• Automatic*</li><li>• Borderless (1 per page)</li><li>• One Photo Centered</li><li>• 1 per page</li><li>• 2 per page</li><li>• 3 per page</li><li>• 4 per page</li><li>• 6 per page</li><li>• 8 per page</li><li>• 16 per page</li></ul>
Quality	<ul style="list-style-type: none"><li>• Auto*</li><li>• Draft</li><li>• Normal</li><li>• Photo</li></ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a> .
* Factory default setting	

## Camera Selection Preview

The **Camera Selection Preview** is accessed by pressing the **Select** button  from the **Print Camera Selections** menu.

To navigate through the camera selections, press the left or right **Arrow** button . Press the **Start** button  to print the photos using the current print settings.


To alter the print settings, press the **Menu** button . From the **Photo Card Mode** menu, scroll to **Change Photo Print Settings**, and press the **Select** button .


## Print Files Mode

Use the **Print Files** mode to print Microsoft® Office files stored on your USB key or memory card. The printer recognizes Microsoft Office files that have filename extensions \*.DOC, \*.XLS, and \*.PPT.



To view or change the **Print Files Mode** menu settings:

1. Make sure that the printer is connected to your computer that has Microsoft Office installed.
2. Insert a memory card into the card slots or a USB key into the PictBridge port.

 **NOTICE:** Do not remove the memory card or USB key, or touch the printer near the area of the memory card or USB key while actively reading, writing, or printing from these devices. Data corruption can occur.




3. Press the up or down **Arrow** button   to scroll to **Print Files**, and then press the **Select** button.

### Print Files Mode Menu


Menu item	Settings
Quality	<ul style="list-style-type: none"><li>• Auto*</li><li>• Draft</li><li>• Normal</li><li>• Photo</li></ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a> .
Change Default Settings	Press the <b>Select</b> button  to enter the <b>Print Files Default Settings</b> menu. For more information, see <a href="#">Print File Default Settings Menu</a> .
* <b>Factory default settings</b>	


## Fax Mode

To view or change the **Fax Mode** menu:

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**.
2. Press the **Select** button .

In order for faxing to function properly:








- The printer's FAX connector (  —upper connector) must be connected to an active telephone line. See [Setting Up the Printer With External Devices](#) for setup details.

 **NOTE:** You cannot fax with a DSL (digital subscriber line) or ISDN (integrated signature digital network) unless you purchase a digital line filter. Contact your Internet Service Provider for more details.

- If you are using the **Dell Fax** to send a fax from within an application, the printer must be connected to a computer with a USB cable.

### Fax Options Menu







Menu item	Action
Fax Number Window	Use the keypad to enter the number to which you want to send a fax. The number displays in the window.

	<b>NOTE:</b> If you have already entered a number on the Fax main menu, then you can also use this window to enter another number and send a broadcast fax.
Phone Book	Press the <b>Select</b> button  to enter the <b>Phone Book</b> menu. For more information, see <a href="#">Phone Book Menu</a> .
Redial History	Press the <b>Select</b> button  to view the redial history. The last five numbers dialed are displayed on the screen.
On Hook Dial	Press the <b>Select</b> button  to enter the <b>On Hook Dial</b> mode.
Delay Sending Fax	Press the <b>Select</b> button  to view the <b>Delay Sending Fax</b> screen. On this screen, use the keypad to specify the time you want the fax to be sent.
Auto Answer	<ul style="list-style-type: none"> <li>• On*</li> <li>• Scheduled—Press the <b>Select</b> button  to enter the <b>Auto Answer Schedule</b> menu. For more information, see <a href="#">Auto Answer Schedule Menu</a>.</li> <li>• Off</li> </ul>
Edit Fax Settings	Press the <b>Select</b> button  to enter the <b>Edit Fax Settings</b> menu. For more information, see <a href="#">Edit Fax Settings Menu</a> .
Fax Setup	Press the <b>Select</b> button  to enter the <b>Fax Setup</b> menu. For more information, see <a href="#">Fax Setup Menu</a> .
<b>* Factory default settings</b>	

## Phone Book Menu

The **Phone Book** menu is accessed by selecting **Phone Book** from the **Fax Mode** menu. You can also access this menu by selecting **Speed Dial Phone Book** from the **Fax Setup** menu.

You can specify up to 99 speed dial numbers—89 individual fax speed dial numbers and 10 group dial entries of up to 30 numbers each.

Menu item	Action
Name Search	Press the <b>Select</b> button  to enter the <b>Name Search</b> menu. For more information, see <a href="#">Name Search Menu</a> .
Phone Number Search	Press the <b>Select</b> button  to enter the <b>Phone Book Search</b> menu. For more information, see <a href="#">Phone Number Search Menu</a> .
Add Entry	Press the <b>Select</b> button  to enter the <b>Phone Book: Add Entry</b> menu. For more information, see <a href="#">Phone Book Add Entry Menu</a> .
Group Search	Press the <b>Select</b> button  to enter the <b>Group Search</b> menu. For more information, see <a href="#">Group Search Menu</a> .
Add Group	Press the <b>Select</b> button  to enter the <b>Phone Book: Add Group</b> menu. For more information, see <a href="#">Phone Book Add Group Menu</a> .
Print List	Press the <b>Select</b> button  to print the phone book stored on your printer.

## Name Search Menu

You can access the **Name Search** menu by selecting **Name Search** from the **Phone Book** menu.


Menu item	Action
Search Criteria Window	Use the keypad to enter a letter. The list automatically scrolls to the appropriate place in the phone book.
Speed dial	The names for the speed dial entries are shown. The number of speed dials listed depends on the number of speed dials you specified on your printer.


## Phone Number Search Menu

You can access the **Phone Book Search** menu by selecting `Phone Number Search` from the **Phone Book** menu.

Menu item	Action
Search Criteria Window	Use the keypad to enter a number. The list automatically scrolls to the appropriate place in the phone book.
Speed dial	The fax numbers for the speed dial entries are shown. The number of speed dials listed depends on the number of speed dials you specified on your printer.

## Phone Book Edit Entry Menu

You can access the **Phone Book: Edit Entry** menu by pressing the **Menu** button  when a speed dial number is highlighted in either the **Phone Number Search** or **Name Search** menus.

Menu item	Action
Name	Use the keypad to edit the name for the contact.
Fax Number	Use the keypad to edit the fax number for the contact.
Speed Dial Number	The speed dial number assigned to this contact is displayed. <b>NOTE:</b> The speed dial number is automatically assigned. You cannot modify the speed dial number.
Delete Entry	Press the <b>Select</b> button  to delete the entry from the phone book.

## Phone Book Add Entry Menu

You can access the **Phone Book: Add Entry** menu by selecting `Add Entry` from the **Phone Book** menu.


Menu item	Action
Name	Use the keypad to enter the name for the contact.
Fax Number	Use the keypad to enter the fax number for the contact.
Speed Dial Number	The lowest available speed dial number is assigned for the contact. <b>NOTE:</b> The speed dial number is automatically assigned. You cannot modify the speed dial number.


## Group Search Menu

You can access the **Group Search** menu by selecting `Group Search` from the **Phone Book** menu.

Menu item	Action
Search Criteria Window	Use the keypad to enter a letter.
Speed dial	The fax numbers for the group entries are shown. The number of groups listed depends on the number of groups specified in your printer.




## Phone Book Edit Group Menu

You can access the **Phone Book: Edit Group** menu by pressing the **Menu** button  when a speed dial number is highlighted in the **Group Search** menu.

Menu item	Action
Name	Use the keypad to edit the name for the group.
Fax Number	Use the keypad to edit the fax numbers for the group.
Speed Dial Number	The speed dial number assigned to this group is displayed. <b>NOTE:</b> The speed dial number is automatically assigned. You cannot modify the speed dial number.
Delete Entry	Press the <b>Select</b> button  to delete the entry from the phone book.

## Phone Book Add Group Menu

You can access the **Phone Book: Add Group** menu by selecting `Add Group` from the **Phone book** menu.

Menu item	Action
Name	Use the keypad to enter a name for the group.
Fax number window	Use the keypad to enter the fax numbers for the group.
Name Search	Press the <b>Select</b> button  to enter the <b>Name Search</b> menu. For more information, see <a href="#">Name Search Menu</a> .
Phone Number Search	Press the <b>Select</b> button  to enter the <b>Phone Book Search</b> menu. For more information, see <a href="#">Phone Number Search Menu</a> .
Redial History	Press the <b>Select</b> button  to display the redial history. The last five numbers dialed are displayed on the screen.
Speed Dial Number	The lowest available speed dial number is assigned to this group. <b>NOTE:</b> The speed dial number is automatically assigned. You cannot modify the speed dial number.

## Auto Answer Schedule Menu

You can access the **Auto Answer Schedule** menu by selecting `Scheduled` from the `Auto Answer` option on the **Fax Mode** menu or by selecting `Auto Answer Schedule` from the **Ringing and Answering** menu.


When **Auto Answer** is turned on, the fax machine answers incoming faxes without user intervention. When **Auto Answer** is turned off, incoming faxes must be answered manually.

Menu item	Action
Current Time	Displays the current time.
Turn Auto Answer On at	Use the keypad to specify the time when you would like to turn <b>Auto Answer</b> on.
Turn Auto Answer Off at	Use the keypad to specify the time when you would like to turn <b>Auto Answer</b> off.



## Edit Fax Settings Menu


You can access the **Edit Fax Settings** menu by selecting `Edit Fax Settings` from the **Fax Mode** menu.

The settings changed on this menu are temporary and will only be applicable to the fax job that you are sending at the time. They will not apply to your subsequent faxes.

Menu item	Action
Cover Page	<ul style="list-style-type: none"><li>• Yes</li><li>• No*</li></ul>
Color	<ul style="list-style-type: none"><li>• Black &amp; White*</li><li>• Color</li></ul>
Quality	<ul style="list-style-type: none"><li>• Standard*</li><li>• Fine</li><li>• Superfine</li><li>• Ultrafine</li></ul>
Lighter/Darker	Press the left or right <b>Arrow</b> button  to specify a darkness setting (middle setting is default).
<b>* Factory default settings</b>	







## Cover Page Menu

You can access the **Cover Page** menu by pressing the **Menu** button  when **Cover Page** is highlighted in the **Edit Fax Settings** menu. From the **Cover Page** menu, press the **Menu** button  to edit the contents of your cover page.

Menu item	Action
From #	<ul style="list-style-type: none"> <li>• Leave Blank*</li> <li>• From #1</li> <li>• From #2</li> <li>• From #3</li> <li>• From #4</li> <li>• From #5</li> </ul> <p><b>NOTE:</b> To assign or change information in the <b>From</b> menu, scroll to the option that you want to edit, and then press the <b>Menu</b> button . Use the keypad to enter information about the sender.</p>
Your Name	Displays the name of the sender.
Your Phone #	Displays the phone number of the sender.
Your Fax #	Use the keypad to enter your fax number.
Priority	<ul style="list-style-type: none"> <li>• None*</li> <li>• FYI</li> <li>• Please Reply</li> <li>• Urgent</li> </ul>
Message	Use the keypad to enter your message for the recipient.
* <b>Factory default settings</b>	

## Fax Setup Menu

You can access the **Fax Setup** menu by selecting **Fax Setup** from the **Fax Mode** menu or by selecting **Change Fax Default Settings** from the **Setup** menu. The settings made on this menu apply to all fax jobs that you will send or receive, unless you restore the settings to factory defaults.






Menu item	Action
Speed Dial Phone Book	Press the <b>Select</b> button  to enter the <b>Phone Book</b> menu. For more information, see <a href="#">Phone Book Menu</a> .
History and Reports	Press the <b>Select</b> button  to enter the <b>History and Reports</b> menu. For more information, see <a href="#">History and Reports Menu</a> .
Ringing and Answering	Press the <b>Select</b> button  to enter the <b>Ringing and Answering</b> menu. For more information, see <a href="#">Ringing and Answering Menu</a> .
Fax Printing	Press the <b>Select</b> button  to enter the <b>Fax Printing</b> menu. For more information, see <a href="#">Fax Printing Menu</a> .
Dialing and Sending	Press the <b>Select</b> button  to enter the <b>Dialing and Sending</b> menu. For more information, see <a href="#">Dialing and Sending Menu</a> .
Fax Blocking	Press the <b>Select</b> button  to enter the <b>Fax Blocking</b> menu. For more information, see <a href="#">Fax Blocking Menu</a> .

## History and Reports Menu


You can access the **History and Reports** menu by selecting **History and Reports** from the **Fax Setup** menu.





Menu item	Action
-----------	--------



View History on Screen	Press the <b>Select</b> button  to display the fax history on the screen.
Print Sent History	Press the <b>Select</b> button  to print a history of sent faxes.
Print Received History	Press the <b>Select</b> button  to print a history of received faxes.
View Pending Faxes	Press the <b>Select</b> button  to display information about pending faxes on the screen.
Report	<ul style="list-style-type: none"> <li>• Manual Print*</li> <li>• Every 40 Jobs</li> </ul>
Print Fax Activity History	Press the <b>Select</b> button  to print a history of your fax activity.
Confirmation	<ul style="list-style-type: none"> <li>• Off</li> <li>• On Error*</li> <li>• For All</li> </ul>
<b>* Factory default settings</b>	


## Fax History More Options Menu



You can access the **Fax History More Options** menu by highlighting one of the numbers shown on the **Fax History** screen and pressing the **Select** button .

Menu item	Action
Redial This Number	Press the <b>Select</b> button  to enter the <b>Fax Mode</b> menu with the selected number displayed in the Fax Number Window.
Add Number to Phone Book	Press the <b>Select</b> button  to enter the <b>Phone Book: Add Entry</b> menu with the fax number field automatically populated with the current fax number.
Add Number to Blocked Faxes	Press the <b>Select</b> button  to enter the <b>Blocked Fax: Add Entry</b> menu with the fax number field automatically populated with the current fax number.
Clear All History	Press the <b>Select</b> button  to clear the fax activity log.

## Ringling and Answering Menu


You can access the **Ringling and Answering** menu by selecting **Ringling** and **Answering** from the **Fax Setup** menu.

Menu item	Action
Ring Volume	<ul style="list-style-type: none"> <li>• Off</li> <li>• Low*</li> <li>• High</li> </ul>
Pick-up On	<ul style="list-style-type: none"> <li>• 1st Ring</li> <li>• 2nd Ring</li> <li>• 3rd Ring*</li> <li>• 5th Ring</li> </ul>
Distinctive Ring	<ul style="list-style-type: none"> <li>• Any Ring*</li> <li>• Single Ring</li> <li>• Double Ring</li> <li>• Triple Ring</li> </ul>
Auto Answer Schedule	Press the <b>Select</b> button  to enter the <b>Auto Answer Schedule</b> menu. For more information, see <a href="#">Auto Answer Schedule Menu</a> .

Fax Forward	<ul style="list-style-type: none"> <li>• Off*</li> <li>• Forward</li> <li>• Print &amp; Forward</li> </ul>
Manual Pickup Key Code	<p>Press the <b>Select</b> button  to display the <b>Pickup Code</b> menu. To change the code, use the keypad to specify a new code, and then press the <b>Select</b> button .</p> <p><b>NOTE:</b> The default code is <b>DELL# (3355#)</b>.</p>
Caller ID Pattern	<ul style="list-style-type: none"> <li>• Pattern 1 (FSK)*</li> <li>• Pattern 2 (DTMF)</li> </ul> <p><b>NOTE:</b> The Caller ID detection pattern is determined by the country or region you selected during initial setup. If phones in your country use two detection patterns, call your telecommunications company to know which pattern it subscribes to.</p>
* Factory default setting	

## Fax Printing Menu



You can access the **Fax Printing** menu by selecting Fax Printing from the **Fax Setup** menu.

Menu item	Action
If Too Big	<ul style="list-style-type: none"> <li>• Fit to Page*</li> <li>• Use Two Pages</li> </ul>
Fax Footer	<ul style="list-style-type: none"> <li>• On*</li> <li>• Off</li> </ul>
2-Sided Print	<ul style="list-style-type: none"> <li>• 1 Sided Print*</li> <li>• 2 Sided Print</li> </ul>
Paper Handling	<p>Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a>.</p>
* Factory default settings	

## Dialing and Sending Menu

You can access the **Dialing and Sending** menu by selecting Dialing and Sending from the **Fax Setup** menu.

Menu item	Action
Your Fax Number	Use the keypad to enter your fax number. This number is shown on the cover page of outgoing faxes.
Your Fax Name	Use the keypad to specify the name for the printer. This is the name shown on the fax header of outgoing faxes.
Cover Page	<ul style="list-style-type: none"> <li>• No*</li> <li>• Yes</li> </ul>
Color	<ul style="list-style-type: none"> <li>• Black &amp; White*</li> <li>• Color</li> </ul>
Quality	<ul style="list-style-type: none"> <li>• Standard*</li> <li>• Fine</li> </ul>





	<ul style="list-style-type: none"> <li>• Superfine</li> <li>• Ultrafine</li> </ul>
Dial Method	<ul style="list-style-type: none"> <li>• Touch-tone*</li> <li>• Pulse</li> <li>• Behind PBX (Dial Tone Detect Off)</li> </ul>
Redial Time	<ul style="list-style-type: none"> <li>• 1 Minute</li> <li>• 2 Minutes*</li> <li>• 3 Minutes</li> <li>• 4 Minutes</li> <li>• 5 Minutes</li> <li>• 6 Minutes</li> <li>• 7 Minutes</li> <li>• 8 Minutes</li> </ul>
Redial Tries	<ul style="list-style-type: none"> <li>• 0 Times</li> <li>• 1 Time</li> <li>• 2 Times</li> <li>• 3 Times*</li> <li>• 4 Times</li> <li>• 5 Times</li> </ul>
Dial Prefix	<ul style="list-style-type: none"> <li>• None*—Press the <b>Select</b> button  to change defaults.</li> <li>• Create—Press the <b>Select</b> button  to create a prefix if one is necessary to obtain an outside line.</li> </ul>
Dial Volume	<ul style="list-style-type: none"> <li>• Off</li> <li>• Low*</li> <li>• High</li> </ul>
Scan	<ul style="list-style-type: none"> <li>• Before Dial*—the fax is scanned to memory before dialing the fax number.</li> <li>• After Dial—the fax number is dialed, communication with receiving fax is established, and then the fax is scanned.</li> </ul>
Max Send Speed	<ul style="list-style-type: none"> <li>• 33,600 bps*</li> <li>• 31,200 bps</li> <li>• 28,800 bps</li> <li>• 26,400 bps</li> <li>• 24,000 bps</li> <li>• 21,600 bps</li> <li>• 19,200 bps</li> <li>• 16,800 bps</li> <li>• 14,400 bps</li> <li>• 12,000 bps</li> <li>• 9,600 bps</li> <li>• 7,200 bps</li> <li>• 4,800 bps</li> <li>• 2,400 bps</li> </ul>
Auto Fax Conversion	<ul style="list-style-type: none"> <li>• On*—the fax is automatically converted to be compatible with the receiving fax machine regardless of the send settings.</li> <li>• Off—an unsupported fax error is given if there is a mismatch between send settings and those on the receiving fax machine.</li> </ul>
Error Correction	<ul style="list-style-type: none"> <li>• On*</li> <li>• Off</li> </ul>

\* Factory default settings

## Fax Blocking Menu

You can access the **Fax Blocking** menu by selecting Fax Blocking from the **Fax Setup** menu.

When fax blocking is on, calls received from fax machines that have a caller ID that matches one specified on the block list or have blocked their caller ID are disconnected.

Menu item	Action
Block List	<ul style="list-style-type: none"><li>• Off*</li><li>• On</li></ul>
Block No-ID	<ul style="list-style-type: none"><li>• Off*</li><li>• On</li></ul>
Blocked Fax Name Search	Press the <b>Select</b> button  to enter the <b>Blocked Fax Name Search</b> menu. For more information, see <a href="#">Blocked Fax Name Search Menu</a> .
Blocked Fax Entry Number Search	Press the <b>Select</b> button  to enter the <b>Blocked Fax Number Search</b> menu. For more information, see <a href="#">Blocked Fax Entry Number Search Menu</a> .
Blocked Fax Add Entry	Press the <b>Select</b> button  to enter the <b>Blocked Fax: Add Entry</b> menu. For more information, see <a href="#">Blocked Fax Add Entry Menu</a> .
Print Blocked Fax List	Press the <b>Select</b> button  to print the contents of the blocked fax list.
* Factory default settings	

## Blocked Fax Name Search Menu

You can access the **Blocked Fax Name Search** menu by selecting Blocked Fax Name Search from the **Fax Blocking** menu.


Menu item	Action
Search Window Criteria	Use the keypad to enter a letter. The list automatically scrolls to the appropriate place in the phone book.
Blocked Fax List Value	The contact being blocked is displayed. The number of contacts on the list depends on the number of fax numbers you have blocked.

## Blocked Fax Entry Number Search Menu


You can access the **Blocked Fax Entry Number Search** menu by selecting Blocked Fax Entry Number Search from the **Fax Blocking** menu.

Menu item	Action
Search Criteria Window	Use the keypad to enter a number. The list automatically scrolls to the appropriate place in the phone book.
Blocked Fax List Number	The number assigned to the fax number being blocked is displayed. The number assigned to the blocked fax list depends on the number of fax numbers you have blocked.

## Blocked Fax Edit Entry Menu

You can access the **Blocked Fax Edit Entry** menu by pressing the **Menu** button  while a number is highlighted in the **Blocked Fax Name Search** or **Blocked Fax Entry Number Search** menus.

Menu item	Action
Name	Use the keypad to edit the name for the contact.

Fax Number	Use the keypad to edit the fax number for the contact.
Blocked Fax #	A number is assigned to this blocked fax number. <b>NOTE:</b> The number is automatically assigned. You cannot modify the assigned number.
Delete Entry	Press the <b>Select</b> button  to delete this entry from the blocked fax list.

## Blocked Fax Add Entry Menu





You can access the **Blocked Fax Add Entry** menu by selecting **Blocked Fax Add Entry** from the **Fax Blocking** menu.

You can add up to 50 numbers to the blocked fax list.

Menu item	Action
Name	Use the keypad to edit the name for the contact.
Fax Number	Use the keypad to edit the fax number for the contact. It is required to enter a number to add an entry from this menu.
Blocked Fax #	A number is assigned to this blocked fax number. <b>NOTE:</b> The number is automatically assigned. You cannot modify the assigned number.


## Scan Mode

To view or change the **Scan Mode** menu settings:

1. Ensure your printer and computer are connected via a USB cable.
2. From the main menu, press the up or down **Arrow** button   to scroll to **Scan**.
3. Press the **Select** button .
4. If your computer is connected to a network, select a host from the **Host Selection** screen, and enter a four-digit PIN number, if necessary, for the selected host.
5. Press the **Select** button .




## Scan Mode Menu

Menu item	Settings
Scan To	<ul style="list-style-type: none"> <li>• Preview</li> <li>• Email</li> <li>• File</li> <li>• software installed on your computer</li> </ul>
Color	<ul style="list-style-type: none"> <li>• Color*</li> <li>• Black &amp; White</li> </ul>
Quality	<ul style="list-style-type: none"> <li>• Automatic*</li> <li>• 150 dpi</li> <li>• 300 dpi</li> <li>• 600 dpi</li> </ul>
Original Size	<ul style="list-style-type: none"> <li>• Auto Detect*</li> <li>• L</li> <li>• 2L</li> <li>• A6</li> </ul>












	<ul style="list-style-type: none"> <li>• A5</li> <li>• B5</li> <li>• A4</li> <li>• Wallet</li> <li>• 3x5"</li> <li>• 4x6"</li> <li>• 5x7"</li> <li>• 8x10"</li> <li>• 8.5x11"</li> </ul>
Change Default Settings	Press the <b>Select</b> button  to enter the <b>Scan Default Settings</b> menu. For more information, see <a href="#">Scan Default Settings Menu</a> .
* <b>Factory default settings</b>	

## Setup Mode

To access the **Setup** menu:

1. From the main menu, press the up or down **Arrow** button   to scroll to Setup.
2. Press the **Select** button .

### Setup Mode Menu

Menu item	Action
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
Change Printer Default Settings	Press the <b>Select</b> button  to enter the <b>Printer Default Settings</b> menu. For more information, see <a href="#">Printer Default Settings Menu</a> .
Change Copy Default Settings	Press the <b>Select</b> button  to enter the <b>Copy Default Settings</b> menu. For more information, see <a href="#">Copy Default Settings Menu</a> .
Change Photo Default Settings	Press the <b>Select</b> button  to enter the <b>Photo Default Settings</b> menu. For more information, see <a href="#">Photo Default Settings Menu</a> .
Change Print File Default Settings	Press the <b>Select</b> button  to enter the <b>Print Files Default Settings</b> menu. For more information, see <a href="#">Print File Default Settings Menu</a> .
Change Fax Default Settings	Press the <b>Select</b> button  to enter the <b>Fax Setup</b> menu. For more information, see <a href="#">Fax Setup Menu</a> .
Change Scan Default Settings	Press the <b>Select</b> button  to enter the <b>Scan Default Settings</b> menu. For more information, see <a href="#">Scan Default Settings Menu</a> .
Change Bluetooth Default Settings	Press the <b>Select</b> button  to enter the <b>Bluetooth Default Settings</b> menu. For more information, see <a href="#">Bluetooth Default Settings Menu</a> .
Change PictBridge Default Settings	Press the <b>Select</b> button  to enter the <b>PictBridge Default Settings</b> menu. For more information, see <a href="#">PictBridge Default Settings Menu</a> .
Print Settings List	Press the <b>Select</b> button  to print a list of the options that were set using the operator panel.
Network Setup	Press the <b>Select</b> button  to enter the <b>Network Setup</b> menu. For more information, see <a href="#">Network Setup Menu</a> .

### Paper Handling Menu

You can select the size and type of the blank paper loaded in the input tray from the **Paper Handling** menu. If you have an optional input tray, you can also specify the paper source.

You can view or change the **Paper Handling** menu by selecting Paper Handling from the **Setup** menu, **Copy Mode**

menu, **Photo Print Settings** menu, **Photo Default Settings** menu, **Print File Default Settings** menu, **Fax Printing** menu, or **Bluetooth Default Settings** menu.

### Paper Handling menu for printer with one input tray

Menu item	Settings
Size	<ul style="list-style-type: none"> <li>• Hagaki</li> <li>• L</li> <li>• 2L</li> <li>• A6</li> <li>• 10x15 cm</li> <li>• A5</li> <li>• 13x18 cm</li> <li>• B5</li> <li>• A4</li> <li>• 3x5</li> <li>• 4x6</li> <li>• 5x7</li> <li>• 8.5x11</li> <li>• 8.5x14</li> </ul> <p><b>NOTE:</b> Size is determined by the country you selected during initial setup. Changing size from any menu changes the option selected in all other menus.</p>
Type	<ul style="list-style-type: none"> <li>• Auto Detect*</li> <li>• Plain</li> <li>• Matte</li> <li>• Photo</li> <li>• Transparency</li> </ul>
* Factory default setting	





### Paper Handling menu for printer with two input trays

Menu item	Settings
Size-Tray 1	<ul style="list-style-type: none"> <li>• Hagaki</li> <li>• L</li> <li>• 2L</li> <li>• A6</li> <li>• A5</li> <li>• B5</li> <li>• A4</li> <li>• 3x5"</li> <li>• 4x6"</li> <li>• 8.5x11"</li> <li>• 8.5x14"</li> </ul> <p><b>NOTE:</b> Size is determined by the country code you selected during initial setup. Changing size from any menu changes the option selected in all other menus.</p>
Type-Tray 1	<ul style="list-style-type: none"> <li>• Auto Detect*</li> <li>• Plain</li> <li>• Matte</li> <li>• Photo</li> <li>• Transparency</li> </ul>
Size-Tray 2	<ul style="list-style-type: none"> <li>• A4</li> <li>• 8.5x11"</li> <li>• 8.5x14"</li> </ul> <p><b>NOTE:</b> Tray 1 and Tray 2 have the same default paper size during the initial setup. You can load different sizes of paper into these two trays and choose the corresponding paper size options for them.</p>

Type-Tray 2	<ul style="list-style-type: none"> <li>• Auto Detect*</li> <li>• Plain</li> <li>• Matte</li> <li>• Photo</li> <li>• Transparency</li> </ul>
Tray Linking	<ul style="list-style-type: none"> <li>• Off*</li> <li>• Auto</li> </ul> <p>For more information, see <a href="#">Understanding Tray Linking</a>.</p>
Copy Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> </ul>
Photo Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> </ul>
Print Files Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> </ul>
Fax Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> <li>• Auto</li> </ul> <p><b>NOTE:</b> Select <b>Auto</b> if you want the printer to pick from the tray containing the paper that matches the size of the incoming fax. You also need to specify the correct paper size for both trays.</p>
PictBridge Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> </ul>
Bluetooth Source	<ul style="list-style-type: none"> <li>• Tray1*</li> <li>• Tray2</li> </ul>
* <b>Factory default setting</b>	

## Printer Default Settings Menu

You can view or change the **Printer Default Settings** by selecting `Change Printer Default Settings` from the **Setup** menu.



Menu item	Settings
Set Date and Time	Press the <b>Select</b> button  to enter the <b>Set Date and Time</b> menu. For more information, see <a href="#">Set Date and Time Menu</a> .
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
Language	Press the left or right <b>Arrow</b> button  to scroll through the language options.
Country	Press the left or right <b>Arrow</b> button  to scroll through the country options.
Key Press Tone	<ul style="list-style-type: none"> <li>• Off</li> <li>• On*</li> </ul>
Power Save	<ul style="list-style-type: none"> <li>• Now</li> <li>• After 10 min</li> <li>• After 30 min*</li> </ul>



	<ul style="list-style-type: none"> <li>After 60 min</li> <li>Never</li> </ul>
Block Host Settings	<ul style="list-style-type: none"> <li>Off*</li> <li>On</li> </ul> <p><b>NOTE:</b> Set <b>Block Host Settings</b> to On if you want to prevent other users from changing the settings of your printer.</p>
Speaker Volume	<ul style="list-style-type: none"> <li>Off</li> <li>Low*</li> <li>High</li> </ul>
* Factory default setting	


## Set Date and Time Menu

You can view or change the **Set Date and Time** menu by selecting **Set Date and Time** from the **Printer Default Settings** menu.

Menu item	Action
Current Time	Use the keypad to enter the current time. Press the left or right <b>Arrow</b> button  to move to the next entry field.
Current Date	Use the keypad to enter the current date. Press the left or right <b>Arrow</b> button  to move to the next entry field.


## Copy Default Settings Menu

You can view or change the **Copy Default Settings** by selecting **Copy Default Settings** from the **Setup** menu or by selecting **Change Default Settings** from the **Copy Mode** menu.

Menu item	Settings
Color	<ul style="list-style-type: none"> <li>Color*</li> <li>Black &amp; White</li> </ul>
Quality	<ul style="list-style-type: none"> <li>Auto*</li> <li>Draft</li> <li>Normal</li> <li>Photo</li> </ul>
Content Type	<ul style="list-style-type: none"> <li>Text &amp; Graphics*</li> <li>Photo</li> <li>Text Only</li> <li>Line Drawing</li> </ul>
2-sided copies	<ul style="list-style-type: none"> <li>1-Sided Original, 1-Sided Copy*</li> <li>1-Sided Original, 2-Sided Copy</li> <li>2-Sided Original, 1-Sided Copy</li> <li>2-Sided Original, 2-Sided Copy</li> </ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
* Factory default setting	


## Photo Default Settings Menu

You can view or change the **Photo Default Settings** by selecting Change Photo Default Settings from the **Setup** menu or by selecting Change Default Settings from the **Photo Card Mode** menu. The settings made on this menu apply to all photos that will be printed, unless you restore the settings to factory defaults.

Menu item	Settings
Photo Size	<ul style="list-style-type: none"> <li>• Hagaki</li> <li>• L</li> <li>• 2L</li> <li>• 60x80 mm</li> <li>• A6</li> <li>• 10x15 cm</li> <li>• A5</li> <li>• B5</li> <li>• A4</li> <li>• 13x18 cm</li> <li>• 3.5x 5"</li> <li>• 4x6"</li> <li>• 5x7"</li> <li>• 8x10"</li> <li>• 8.5x11"</li> </ul>
Layout	<ul style="list-style-type: none"> <li>• Automatic*</li> <li>• Borderless (1 per page)</li> <li>• One Photo Centered</li> <li>• 1 per page</li> <li>• 2 per page</li> <li>• 3 per page</li> <li>• 4 per page</li> <li>• 6 per page</li> <li>• 8 per page</li> <li>• 16 per page</li> </ul>
Quality	<ul style="list-style-type: none"> <li>• Auto*</li> <li>• Draft</li> <li>• Normal</li> <li>• Photo</li> </ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
<b>* Factory default setting</b>	

## Print File Default Settings Menu

You can view or change the **Print File Default Settings** by selecting Change Print File Default Settings from the **Setup** menu or by selecting Change Default Settings from the **Print Files Mode** menu.

Menu item	Settings
Quality	<ul style="list-style-type: none"> <li>• Auto*</li> <li>• Draft</li> <li>• Normal</li> <li>• Photo</li> </ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
<b>* Factory default setting</b>	

## Fax Setup Menu

You can access the **Fax Setup** menu by selecting Change Fax Default Settings from the **Setup** menu or by selecting

Fax Setup from the **Fax Mode** menu. For more information, see [Fax Setup Menu](#).

## Scan Default Settings Menu

You can view or change the **Scan Default Settings** by selecting Change Scan Default Settings from the **Setup** menu or by selecting Change Default Settings from the **Scan Mode** menu.

Menu item	Settings
Color	<ul style="list-style-type: none"><li>• Color*</li><li>• Black &amp; White</li></ul>
Quality	<ul style="list-style-type: none"><li>• Automatic*</li><li>• 150 dpi</li><li>• 300 dpi</li><li>• 600 dpi</li></ul>
Original Size	<ul style="list-style-type: none"><li>• Auto Detect*</li><li>• L</li><li>• 2L</li><li>• A6</li><li>• A5</li><li>• B5</li><li>• A4</li><li>• Wallet</li><li>• 3x5</li><li>• 4x6</li><li>• 5x7</li><li>• 8x10</li><li>• 8.5x11</li></ul>
* Factory default setting	


## Bluetooth Default Settings Menu

You can view or change the **Bluetooth Default Settings** by selecting Change Bluetooth Default Settings from the **Setup** menu. For more information, see [Bluetooth Mode](#).

## PictBridge Default Settings Menu







You can view or change the **PictBridge Default Settings** by selecting Change PictBridge Default Settings from the **Setup** menu.

Menu item	Settings
Photo Size	<ul style="list-style-type: none"><li>• Hagaki</li><li>• L</li><li>• 2L</li><li>• 60x80 mm</li><li>• A6</li><li>• 10x15 cm</li><li>• A5</li><li>• B5</li><li>• A4</li><li>• 13x18 cm</li><li>• 3.5x 5"</li><li>• 4x6"</li><li>• 5x7"</li><li>• 8x10"</li><li>• 8.5x11"</li></ul>
Layout	<ul style="list-style-type: none"><li>• Automatic*</li><li>• Borderless (1 per page)</li></ul>

	<p>One Photo Centered</p> <ul style="list-style-type: none"> <li>• 1 per page</li> <li>• 2 per page</li> <li>• 3 per page</li> <li>• 4 per page</li> <li>• 6 per page</li> <li>• 8 per page</li> <li>• 16 per page</li> </ul>
Quality	<ul style="list-style-type: none"> <li>• Auto*</li> <li>• Draft</li> <li>• Normal</li> <li>• Photo</li> </ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu. For more information, see <a href="#">Paper Handling Menu</a> .
<b>* Factory default setting</b>	



## Network Setup Menu

You can access **Setup** menu by selecting *Network Setup* from the **Setup** menu.

Menu item	Settings
Print Network Setup Page	Press the <b>Select</b> button  to print a list of network settings.
Wireless Menu	Press the <b>Select</b> button  to enter the <b>Wireless Setup Menu</b> . For more information, see <a href="#">Wireless Menu</a> .
TCP/IP	Press the <b>Select</b> button  to enter the <b>TCP/IP Menu</b> . For more information, see <a href="#">TCP/IP Menu</a> .
Network Time Menu	<p>Press the <b>Select</b> button  to enter <b>Network Time Menu</b>.</p> <p>From the Network Time Menu, press the left or right <b>Arrow</b> button  to enable or disable the <b>Time Server</b>, and then press the <b>Back</b> button  to save the settings.</p> <p><b>NOTE:</b> When <b>Time Server</b> is enabled, the wireless Ethernet card updates the printer's time once a day or every time the printer is powered on.</p>
Active Network	<ul style="list-style-type: none"> <li>• Auto</li> <li>• Ethernet 10/100</li> <li>• Wireless 802.11b/g</li> </ul>
<b>* Factory default setting</b>	













## Wireless Menu

You can view or change the settings in the **Wireless Setup Menu** by selecting *Wireless Menu* from the **Network Setup** menu.

Menu item	Settings
Print Wireless Setup Page	Press the <b>Select</b> button  to print a list of wireless network settings.
Network Name	<p>Reflects the current SSID being used.</p> <p><b>NOTE:</b> You cannot change the value of Network Name.</p>
Wireless Signal Strength	Press the <b>Select</b> button  to view the current signal strength.
<b>* Factory default setting</b>	




## TCP/IP Menu

You can view or change the settings in the **TCP/IP Menu** by selecting **TCP/IP** from the **Network Setup** menu.






Menu item	Settings
Enable DHCP	<ul style="list-style-type: none"> <li>• Yes*</li> <li>• No</li> </ul> <p><b>NOTE:</b> You cannot change or set an IP Address, IP Netmask, and IP Gateway if DHCP is enabled.</p>
Set IP Address	<p>Press the <b>Select</b> button  to enter the <b>Set IP Address</b> menu.</p> <p>From the <b>Set IP Address</b> menu, use the keypad to enter an IP address. Press the right <b>Arrow</b> button  to enter a set of numbers in the next field, or press the left <b>Arrow</b> button  to erase an entry. Press the <b>Back</b> button  to save the settings.</p> <p><b>NOTE:</b> The IP address cannot be changed if DHCP is enabled.</p>
Set IP Netmask	<p>Press the <b>Select</b> button  to enter the <b>Set IP Netmask</b> menu.</p> <p>From the <b>Set IP Netmask</b> menu, use the keypad to enter an IP address. Press the right <b>Arrow</b> button  to enter a set of numbers in the next field, or press the left <b>Arrow</b> button  to erase an entry. Press the <b>Back</b> button  to save the settings.</p> <p><b>NOTE:</b> The IP address cannot be changed if DHCP is enabled.</p>
Set IP Gateway	<p>Press the <b>Select</b> button  to enter the <b>Set IP Gateway</b> menu.</p> <p>From the <b>Set IP Gateway</b> menu, use the keypad to enter an IP address. Press the right <b>Arrow</b> button  to enter a set of numbers in the next field, or press the left <b>Arrow</b> button  to erase an entry. Press the <b>Back</b> button  to save the settings.</p> <p><b>NOTE:</b> The IP address cannot be changed if DHCP is enabled.</p>
* <b>Factory default setting</b>	

## Maintenance Mode


To access **Maintenance** mode options:

1. From the main menu, press the up or down **Arrow** button   to scroll to Maintenance.
2. Press the **Select** button .

### Maintenance Mode Menu

Menu item	Action
View Ink Levels	Press the <b>Select</b> button  to display the current ink level for each cartridge on the screen.
Clean Cartridges	Press the <b>Select</b> button  to clean the ink cartridges.
Align Cartridges	Press the <b>Select</b> button  to align the ink cartridges.
Change Print Cartridges	Press the <b>Select</b> button  to view steps detailing how to change ink cartridges.
Print Test Page	Press the <b>Select</b> button  to print a test page.
Call Diagnostics	<ul style="list-style-type: none"> <li>• Off*</li> <li>• Audio on</li> <li>• Print T30 Signals Report</li> <li>• Both Audio and Report</li> </ul>


Reset Defaults

Press the **Select** button  to reset all settings to factory default settings.


\* **Factory default setting**

## PictBridge Mode

Your printer automatically switches to **PictBridge** mode when you connect a PictBridge-enabled camera. You can print pictures using the controls of the camera. For more information, see [Printing Photos From a PictBridge-Enabled Camera](#).


To view or change the **PictBridge** default print settings, press the **Menu** button .

### PictBridge Default Print Settings Menu







Menu item	Settings
Photo Size	<ul style="list-style-type: none"><li>• Hagaki</li><li>• L</li><li>• 2L</li><li>• 60x80mm</li><li>• A6</li><li>• 10x15cm</li><li>• A5</li><li>• B5</li><li>• A4</li><li>• 13x18cm</li><li>• 3.5x5"</li><li>• 4x6"</li><li>• 5x7"</li><li>• 8x10"</li><li>• 8.5x11"</li></ul> <p><b>NOTE:</b> Photo Size is determined by the country or region you selected during initial setup.</p>
Layout	<ul style="list-style-type: none"><li>• Automatic*</li><li>• Borderless (1 per page)</li><li>• One Photo Centered</li><li>• 1 per page</li><li>• 2 per page</li><li>• 3 per page</li><li>• 4 per page</li><li>• 6 per page</li><li>• 8 per page</li><li>• 16 per page</li></ul>
Quality	<ul style="list-style-type: none"><li>• Auto*</li><li>• Draft</li><li>• Normal</li><li>• Photo</li></ul>
Paper Handling	Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a> .
* <b>Factory default setting</b>	

## Bluetooth Mode



To print from an external Bluetooth-enabled device, you must attach a USB Bluetooth adapter to the PictBridge port. The

Bluetooth icon  appears on the display once the USB Bluetooth adapter is active.

To view or change **Bluetooth Default Settings**:


1. Press the up or down **Arrow** button   to scroll to Setup, and then press the **Select** button .
2. Press the up or down **Arrow** button   to scroll to Change Bluetooth Default Settings, and then press the **Select** button .

## Bluetooth Default Settings Menu

Menu item	Settings
Bluetooth Enabled	<ul style="list-style-type: none"> <li>• On*</li> <li>• Off</li> </ul> <p><b>NOTE:</b> When <b>Bluetooth Enable</b> is set to On, the printer accepts Bluetooth connections and allows the USB Bluetooth adapter to communicate with other Bluetooth-enabled devices.</p>
Discovery Mode	<ul style="list-style-type: none"> <li>• On*</li> <li>• Off</li> </ul> <p><b>NOTE:</b> Set the <b>Discovery Mode</b> to On if you want other Bluetooth-enabled devices to detect the USB Bluetooth adapter attached to your printer.</p>
Security	<ul style="list-style-type: none"> <li>• Low*</li> <li>• High</li> </ul>
Pass Key	<p>Specify a pass key. Any external Bluetooth-enabled device needs to enter this passkey before it sends a print job.</p> <p><b>NOTE:</b> You only need to specify a pass key if the <b>Security Level</b> is set to High.</p>
Trusted Device-Clear All	<p>Press the <b>Select</b> button  to clear the list of Trusted Devices.</p> <p><b>NOTE:</b> Your printer stores a maximum of eight external Bluetooth-enabled devices (trusted devices). When the printer detects more than eight devices, the least recently used device is removed from the list.</p>
Device Name	<p>The name assigned to the USB Bluetooth adapter. When printing from an external Bluetooth-enabled device, the <b>Device Name</b> or <b>Device Address</b> should be selected.</p>
Device Address	<p>The address of your USB Bluetooth adapter. When printing from an external Bluetooth-enabled device, the <b>Device Name</b> or <b>Device Address</b> should be selected.</p> <p><b>NOTE:</b> You cannot change the <b>Device Address</b>.</p>
Paper Handling	<p>Press the <b>Select</b> button  to enter the <b>Paper Handling</b> menu, and then select the size and type of the blank paper loaded in the input tray. If you have an optional input tray, you can also specify the paper source. For more information, see <a href="#">Paper Handling Menu</a>.</p>
<b>*Factory default setting</b>	

# Installing the Dell 966 Internal Wireless/Ethernet Adapter

- [Minimum Requirements for Setup](#)
- [Wireless Network Settings](#)
- [Wireless Encryption](#)
- [Installing and Setting Up the Adapter](#)
- [Configuring the Adapter Using the Wireless Setup Utility](#)

 **NOTE:** The Dell 966 Internal Wireless/Ethernet Adapter may not be available in all regions. Check with your local Dell Sales Representative to determine availability.

---

## Minimum Requirements for Setup

- The Dell™ 966 Internal Wireless/Ethernet Adapter
  - The Dell Photo All-In-One Printer 966
  - An existing wireless network
  - The *Drivers and Utilities* CD that came with your printer
  - A computer running one of the following operating systems:
    - Windows Vista™
    - Windows® XP
    - Windows 2000
- 

## Wireless Network Settings

Some wireless network settings may be needed to configure the adapter that has been installed in the printer. Here are some of the settings that you may need:

- Network Name, also known as SSID (Service Set ID)
  - BSS (Basic Service Set) Type (the type of wireless network you use—Ad-Hoc or Infrastructure)
  - Wireless Channel Number
  - Network Authentication and encryption type
  - Security Key(s)
- 

## Wireless Encryption

The following security types are supported:

- No security



- WEP with either 64-bit or 128-bit key
- WPA with either 128-bit TKIP encryption engine, or 128-bit AES-CCMP encryption engine

A WPA (WiFi Protected Access) pre-shared key is like a password and must meet the following criteria:

- If you are using Hex characters, valid keys are 64 characters long.
- If you are using ASCII, valid keys are at least 8 characters long.

The wireless network may use anywhere from one to four WEP keys. A WEP key is like a password and must meet the following criteria:

- If you are using Hex characters, valid keys are either 10 or 26 characters long.
- If you are using ASCII, valid keys are either 5 or 13 characters long.

---

## Installing and Setting Up the Adapter

### Installing the Adapter

1. Turn off your printer, and then unplug the power cable from the wall.




**⚠ CAUTION:** Failure to unplug the printer can cause damage to your printer and card. Make sure the power is off and the power cable is unplugged from the wall before proceeding.

2. Remove the back cover by pushing the tab to the left and then pulling the cover away from the printer.
3. Remove the screws and the cover plate.



**⚠ CAUTION:** Wireless adapters are easily damaged by static electricity. Touch something metal such as the printer frame before you touch the card.

4. Unpack the adapter. Save the packaging materials.
5. Align the edges of the adapter into the guides on the left and right, and then slide the card into the printer. It is normal that the adapter is not flush with the back of the printer until step 6 is completed.




**NOTE:** To verify that your adapter is aligned properly, make sure the Ethernet port is located on the left side of the adapter.

6. Tighten the thumb screws on the left and right to secure the adapter.



7. Rotate the antenna until it points up.



You are now ready to configure your adapter to work on your wireless or Ethernet network.

## Setting up the Adapter to Work on a Wireless Network

1. Plug the printer power cable into the wall outlet.
2. Press the **Power** button.
3. *If you are using your printer with a new Dell computer:* Connect the USB cable between the port on the back of the printer and the port on the back of the computer, and then go to [step 8](#).


*If you are using your printer with an existing computer:* Go to the next step.

4. Make sure your computer is on, and then insert the *Drivers and Utilities* CD. The CD launches automatically.

**NOTE:** If you do not have your *Drivers and Utilities* CD, you can download the appropriate software from [support.dell.com](http://support.dell.com).


5. Select **Using a wireless network**, and then click **Next**.
6. Select **I Agree with the terms of this license agreement**, and then click **Next**.
7. Read the Firewall Exception information, and then click **Next**.
8. Select the wireless settings you want to use, and then click **Next**.


Follow the instructions on your screen to complete installation. For more information about configuring your adapter to work on the network, see [Configuring the Adapter Using the Wireless Setup Utility](#).

 **NOTE:** The network name (SSID) and the security settings for the wireless network you want to connect to may be needed to complete this setup wizard. For more information, see the wireless network administrator or your network documentation.

For more information about configuring your adapter to work on the network, see [Configuring the Adapter Using the Wireless Setup Utility](#).

## Setting up the Adapter to Work on an Ethernet Network



1. Connect your printer to your network using an Ethernet cable (sold separately).
2. Connect the printer power cable to the wall, and then press the **Power** button .
3. Insert the *Drivers and Utilities* CD that came with your printer. The CD launches automatically.


 **NOTE:** If you do not have your *Drivers and Utilities* CD, you can download the appropriate software from [support.dell.com](http://support.dell.com).

4. Select **Using an Ethernet cable**, and then click **Next**.
5. Click **I Agree to the terms of this license agreement** to accept the license agreement.
6. Read the Firewall Exception information, and then click **Next**.
7. Your printer should appear in the printer list, and it should already be selected. Click **Next** to begin the installation process.

If your printer is not shown, you may need to manually configure your adapter's IP address to work with your network.

For more information about configuring your adapter to work on the network, see [Configuring the Adapter Using the Wireless Setup Utility](#).

## Setting up the Printer Using Advanced Setup

1. Connect the printer power cable to the wall, and then press the **Power** button .
2. Insert the *Drivers and Utilities* CD that came with your printer. The CD launches automatically.

 **NOTE:** If you do not have your *Drivers and Utilities* CD, you can download the appropriate software from [support.dell.com](http://support.dell.com).

3. Select **Advanced Setup**, and then click **Next**.
4. Select how the printer will be attached to a network, and then click **Next**.
5. Click **I Agree to the terms of this license agreement** to accept the license agreement.

6. *If you selected Peer-to-Peer Client:* Enter the remote computer's name and the shared printer's name, and then click **Next**. Follow the instructions on your screen to complete installation.

*If you selected Peer-to-Peer Host:* Select **I want to share my printer**, enter the Share Name for the printer, and then click **Next**. Follow the instructions on your screen to complete installation.

*If you selected Dell Wireless Adapter 3300:* Follow the instructions on your screen to complete installation.

---

## Configuring the Adapter Using the Wireless Setup Utility

### Configuration Overview

Configuring the card using the Wireless Setup Utility involves connecting the printer in which the card has been installed to a computer by USB cable, and launching the *Documents and Utilities* CD. The Wireless Setup Utility steps you through the configuration process. The wizard can automatically detect wireless network settings or allow you to manually enter the network configuration settings.

Before configuring the adapter, make sure your printer has been set up correctly:

- The adapter has been installed correctly in the printer.
- The ink cartridges are installed correctly.
- Paper has been loaded into the printer.
- The USB cable is attached to the printer and the computer.
- The printer is turned on and ready to be installed.

### Using an Available Wireless Network Configuration

1. From the **Wireless Networks Found In Your Area** screen, select the appropriate **Network Name (SSID)** from the list, and then click **Next**.
2. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.



**NOTE:** Clicking **Next** prompts the setup utility to verify wireless communication with the printer. The verification process can take up to 120 seconds.

3. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

### Entering a Different Wireless Network Configuration

1. From the **Wireless Networks Found In Your Area** screen, select **I want to enter a different configuration**, and then click **Next**.
2. *If the Network Name (SSID) you want to use is available*, select it from the list, and then click **Next**.

*If the Network Name (SSID) is not available*

- a. Select **I want to enter a different network name**, and then click **Next**.
- b. Enter the **Network Name (SSID)**.
- c. Select the appropriate **Channel** from the drop-down list. (**Auto** is the default.)

d. Select your **Wireless Mode**.

- For *Infrastructure Mode*, select **Access an existing network through a wireless router (Infrastructure Mode) - Typical**, and then click **Next**.

For additional setup instructions, see [Manually Configuring the Adapter in Infrastructure Mode](#).

- For *Ad-Hoc Mode*, select **Access other computers directly without using a wireless router (Ad-Hoc Mode)**, and then click **Next**.

For additional setup instructions, see [Manually Configuring the Adapter in Ad-Hoc Mode](#).

3. Select the appropriate security method, and then click **Next**. If no security was detected, go to [step 5](#).

4. Enter the appropriate security key(s) for the network, and then click **Next**.

5. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.



**NOTE:** Clicking **Next** prompts the setup utility to verify wireless communication with the printer. The verification process can take up to 120 seconds.

6. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

## Manually Configuring the Adapter in Infrastructure Mode

To set up the adapter in Infrastructure Mode, the setup steps vary based on the security settings you select.

- *If you don't want any security*

1. From the **Wireless Security Settings** screen, select **No Security**, and then click **Next**.

2. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.

3. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

- *If you want to use Wired Equivalent Privacy (WEP) security*

1. From the **Wireless Security Settings** screen, select **Wired Equivalent Privacy (WEP)**, and then click **Next**.

The **WEP Security Information** screen opens.

2. Enter the appropriate **Network Key**, and then click **Next**.

3. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.

4. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

- *If you want to use Wi-Fi Protected Access (WPA) security*

1. From the **Wireless Security Settings** screen, select **Wi-Fi Protected Access (WPA)** and then click **Next**.

The **WPA Security Information** screen opens.

2. Enter the appropriate **WPA Network Key**, and then click **Next**.

3. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.
  4. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).
- *If you only want to connect to access points that support WPA2 security*
    1. From the **Wireless Security Settings** screen, select **Wi-Fi Protected Access (WPA)**, and then click **Advanced WPA Settings**.

The **Advanced WPA Options** dialog box opens.
    2. Select the **Use WPA2 authentication only** check box, and then click **OK**.

You are returned to the **Wireless Security Settings** screen.
    3. Click **Next**.
    4. Enter the appropriate **WPA Network Key**, and then click **Next**.
    5. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.
    6. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

## Manually Configuring the Adapter in Ad-Hoc Mode

To set up the adapter in Ad-Hoc Mode, the setup steps vary based on the security settings you select. The security options are more limited in Ad-Hoc Mode than they are in Infrastructure Mode.

- *If you don't want any security*
  1. From the **Wireless Security Settings** screen, select **No Security**, and then click **Next**.
  2. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.
  3. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).
- *If you want to use Wired Equivalent Privacy (WEP) security*
  1. From the **Wireless Security Settings** screen, select **Wired Equivalent Privacy (WEP)**, and then click **Next**.
  2. Enter the appropriate **Network Key**.
  3. If you have additional network keys, select the **My network requires more than one network key** check box, and then enter the additional network keys.
  4. Click **Next**.
  5. On the **Apply and Verify Wireless Settings** screen, check each network attribute to make sure the settings are correct, and then click **Next** to apply the settings.
  6. Verify that the adapter can communicate over the network. For more information, see [Verifying Network Communication](#).

## Verifying Network Communication

You should verify that your adapter can communicate over the network before completing installation of the printer software.

- *If the adapter was successfully configured and is available on the network*, remove the USB cable, and click **Next** to continue with printer software installation.
- *If the adapter was not able to join the wireless network*, try one of the following suggestions:
  - Click **View Settings** to verify the settings are correct.
  - Select **I want to change the settings I entered**, and then click **Next**.

Follow the instructions on your screen to update the wireless settings.

- Select **I have moved my wireless printer closer to the wireless router. I would like to try connecting again**, and then click **Next**.

# Loading Paper and Originals

- [Loading Paper Into Trays](#)
  - [Understanding the Automatic Paper Type Sensor](#)
  - [Loading Original Documents](#)
- 

## Loading Paper Into Trays

### Loading Paper


1. Fan the paper.




2. Remove the paper tray. Push the lever in, and then extend the tray until it is long enough to accommodate the length of the paper.



3. Load paper in the paper tray, and adjust the paper guides.

 **NOTE:** You can only load letter size, legal size, or A4 paper in the optional paper tray.




4. Replace the paper tray.






5. Extend the paper support on the paper tray, and then lift the paper stop.



 **NOTE:** The paper exit tray can hold up to 50 sheets of paper.

## Print Media Guidelines

Load up to:	Make sure:
150 sheets of plain paper	<ul style="list-style-type: none"> <li>The paper guides rest against the edges of the paper.</li> <li>You load the paper with the print side facing down and the top going into the printer first.</li> <li>You select <b>Automatic</b>, <b>Draft</b>, <b>Normal</b>, or <b>Photo</b> print quality. Do not select <b>Draft</b> if you have a Photo cartridge installed.</li> </ul>
10 envelopes in the paper tray 1 envelope into the small media feeder 	<ul style="list-style-type: none"> <li>The print side of the envelope faces down.</li> <li>You can also insert envelopes into the small media feeder one at a time.</li> <li>You print the envelopes with <b>Landscape</b> orientation with the return address on the left.</li> </ul> <p><b>NOTE:</b> If you are mailing within Japan, the envelope can be printed in Portrait orientation with the stamp in the lower right corner or in Landscape orientation with the stamp in the lower left corner. If you are mailing internationally, print Landscape orientation with the stamp in the upper left corner.</p> <ul style="list-style-type: none"> <li>You select the correct envelope size. Select the next biggest size if the exact envelope size is not listed, and set the left and right margins so your envelope text is correctly positioned.</li> </ul>
20 sheets of banner paper	<ul style="list-style-type: none"> <li>You remove all paper from the paper input tray before inserting banner paper.</li> <li>You use banner paper designed for inkjet printers.</li> <li>You select <b>A4 Banner</b> or <b>Letter Banner</b> paper size.</li> </ul> <p><b>NOTE:</b> For more information on how to load banner paper, see <a href="#">Loading Banner Paper</a>.</p>
25 greeting cards, index cards, postcards, or photo cards in the paper tray 1 greeting card, index card, postcard, or photo card into the small media feeder 30 sheets of Hagaki or Hagaki photo cards in the paper tray	<ul style="list-style-type: none"> <li>The print side of the cards faces down.</li> <li>You can also insert cards into the small media feeder one at a time.</li> <li>You select <b>Automatic</b>, <b>Normal</b> or <b>Photo</b> print quality.</li> </ul>



50 sheets of glossy/photo or matte paper	<ul style="list-style-type: none"> <li>• The print side of the paper faces down.</li> <li>• The paper guides rest against the edges of the paper.</li> <li>• You select <b>Automatic</b>, <b>Normal</b> or <b>Photo</b> print quality.</li> </ul>
10 mm stack of iron-on transfers	<ul style="list-style-type: none"> <li>• You follow the loading instructions on the iron-on transfer packaging.</li> <li>• The print side of the transfer faces down.</li> <li>• The paper guides rest against the edges of the transfer.</li> <li>• You select <b>Automatic</b>, <b>Normal</b> or <b>Photo</b> print quality.</li> </ul>
50 sheets of transparencies	<ul style="list-style-type: none"> <li>• The rough side of the transparencies faces down.</li> <li>• The paper guides rest against the edges of the transparencies.</li> <li>• You select <b>Automatic</b>, <b>Draft</b>, <b>Normal</b> or <b>Photo</b> print quality.</li> </ul>
25 sheets of labels	<ul style="list-style-type: none"> <li>• The print side of the labels faces down.</li> <li>• The top of the labels feeds into the printer first.</li> <li>• The paper guides rest against the edges of the paper.</li> </ul>
150 sheets of letterhead paper	<ul style="list-style-type: none"> <li>• The print side of the letterhead faces down.</li> <li>• The top of the letterhead feeds into the printer first.</li> <li>• The paper guides rest against the edges of the paper.</li> </ul>
150 sheets of custom size paper	<ul style="list-style-type: none"> <li>• The paper fits within these dimensions: Width: 3.0 – 8.5 inches (76 – 216 mm) Length: 5.0 – 17.0 inches (127 – 432 mm)</li> <li>• The print side of the paper faces down.</li> <li>• The paper guides rest against the edges of the paper.</li> </ul>

## Loading Banner Paper

1. Remove the paper tray.
2. Remove any paper from the tray.
3. Push the lever in, and then extend the tray until it is long enough to accommodate legal size paper.



4. Replace the paper tray.
5. Tear off only the number of banner pages needed for the banner.
6. Set the stack of paper on a flat surface in front of the printer.
7. Slide the first sheet of the banner over the handle and all the way into the back of the paper tray.



## Understanding Tray Linking

If you purchased an optional paper tray, you can set the trays to link to each other. Tray linking enables the automatic linking feature for trays when you load the same size and type of paper in the standard and optional paper trays. The printer automatically links the trays; when one tray is empty, paper feeds from the next linked tray.

For example, if you have the same size and type of paper in Tray 1 (standard paper tray) and Tray 2 (optional tray), the printer selects print media from Tray 1 until it becomes empty, and then the printer automatically feeds print paper from Tray 2.

In addition, you can load a different size of paper for each tray so that the printer picks the paper that matches the size of the fax you received. For example, if letter size is loaded in Tray 1 and legal size is loaded in Tray 2, if you receive a legal size fax, the printer picks from Tray 2.

 **NOTE:** You can only load letter size, legal size, or A4 paper in the optional paper tray.

You can enable Tray Linking after you have installed the optional paper tray. You can also turn this option on and off, as needed.

## Enabling Tray Linking for Print Jobs Using the Computer

1. Turn on your computer and printer, and make sure they are connected.
2. Load paper of the same type and size in both paper trays.
3. With your document open, click **File® Print**.

The **Print** dialog box opens.

4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).








The **Printing Preferences** dialog box opens.

5. On the **Print Setup** tab, select **Automatic** from the **Paper Source** drop-down list.
6. On the **Print Setup** and **Advanced** tabs, make any necessary changes for your document.
7. When you finish customizing your settings, click **OK**.










The **Printing Preferences** dialog box closes.

8. Click **OK** or **Print**.








## Enabling Tray Linking for Print Jobs Using the Operator Panel

1. From the main menu, use the up or down **Arrow** button  to scroll to **Setup**, and then press the **Select** button .
2. Press the up or down **Arrow** button  to scroll to **Paper Handling**, and then press the **Select** button .
3. Press the up or down **Arrow** button  to scroll to **Tray Linking**, and then press the left or right **Arrow** button  to scroll to **Auto**.
4. Press the **Back** button .






## Enabling Tray Linking For Copying Jobs


1. Load paper of the same type and size in both paper trays.
2. From the **Main menu**, press the up or down **Arrow** button  to scroll to **Setup**, and then press the **Select** button .
3. From the **Setup** menu, press the up or down **Arrow** button  to scroll to **Change Copy Default Settings**, and then press the **Select** button .
4. From the **Copy Default Settings** menu, press the up or down **Arrow** button  to scroll to **Paper Handling**, and then press the **Select** button .
5. From the **Paper Handling** menu, specify the size and type of paper loaded in both paper trays.
6. Press the up or down **Arrow** button  to scroll to **Tray Linking**, and then press the left or right **Arrow** button  to select **Auto**.
7. Press the **Back** button  to save the settings and return to the previous menu.

## Enabling Tray Linking to Print Received Faxes

1. Load paper of the same type but of different sizes in both trays.
2. From the **Main menu**, press the up or down **Arrow** button  to scroll to **Setup**, and then press the **Select** button .
3. From the **Setup** menu, press the up or down **Arrow** button  to scroll to **Change Fax Default Settings**, and then press the **Select** button .
4. From the **Fax Setup** menu, press the up or down **Arrow** button  to scroll to **Fax Printing**, and then press the **Select** button .
5. From the **Fax Printing** menu, press the up or down **Arrow** button  to scroll to **Paper Handling**, and then

press the **Select** button .

- From the **Paper Handling** menu, specify the size and type of paper loaded in both paper trays.
- Press the up or down **Arrow** button  to scroll to **Tray Linking**, and then press the left or right **Arrow** button  to select **Auto**.
- Press the up or down **Arrow** button  to scroll to **Fax Source**, and then press the left or right **Arrow** button  to select the paper source.
- Press the **Back** button  to save the settings and return to the previous menu.

 **NOTE:** If you load media of the same type and size in both trays, the printer picks from the next tray once the paper source you specified for faxing is empty.


## Understanding the Automatic Paper Type Sensor

Your printer has an automatic paper type sensor that detects the following paper types:

- Plain/coated
- Transparency
- Photo/glossy

If you load one of these paper types, the printer detects the paper type and automatically adjusts the Quality/Speed settings.

Paper type	Quality/Speed settings	
	Black and Color Cartridges Installed	Photo and Color Cartridges Installed
Plain/coated	Normal	Photo
Transparency	Normal	Photo
Photo/glossy	Photo	Photo

 **NOTE:** Your printer cannot detect paper size.

To choose paper size:

- With your document open, click **File® Print**.  
The **Print** dialog box opens.
- Click **Preferences, Properties, Options, or Setup** (depending on the program or operating system).  
The **Printing Preferences** dialog box opens.
- On the **Print Setup** tab, select the paper size.
- Click **OK**.

Unless you turn off the automatic paper type sensor, it always remains on. To turn off the automatic paper type sensor for a specific print job:

- With your document open, click **File® Print**.  
The **Print** dialog box opens.
- Click **Preferences, Properties, Options, or Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.


3. On the **Print Setup** tab, select the paper type.
4. Click **OK**.

To turn off the automatic paper type sensor for all print jobs:

1. *In Windows® XP*, click **Start® Control Panel® Printers and Other Hardware® Printers and Faxes**.

*In Windows 2000*, click **Start® Settings® Printers**.

*In Windows Vista™*:

- a. Click  **Control Panel**.
  - b. Click **Hardware and Sound**.
  - c. Click **Printers**.
2. Right-click the printer icon.
  3. Click **Printing Preferences**.
  4. On the **Print Setup** tab, select the paper type.
  5. Click **OK**.

---


## Loading Original Documents

### Into the ADF

You can load up to 50 sheets of an original document into the ADF for scanning, copying, and faxing. The ADF is recommended for loading multiple-page documents.

1. Load an original document text side up into the ADF.



 **NOTE:** Do not load postcards, photos, small items, or thin media (such as magazine clippings) into the ADF. Place these items on the scanner glass.

2. Adjust the paper guide on the ADF against the edges of the paper.

### ADF Paper Capacity

Load up to	Make sure
50 sheets of letter size paper	<ul style="list-style-type: none"><li>• The document is loaded text side up.</li><li>• The paper guide rests against the edge of the paper.</li></ul>

50 sheets of legal size paper	<ul style="list-style-type: none"> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> </ul>
50 sheets of A4 size paper	<ul style="list-style-type: none"> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> </ul>
50 sheets of two-, three-, or four-hole pre-punched media	<ul style="list-style-type: none"> <li>• The paper fits within these dimensions: Width: 8.27 – 8.5 inches (210.0 – 215.9 mm) Length: 11.0 – 14.0 inches (279.4 – 355.6 mm)</li> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> </ul>
50 sheets of edge-reinforced three-hole copier media	<ul style="list-style-type: none"> <li>• The paper fits within these dimensions: Width: 8.27 – 8.5 inches (210.0 – 215.9 mm) Length: 11.0 – 14.0 inches (279.4 – 355.6 mm)</li> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> </ul>
50 sheets of preprinted forms and letterhead media	<ul style="list-style-type: none"> <li>• The paper fits within these dimensions: Width: 8.27 – 8.5 inches (210.0 – 215.9 mm) Length: 11.0 – 14.0 inches (279.4 – 355.6 mm)</li> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> <li>• You allow the preprinted media to dry thoroughly before use in the ADF.</li> <li>• You do <i>not</i> use media printed with metallic ink particles in the ADF.</li> <li>• You avoid embossed designs.</li> </ul>
50 sheets of custom size paper	<ul style="list-style-type: none"> <li>• The paper fits within these dimensions: Width: 8.27 – 8.5 inches (210.0 – 215.9 mm) Length: 11.0 – 14.0 inches (279.4 – 355.6 mm)</li> <li>• The document is loaded text side up.</li> <li>• The paper guide rests against the edge of the paper.</li> </ul>

## On the Scanner Glass

1. Open the top cover.



2. Place the document face down on the scanner glass.



**NOTE:** Make sure the upper left corner of the front of the item aligns with the arrow on the printer.



3. Close the top cover.





# Maintenance

- [Replacing Ink Cartridges](#)
- [Aligning Ink Cartridges](#)
- [Cleaning the Ink Cartridge Nozzles](#)
- [Restoring Factory Default Settings](#)

**⚠ CAUTION:** Before performing any of the procedures listed in this section, read and follow the safety information in your *Owner's Manual*.

Dell ink cartridges are available only through Dell. You can order more ink online at [www.dell.com/supplies](http://www.dell.com/supplies) or by phone.

Dell recommends Dell ink cartridges for your printer. Dell does not provide warranty coverage for problems caused by using accessories, parts, or components not supplied by Dell.

---


## Replacing Ink Cartridges

1. Turn on your printer.
2. Lift the printer unit.



The ink cartridge carrier moves and stops at the loading position unless the printer is busy.


3. Press down on the ink cartridge lever to raise each ink cartridge lid.




4. Remove the old ink cartridges.



5. Store the cartridges in an air-tight container, such as the storage unit you received with your photo cartridge, or dispose of them properly.
6. If you are installing new ink cartridges, remove the sticker and transparent tape from the back and bottom of each ink cartridge.


 **NOTE:** The following illustration shows a black cartridge and a color cartridge (used for normal printing). For photo printing, use a photo cartridge and a color cartridge.



7. Insert the new ink cartridges. Make sure the black or photo ink cartridge is secure in the left ink cartridge carrier, and the color ink cartridge is secure in the right ink cartridge carrier.



8. *Snap* each lid closed.



9. Lower the printer unit until it is completely closed.









---

## Aligning Ink Cartridges

Your printer automatically prompts you to align the ink cartridges when they are installed or replaced. You may also need to align ink cartridges when characters are not properly formed or are not aligned at the left margin, or when vertical or straight lines appear wavy.

To align the ink cartridges from the operator panel:

1. Load plain paper. For more information, see [Loading Paper](#).
2. Press the up or down **Arrow** button   to scroll to Maintenance.
3. Press the **Select** button .
4. Press the up or down **Arrow** button   to scroll to Align Cartridges.
5. Press the **Select** button .

The alignment page begins printing. The ink cartridges align when the page prints.

To align the ink cartridges from the printer software:

1. Load plain paper.
2. *In Windows XP*, click **Start® Control Panel® Printers and Other Hardware® Printers and Faxes**.

*In Windows 2000*, click **Start® Settings® Printers**.

*In Windows Vista*:

- a. Click  **Control Panel**.
- b. Click **Hardware and Sound**.
- c. Click **Printers**.

3. Right-click the printer icon.
  4. Click **Printing Preferences**.
- The **Printing Preferences** dialog box opens.
5. Click the **Maintenance** tab.
  6. Click **Align Ink Cartridges**.
  7. Click **Print**.

The ink cartridges align when the page prints.







---

## Cleaning the Ink Cartridge Nozzles

You may need to clean the nozzles when:

- White lines appear in graphics or solid black areas.
- Print appears smudged or too dark.
- Colors fade, do not print, or do not print correctly.
- Vertical lines appear jagged, or edges appear rough.

To clean the nozzles from the operator panel:

1. Load plain paper. For more information, see [Loading Paper](#).
2. Press the up or down **Arrow** button   to scroll to Maintenance.
3. Press the **Select** button .
4. Press the up or down **Arrow** button   to scroll to Clean Cartridges.
5. Press the **Select** button .


The cleaning page begins printing.

To clean the nozzles from the printer software:

1. Load plain paper.
2. *In Windows XP*, click **Start® Control Panel® Printers and Other Hardware® Printers and Faxes**.

*In Windows 2000*, click **Start® Settings® Printers**.

*In Windows Vista*:

- a. Click  **Control Panel**.
  - b. Click **Hardware and Sound**.
  - c. Click **Printers**.
3. Right-click the printer icon.
  4. Click **Printing Preferences**.

The **Printing Preferences** dialog box opens.

5. Click the **Maintenance** tab.
6. Click **Clean Ink Cartridges**.

The cleaning page begins printing.








7. If the print quality has not improved, click **Clean Again**.
8. Print your document again to verify the improved print quality.

If you are still not satisfied with the print quality, wipe the nozzles with a clean, dry cloth, and then print your document again.

---

## Restoring Factory Default Settings

Menu settings marked with an asterisk (\*) indicate the active settings. You can restore the original printer settings, often referred to as the *factory default settings*.

1. Make sure the printer is on.
2. Press the up or down **Arrow** button   to scroll to **Maintenance**, and then press the **Select** button .
3. Press the up or down **Arrow** button   to scroll to **Reset Defaults**, and then press the **Select** button .
4. With **Yes** highlighted, press the **Select** button .

 **NOTE:** Some settings such as phone lists, time, date, and country are not changed.

# Printing

- [Printing Documents](#)
  - [Printing Photos](#)
  - [Printing Envelopes](#)
  - [Printing From a Bluetooth-enabled Device](#)
  - [Printing Photos From a PictBridge-Enabled Camera](#)
  - [Printing Collated Copies of Your Document](#)
  - [Printing More Than One Page on a Sheet of Paper](#)
  - [Duplexing a Print Job \(Two-Sided Printing\)](#)
  - [Printing an Image as a Multi-page Poster](#)
  - [Printing a Banner](#)
- 

## Printing Documents

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. With your document open, click **File® Print**.

The **Print** dialog box opens.

4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).


The **Printing Preferences** dialog box opens.

5. On the **Print Setup** and **Advanced** tabs, make any necessary changes for your document.
6. When you finish customizing your settings, click **OK**.


The **Printing Preferences** dialog box closes.

7. Click **OK** or **Print**.
- 

## Printing Photos

 **NOTE:** Dell recommends you use a color cartridge and a photo cartridge for printing photos.

1. Turn on your computer and printer, and make sure they are connected.
2. Load photo/glossy paper with the print side facing up.

 **NOTE:** Photo/glossy paper is recommended for printing photos.

3. With your document open, click **File® Print**.


The **Print** dialog box opens.

4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

 **NOTE:** If you are using Dell Photo Suite™, select **Printer Settings** to view **Printing Preferences**.


5. On the **Print Setup** tab, select **Photo**, and then select the dpi settings for the photo from the drop-down menu.

 **NOTE:** To print borderless photos, select the **Borderless** check box on the **Print Setup** tab, and then select the borderless paper size from the drop-down menu on the **Advanced** tab. Borderless printing is only performed if you are using photo/glossy paper. The printout on non-photo paper contains a 2 mm margin on all sides.

6. On the **Print Setup** and **Advanced** tabs, make any necessary changes for your document.
7. When you finish customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

8. Click **OK** or **Print**.
9. Remove each photo after it exits the printer to prevent your photos from sticking together or smudging.

 **NOTE:** Before placing your prints in a nonadhesive photo album or frame, allow sufficient time for the prints to dry thoroughly (12 to 24 hours, depending on ambient conditions). This maximizes the life of your prints.

---

## Printing Envelopes

1. Turn on your computer and printer, and make sure they are connected.
2. Load the envelope with the print side facing down.




3. With your document open, click **File® Print**.

The **Print** dialog box opens.

4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

5. On the **Print Setup** tab, select **Envelope** orientation, and then choose the size of the envelope from the **Paper size: drop-down** menu.

 **NOTE:** If you are mailing within Japan, the envelope can be printed in portrait orientation with the stamp in the lower right corner or in landscape orientation with the stamp in the lower left corner. If you are mailing internationally, print landscape orientation with the stamp in the upper left corner.

6. On the **Print Setup** and **Advanced** tabs, make any necessary changes for your document.
7. When you finish customizing your settings, click **OK**.


The **Printing Preferences** dialog box closes.

8. Click **OK** or **Print**.
- 

## Printing From a Bluetooth-enabled Device


- This All-In-One (AIO) printer is compliant with Bluetooth Specification 1.2. It supports Object Push Profile. Check with your Bluetooth-enabled device manufacturers (cellular phone or PDA) to determine their hardware compatibility and interoperability. It is recommended that you use the latest firmware on your Bluetooth-enabled device.
- To print Microsoft documents from your Windows Mobile/Pocket PC PDA, you require additional third-party software and drivers. For more information about the required software and drivers, and to purchase these components, refer to the Westtek Web site at [www.westtek.com](http://www.westtek.com).
- Before you call Dell customer support, see the section for information on setting up a connection with a Bluetooth-enabled device. You can also visit the Dell Support Web site at [support.dell.com](http://support.dell.com). This Web site contains the latest documentation. Ensure that you read the documentation that came with your Bluetooth device for setup instructions.

## Setting up a Connection with an External Bluetooth-Enabled Device

 **NOTE:** Your Bluetooth device does not support printing files through your computer.

If you are sending a print job to your printer from an external Bluetooth-enabled device for the first time, you need to set up your printer so that the USB Bluetooth adapter (attached to your printer) can communicate with other Bluetooth-enabled devices. You do not need to repeat this setup on your printer for the subsequent print jobs. However, you will need to repeat the setup if:

- You reset the printer to its factory default settings. For more information, see [Restoring Factory Default Settings](#).
- You cleared the contents of the Bluetooth device list, or your device is not listed as a trusted device.
- You changed the security level or the pass key of the USB Bluetooth adapter.
- You changed the USB Bluetooth adapter attached to your printer.


 **NOTE:** You need to set up a connection for each Bluetooth device that you will use to send a print job to the printer. Refer to the device documentation for more information.









To set up a connection between the external Bluetooth-enabled device and the USB Bluetooth adapter:

1. Activate Bluetooth on the device.



Refer to the device documentation for information.


2. Turn on the printer.
3. Insert a USB Bluetooth adapter (sold separately) into the PictBridge port.




4. Press the up or down **Arrow** button   to scroll to **Setup**, and then press the **Select** button .
5. Press the up or down **Arrow** button   to scroll to **Change Bluetooth Default Settings**, and then press the **Select** button .
6. From **Bluetooth Enabled**, press the left or right **Arrow** button   to scroll to **On**.




7. From *Discovery Mode* , press the left or right **Arrow** button  to scroll to *On*.
8. From *Security* , press the left or right **Arrow** button  to choose a security level.

 **NOTE:** If the security level is set to *High*, you need to specify a pass key for the USB Bluetooth adapter. Any external Bluetooth-enabled device needs to enter this pass key to send a print job to your printer.


9. Press the **Back** button  to save your settings and go back to the previous menu.


## Printing from a Bluetooth-enabled Device










1. Make sure the external Bluetooth-enabled device is set up to print to the printer. Refer to the device documentation for information.


 **NOTE:** Some devices display the USB Bluetooth adapter's name or address. Access the **Bluetooth Default Settings** menu to view the name and address of your USB Bluetooth adapter.

2. Insert a USB Bluetooth adapter (sold separately) into the PictBridge port.



 **NOTICE:** Do not remove the Bluetooth-enabled device or touch the printer near the area of the memory card or Bluetooth-enabled device while actively printing from Bluetooth. Data corruption can occur.

3. Set **Bluetooth Enabled** and **Discovery Mode** to *On*.
  - a. From the main menu, press the up or down **Arrow** button  to scroll to *Setup*, and then press the **Select** button .
  - b. Press the up or down **Arrow** button  to scroll to *Change Bluetooth Default Settings*, and then press the **Select** button .
  - c. Press the up or down **Arrow** button  to scroll to *Bluetooth Enabled*, and then press the left or right **Arrow** button  to scroll to *On*.
  - d. Press the up or down **Arrow** button  to scroll to *Discovery Mode*, and then press the left or right **Arrow** button  to scroll to *On*.
  - e. Press the **Back** button .
4. From your external Bluetooth-enabled device, send the print job to the printer. Refer to the device documentation for more information.

 **NOTE:** If the security level is set to *High*, you are required to enter the pass key from the external Bluetooth-enabled device. The pass key can be changed or viewed in the **Bluetooth Default Settings** menu. For more information, see [Bluetooth Mode](#).

# Printing Photos From a PictBridge-Enabled Camera

Your printer supports PictBridge-enabled cameras.

1. Insert one end of the USB cable into the camera.
2. Insert the other end of the USB cable into the PictBridge port on the front of the printer.

Refer to the instructions included with your camera for selection of the appropriate camera USB settings and PictBridge connection and usage information.



**NOTE:** When your printer is not connected to a computer, and a PictBridge camera is connected to your printer, some of the functions of your printer operator panel buttons may be unavailable. These functions become available after you disconnect the PictBridge camera from your printer.

3. Turn on your digital camera.

The printer automatically enters **PictBridge** mode.

4. Refer to the instructions included with your camera to begin printing photos.

**NOTE:** For many digital cameras, there are two USB mode selections: computer and printer (or PTP). For PictBridge printing, the printer (or PTP) USB selection should be used. For more information, refer to the documentation included with your camera.

**NOTICE:** Do not remove the PictBridge-enabled device or touch the printer near the area of the memory card or PictBridge-enabled device while actively printing from PictBridge. Data corruption can occur.

---

## Printing Collated Copies of Your Document

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. With your document open, click **File**® **Print**.

The **Print** dialog box opens.

4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

5. On the **Print Setup** tab, specify the number of copies to print.

**NOTE:** You must specify more than one copy for the **Collate Copies** check box to become active.

6. Select the **Collate copies** check box.
7. On the **Print Setup** and **Advanced** tabs, make any additional changes for your document.

8. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

9. Click **OK** or **Print**.
- 

## Printing More Than One Page on a Sheet of Paper

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. With your document open, click **File® Print**.
4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

5. On the **Advanced** tab, select **N-up** from the **Layout** drop-down list.
6. From the **Pages per sheet** drop-down list, select how many pages you want to be printed on one sheet.
7. Select the **Print Page Borders** check box if you want borders between pages.
8. On the **Print Setup** tab and **Advanced** tab, make any additional changes for your document.
9. Select the number of pages to print on each page.
10. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

11. Click **OK** or **Print**.
- 

## Duplexing a Print Job (Two-Sided Printing)

### Automatic Duplex

Automatic duplex allows you to print your document on both sides of the paper without having to manually re-orient the sheets. Make sure:

- You installed the optional duplex unit.
- You loaded letter size or A4 plain paper. You cannot duplex-print on envelopes, card stock, or photo paper.

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. With your document open, click **File® Print**.
4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).
5. Click the **Advanced** tab, and then select the **2-sided printing** check box.
6. From the drop-down list, select **Automatic**.

7. Select how you want to bind your pages.
8. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

9. Click **OK** or **Print**.

## Manual Duplex

Manual duplex allows you to print your document on both sides of the paper. The printer prints the odd-numbered pages of the document on the front sides of the paper. Reload the document with the blank side of the paper facing down, and print the even-numbered pages of the document on the back sides of the paper.

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. With your document open, click **File® Print**.
4. Click **Preferences, Properties, Options, or Setup** (depending on the program or operating system).
5. Click the **Advanced** tab, and then select the **2-sided printing** check box.
6. From the drop-down list, select **Manual**.
7. Select how you want to bind your pages.
8. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

9. Click **OK** or **Print**.
10. When all the odd-numbered pages have exited the printer, follow the instructions on your computer screen.

---

## Printing an Image as a Multi-page Poster

1. Turn on your computer and printer, and make sure they are connected.
2. Load paper. For more information, see [Loading Paper](#).
3. With your document open, click **File® Print**.
4. Click **Preferences, Properties, Options, or Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

5. On the **Advanced** tab, select **Poster** from the **Layout** drop-down list.
6. Select the size of the poster.
7. On the **Print Setup** tab and **Advanced** tab, make any additional changes for your document.
8. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

9. Click **OK** or **Print**.

---

## Printing a Banner

1. Turn on your computer and printer, and make sure they are connected.
2. Load paper. For more information, see [Loading Banner Paper](#).
3. With your document open, click **File**® **Print**.
4. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

5. On the **Advanced** tab, select **Banner** from the **Layout** drop-down list, and then select **Letter Banner** or **A4 Banner** from the **Banner Paper Size** drop-down list.
6. On the **Print Setup** tab and **Advanced** tab, make any additional changes for your document.
7. When you are finished customizing your settings, click **OK**.

The **Printing Preferences** dialog box closes.

8. Click **OK** or **Print**.



**NOTE:** Once the printer begins printing, wait until you can see the leading edge of the banner exiting the printer, and then carefully unfold the paper down to the floor in front of the printer.

# Troubleshooting

- [Setup Problems](#)
- [General Problems](#)
- [Error Messages](#)
- [Improving Print Quality](#)
- [General Guidelines for Selecting or Loading Print Media](#)
- [Avoiding Jams and Misfeeds](#)

If the printer does not work, ensure that the printer is properly connected to the electrical outlet and computer, if using a computer.

---

## Setup Problems

### Computer Problems

#### Verify your printer is compatible with your computer.


The printer supports Windows XP Professional x64, Windows XP, Windows 2000, and Windows Vista.

#### Make sure you turned on both your printer and your computer.

#### Check the USB cable.

- Ensure the USB cable is firmly connected to your printer and your computer.
- Shut down the computer, reconnect the USB cable as shown on the *Setting Up Your Printer* poster, and then restart the computer.

#### If the software installation screen does not appear automatically, install the software manually.

1. Insert the *Drivers and Utilities* CD.
2. In *Windows XP*, click **Start® My Computer**.  
*In Windows 2000*, double-click **My Computer** from your desktop.  
*In Windows Vista*, click  **Computer**.
3. Double-click the **CD-ROM drive** icon, and then double-click **setup.exe**.
4. When the printer software installation screen appears, click **Personal Installation** or **Network Installation**.
5. Follow the instructions on your screen to complete the installation.

#### Determine if the printer software is installed.

Click **Start® Programs** or **All Programs® Dell Printers**.

For *Windows Vista*:

1. Click  **Programs**.
2. Click **Dell Printers**.

If the printer does not appear in the list of printers, the printer software is not installed. Install the printer software. For more information, see [Removing and Reinstalling Software](#).

### Correct communication problems between the printer and the computer.


- Remove the USB cable from your printer and your computer. Reconnect the USB cable to your printer and your computer.
- Turn off the printer. Unplug the printer power cable from the electrical outlet. Reconnect the printer power cable into the electrical outlet, and turn on the printer.
- Restart your computer.

### Set your printer as the default printer.

1. *In Windows XP*, click **Start**® **Control Panel**® **Printers and Other Hardware**® **Printers and Faxes**.

*In Windows 2000*, click **Start**® **Settings**® **Printers**.

*In Windows Vista*:

- a. Click  **Control Panel**.
  - b. Click **Hardware and Sound**.
  - c. Click **Printers**.
2. Right-click the printer icon, and select **Set as Default Printer**.


### Printer won't print and print jobs are stuck in the print queue.

Check for multiple instances of the printer installed on your computer.

1. *In Windows XP*, click **Start**® **Control Panel**® **Printers and Other Hardware**® **Printers and Faxes**.

*In Windows 2000*, click **Start**® **Settings**® **Printers**.

*In Windows Vista*:

- a. Click  **Control Panel**.
  - b. Click **Hardware and Sound**.
  - c. Click **Printers**.
2. Check for multiple objects for your printer.
  3. Print a job to each of these print objects to see which printer is active.
  4. Set that print object as the default printer by right-clicking the printer icon and selecting **Set as Default Printer**.
  5. Delete the other copies of the print object by right-clicking the printer name and selecting **Delete**.

To prevent multiple instances of the printer in your **Printers** folder, make sure you always plug the USB cable back into the same USB port that was originally used for the printer. Also, do not install printer drivers multiple times from the *Drivers and Utilities* CD.

## Printer Problems

Ensure the printer power cable is firmly connected to the printer and the electrical outlet.

Determine if the printer has been held or paused.

1. In *Windows XP*, click **Start® Control Panel® Printers and Other Hardware® Printers and Faxes**.

In *Windows 2000*, click **Start® Settings® Printers**.

In *Windows Vista*:

- a. Click  **Control Panel**.
  - b. Click **Hardware and Sound**.
  - c. Click **Printers**.
2. Right-click the printer icon.
3. Make sure **Pause Printing** is not selected. If **Pause Printing** is selected, click it to clear the option.

Check for blinking lights on the printer.

For more information, see [Error Messages](#).

Ensure you installed the ink cartridges correctly and removed the sticker and tape from each cartridge.

Make sure you loaded the paper correctly.

For more information, see [Loading Paper](#).

Ensure the printer is not connected to a PictBridge-enabled camera.

For more information, see [Printing Photos From a PictBridge-Enabled Camera](#).

## General Problems

### Printing Problems

Check the ink levels, and install new print cartridges if necessary.

For more information, see:

- [Dell Ink Management System](#).
- [Replacing Ink Cartridges](#).

Make sure you remove individual sheets from the paper exit tray.

To avoid ink smudging when you are using the following media, remove each sheet as it exits, and allow it to dry:

- Photo paper



- Glossy paper
- Transparency
- Labels
- Envelopes
- Iron-on transfers

### Free up memory resources on your computer when print speed is slow

- Close all applications not in use.
- Try minimizing the number and size of graphics and images in your document.
- Consider purchasing more Random Access Memory (RAM) for your computer.
- Remove as many unused fonts as possible from your system.
- Uninstall the printer software, and then reinstall it. For more information, see [Removing and Reinstalling Software](#).
- Select a lower print quality. For more information, see [Using Printing Preferences](#).

### Make sure you loaded the paper correctly.

For more information, see [Loading Paper](#).

## Copying Problems

### Check for blinking lights or error messages on the printer.

For more information, see [Error Messages](#).


### Make sure the scanner glass is clean.

If the scanner glass is dirty, gently wipe it with a clean, lint-free cloth dampened with water.

### Use the Remove Patterns option to remove image patterns from magazines or newspapers.

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  3. Click **See More Copy Settings**, and then click **Advanced**.

The **Advanced Copy Settings** dialog box opens.

4. From the **Image Patterns** tab, select *Remove image patterns from magazine/newspaper (descreen)*, and then click **OK**.
5. Click **Copy Now**.

### **Make sure the document or photo is loaded correctly on the scanner glass or into the ADF.**

For more information, see how to load originals:

- [On the Scanner Glass](#).
- [Into the ADF](#).

### **Check paper sizes.**

Make sure the paper size being used matches the size you selected on the operator panel or the **Dell All-In-One Center**.

## **Scanning Problems**

### **Check for blinking lights and error messages on the printer.**

For more information, see [Error Messages](#).

### **Check the USB cable.**

- Ensure the USB cable is firmly connected to your printer and your computer.
- Shut down the computer, reconnect the USB cable as shown on the *Setting Up Your Printer* poster, and then restart the computer.

### **Determine if the printer software is installed.**

Click **Start® Programs** or **All Programs® Dell Printers**.

For *Windows Vista*:

1. Click  **Programs**.
2. Click **Dell Printers**.

If the printer does not appear in the list of printers, the printer software is not installed. Install the printer software. For more information, see [Removing and Reinstalling Software](#).

### **Correct communication problems between the printer and the computer.**

- Remove the USB cable from your printer and your computer. Reconnect the USB cable to your printer and your computer.
- Turn off the printer. Unplug the printer power cable from the electrical outlet. Reconnect the printer power cable into the electrical outlet, and turn on the printer.
- Restart your computer.

### **Change the scan resolution to a lower value if scanning takes too long or freezes the computer.**

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.


The **Dell All-In-One Center** opens.

3. Click **See More Scan Settings**.
4. Select a lower scan resolution from the **Select Scan Quality** menu.
5. Click **Scan Now**.

### Change the scan resolution to a higher value if the scanned image quality is poor.

1. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.
- The **Dell All-In-One Center** opens.
3. Click **See More Scan Settings**.
  4. Select a higher scan resolution from the **Select Scan Quality** menu.
  5. Click **Scan Now**.

### Use the Remove Patterns option to remove image patterns from magazines or newspapers.

1. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.









For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.
- The **Dell All-In-One Center** opens.
3. Click **See More Scan Settings**, and then click **Advanced**.
- The **Advanced Scan Settings** dialog box opens.
4. From the **Image Patterns** tab, select **Remove image patterns from magazine/newspaper (descreen)**, and then click **OK**.

5. Click **Scan Now**.

### Choose another application if scanning to an application fails.


*Using the operator panel*

1. From the main menu, press the up or down **Arrow** button   to scroll to **Scan**, and then press the **Select** button .
2. Press the **Select** button .
3. From the **Scan Mode** menu, press the up or down **Arrow** button   to scroll to **Scan To**, and then press the left and right **Arrow** button   to choose another application.

*Using the computer*

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

*For Windows Vista:*

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

3. From the **Send scanned images to:** drop-down menu, choose another application.

**NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add your program to the list.

### Make sure the document or photo is loaded correctly on the scanner glass or into the ADF.

For more information, see how to load originals:

- [On the Scanner Glass](#).
- [Into the ADF](#).

### Make sure the scanner glass is clean.

If the scanner glass is dirty, gently wipe it with a clean, lint-free cloth dampened with water.

## Fax Problems

**Make sure you turned on both your printer and your computer, and the USB cable is properly inserted.**

**Ensure the computer is connected to an active analog telephone line.**















- Using the fax function requires a phone connection to the fax modem in your computer.
- When using DSL broadband service, make sure you have a DSL filter installed on your phone cord. Contact your Internet Service Provider for more information.

- Make sure your computer is not connected to the Internet by dial-up modem when trying to fax.

**When using an external modem, make sure it is turned on and it is correctly connected to your computer.**

**When the printer's memory is full, print a fax activity report and resend pages that were not transmitted.**















**When sending color pages, set the printer to scan the original documents after dialing.**

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button   to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button   to scroll to **Dialing and Sending**, and then press the **Select** button .
4. Press the up or down **Arrow** button   to scroll to **Scan**, and then press the left or right **Arrow** button   to scroll to **After Dial**.
5. Press the **Back** button  to save the changes.











**NOTE:** This setting is applicable for all subsequent fax jobs.

**If caller ID is not working, make sure that you selected the correct Caller ID pattern.**

The Caller ID detection pattern is determined by the country or region you selected during initial setup. If phones in your country use two detection patterns, call your telecommunications company to determine which pattern it subscribes to.

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button   to scroll to **Fax Setup**, and then press the **Select** button .
3. Press the up or down **Arrow** button   to scroll to **Ringing and Answering**, and then press the **Select** button .
4. Press the up or down **Arrow** button   to scroll to **Caller ID pattern**, and then press the left or right **Arrow**   button to select an option.
  - Select **Pattern 1** if telephones in your country subscribe to a detection pattern using frequency-shift keying (FSK).
  - Select **Pattern 2** if telephones in your country subscribe to a detection pattern using dual tone multifrequency (DTMF).
5. Press the **Back** button .

**Set the quality of the outgoing fax to Ultrafine.**

1. From the main menu, press the up or down **Arrow** button   to scroll to **Fax**, and then press the **Select** button .
2. Press the up or down **Arrow** button   to scroll to **Edit Fax Settings**, and then press the **Select** button .
3. Press the up or down **Arrow** button   to scroll to **Quality**, and then use the left or right **Arrow** button   to scroll to **Ultrafine**.

4. Press the **Back** button .

If the quality of the received fax is still poor, the fax machine at the receiving end may be limiting the fax quality. Any adjustments that you make on your printer do not affect the quality of faxes received at the other end.

## Networking Problems

### Check the cable connections.

If the printer is attached to a network adapter:

- Check the Ethernet cable and USB cable for any obvious damage.
- Firmly plug one end of the USB cable into the printer, and the other end into the network adapter.
- Firmly plug one end of the Ethernet cable into the network adapter, and the other end into the network hub or wall connection.

If the printer is attached to a computer that is connected to the network:

- Check the USB cable for any obvious damage.
- Firmly plug one end of the USB cable into the printer, and the other end into the computer.

### Check your network connection.

Make sure the printer is connected to a working network connection.

### Check the network adapter documentation for setup and usage information.

## Memory Card Problems

### Make sure that the type of memory card you are using can be used in the printer.

For more information, see [Printing From a Memory Card or USB Key](#).

### Insert only one memory card at a time.

### Insert the memory card until it stops.

The printer will not read the contents of the memory card if it is not properly inserted into the memory card slot.

### When printing images from a memory card, make sure the file format of the images is supported by the printer.

Only images in JPG and a limited set of TIFF formats can be printed directly from the memory card. If you want to print photos stored on the memory card in a different file format, the photos must be transferred to your computer before printing.

### Ensure the printer is not connected to a PictBridge-enabled camera.

For more information, see [Printing Photos From a PictBridge-Enabled Camera](#).

## Paper Problems

### Make sure you loaded the paper correctly.

For more information, see [Loading Paper](#).

### Use only paper recommended for your printer.

For more information, see [Print Media Guidelines](#).

### Use a smaller amount of paper when printing multiple pages.

For more information, see [Print Media Guidelines](#).

### Make sure the paper is not wrinkled, torn, or damaged.

### Check for a paper jam.


If the paper jam is near the paper input tray:

1. Remove the paper tray.



2. Pull firmly on the paper to remove it.
3. Replace the paper tray.



4. Press the **Select** button .
5. Resend your print job to print any missing pages.

If the paper jam is not visible:


1. Turn off the printer.
2. Lift the printer unit.




3. Firmly grasp the paper, and gently pull it from the printer.
4. Close the printer unit.
5. Turn on the printer, and print the document again.

If the jam is located in the duplex unit or near the rear access door:

1. If you have a duplex unit, remove it.



2. Open the rear access door.
3. Firmly grasp the paper, and gently pull it from the printer.
4. Close the rear access door.
5. Re-install the duplex unit.
6. Press the **Select** button  to continue printing.

If the paper jam occurs near the ADF:

1. Lift the ADF cover located to the left of the ADF input tray.



2. Firmly grasp the paper, and then gently pull it from the printer.




3. Close the ADF cover.





















4. Press the **Select** button .

5. Resend your print job to print any missing pages.

## Error Messages

Error Message:	What it indicates:	Solution:
Alignment problem. Verify tape removed from cartridges, run a few cleaning cycles or check troubleshooting. Press  to retry	The tape was not removed from the ink cartridges before the cartridges were installed.	Remove the tape from the ink cartridges. For more information, see <a href="#">Replacing Ink Cartridges</a> .
There is a problem reading the memory card. Ensure that it is not damaged and is inserted correctly.	The memory card is inserted in the wrong slot.	Remove the memory card, and reinsert it into the correct slot. For more information, see <a href="#">Printing Photos</a> .
No valid photo image files detected.	The memory card or the USB key does not contain supported files.	Make sure that your photos are saved as JPG or TIFF.
Failed to retrieve the File from the Mass Storage Device.	The computer fails to retrieve the file from a memory card or a USB key.	Make sure that the memory card or USB key is not damaged.
Failed to find an MS Office application to print.	The computer fails to find an application to print.	Make sure that the memory card or USB key contains files that have *.DOC, *.XLS, or *.PPT as filename extensions.
The attached device is not a PictBridge or a supported Mass Storage Class Device. Please disconnect and refer to user manual.		Attach a PictBridge-enabled camera or a USB key into the PictBridge port.
Unplug device to use other printer features.	An unsupported device is attached or inserted into the PictBridge port.	Remove the unsupported device.
Paper or photo size error Change paper or photo setting in Camera or printer defaults	The size of the photo is greater than the paper size set.	<ul style="list-style-type: none"> <li>Choose a photo size that is smaller than the paper size.</li> <li>Choose a paper size that is greater than the photo size. If you want to print a borderless picture, choose a paper size that is the same size as the photo.</li> </ul>
The attached device is not a supported Bluetooth device. Please disconnect and refer to user manual.		Attach a USB Bluetooth adapter into the PictBridge port.
Left cartridge missing. Insert		Insert a black or photo cartridge in the left

Black or Photo Cartridge.		cartridge carrier. For more information, see <a href="#">Replacing Ink Cartridges</a> .
Right cartridge missing. Insert Color Cartridge.		Insert a color cartridge in the right cartridge carrier. For more information, see <a href="#">Replacing Ink Cartridges</a> .
Left cartridge error. Replace cartridge. Right cartridge error. Replace cartridge.		The cartridge is inserted in the wrong cartridge carrier. Insert the black or photo cartridge in the left carrier and the color cartridge in the right. For more information, see <a href="#">Replacing Ink Cartridges</a> .
Check the AIO for Obstructions, then press  .	A printhead carrier jam exists in the printer.	Clear the carrier jam, and then press the <b>Select</b> button  .
Error XXXX	If the LCD displays <b>Error</b> followed by a four-digit number, an advanced error has occurred.	Contact Customer Support. For more information, go to <a href="http://support.dell.com">support.dell.com</a> .
Paper Jam	A paper jam exists in the printer.	Clear the paper jam. For more information, see <a href="#">Check for a paper jam.</a>
Clear Automatic Document Feeder jam then press  .		Clear the paper jam in the ADF.
Low Ink Error	The ink cartridge is running low on ink. The <b>Low Ink Error</b> occurs when your ink cartridges reach levels of 25 percent, 15 percent, and 10 percent remaining.	Replace the ink cartridge. For more information, see <a href="#">Replacing Ink Cartridges</a> .
Document in Memory. Replace Cartridge to Print.	There is not enough ink to complete the print job.	Replace the ink cartridge, and align the new cartridges. The printer continues to print the remaining pages.
Paper Out	If you have an optional input paper tray and you loaded paper into both trays, Tray Linking is not enabled.	Enable Tray Linking. For more information, see <a href="#">Understanding Tray Linking</a> .
Media Mismatch	You have enabled Tray Linking and set the paper type to <b>Automatic</b> or <b>Auto-Detect</b> , but the paper loaded is not plain paper.	Press the <b>Select</b> button  to continue printing. Otherwise, press the <b>Cancel</b> button  , and then load plain paper.
Out of Memory. Unable to complete multiple copies. Press  .	The printer does not have enough memory to scan all the originals loaded into the ADF.	Press the <b>Select</b> button  to print the pages that were scanned. Reload the originals that were not scanned, and make copies of them.
Faxes in memory. Load plain paper and Press  .	The printer received incoming faxes, but there is no plain paper loaded in the input tray.	Load plain paper in the input tray, and then press the <b>Select</b> button  .
Fax Received. Load Paper, then select size to print fax.	There is an incoming fax, but the paper loaded is not supported.	Load a plain Letter, Legal, or A4 size paper into the input tray, and then select the paper size.
Unsupported Fax Mode	The <b>Auto Fax Conversion</b> option is off, and the receiving fax machine does not support color or the resolution of the fax you are sending.	Turn <b>Auto Fax Conversion</b> on.  <ol style="list-style-type: none"> <li>1. From the main menu, press the up or down <b>Arrow</b> button  to scroll to Fax, and then press the <b>Select</b> button .</li> <li>2. Press the up or down <b>Arrow</b> button  to scroll to Fax Setup, and then press the <b>Select</b> button .</li> <li>3. Press the up or down <b>Arrow</b> button  to scroll to Dialing and Sending, and then press the <b>Select</b> button .</li> <li>4. Press the up or down <b>Arrow</b> button  to scroll to Auto Fax Conversion, and then press the left or right <b>Arrow</b> button  to scroll to On.</li> <li>5. Press the <b>Back</b> button .</li> </ol>

---

## Improving Print Quality

If you are not satisfied with the print quality of your documents, there are several different ways to improve the print quality.

- Use the appropriate paper. For example, use Dell™ Premium Photo Paper if you are printing photos with a photo ink cartridge.
- Use paper that is a heavier weight, bright white, or coated. Use Dell Premium Photo Paper if you are printing photos.

 **NOTE:** Dell Premium Photo Paper may not be available in all areas.

- Select a higher print quality.

To select a higher print quality:

1. With your document open, click **File® Print**.

The **Print** dialog box opens.

2. Click **Preferences**, **Properties**, **Options**, or **Setup** (depending on the program or operating system).

The **Printing Preferences** dialog box opens.

3. On the **Print Setup** tab, select a higher quality setting.

4. Print your document again.

5. If the print quality does not improve, try aligning or cleaning the ink cartridges. For more information, see [Aligning Ink Cartridges](#) and [Cleaning the Ink Cartridge Nozzles](#).

For additional solutions, go to [support.dell.com](http://support.dell.com).

---

## General Guidelines for Selecting or Loading Print Media

- Attempting to print on damp, curled, wrinkled, or torn paper can cause paper jams and poor print quality.
- Use only high-quality, copier-grade paper for the best print quality.
- Avoid paper with embossed lettering, perforations, or a texture that is too smooth or rough. Paper jams may occur.
- Store paper in its packaging until you are ready to use it. Place cartons on pallets or shelves, not on the floor.
- Do not place heavy objects on top of the media, whether or not it is packaged.
- Keep paper away from moisture or other conditions that can cause it to wrinkle or curl.
- Store unused paper at temperatures ranging between 15°C and 30°C (59°F and 86°F). The relative humidity should be between 10% and 70%.
- During storage, you should use moisture-proof wrap, such as a plastic container or bag, to prevent dust and moisture from contaminating the paper.

---

## Avoiding Jams and Misfeeds

You can avoid most jams and misfeeds by following these guidelines:

- Use media that follows the printer's Media Guidelines.
- Make sure that the media is properly loaded in the input tray.
- Do not overload the input tray.
- Do not remove media from the input tray while printing.
- Flex, fan, and straighten the paper before loading.
- Do not use creased, damp, or curled paper.
- Orient the media according to the instructions for the printer.


# Printing From a Memory Card or USB Key

- [Printing Photos](#)
- [Altering Photos Before Printing](#)
- [Printing Microsoft Office Files](#)


Most digital cameras use a memory card to store photos. The printer supports the following digital media:


- Compact Flash Type I and II
- Memory Stick
- Memory Stick PRO
- Memory Stick Duo (with adapter)
- Mini SD (with adapter)
- Microdrive
- Secure Digital
- MultiMedia Card
- xD-Picture Card

Memory cards should be inserted with the label facing up. The card reader has four slots to accommodate these media and a small light that blinks indicating the card is being read or is transmitting data.


 **NOTE:** Do not insert more than one memory card at a time. Do not insert a memory card if there is already a USB key inserted in the printer.

The connector that is used for PictBridge may also be used for accessing information stored on USB Flash Drive devices.

 **NOTE:** Do not insert a USB key if there is already a memory card inserted in the printer.

 **NOTICE:** Do not remove the memory card or USB key, or touch the printer near the area of the memory card or USB key while actively reading, writing, or printing from these devices. Data corruption can occur.

When you insert a memory card or USB key, the printer automatically switches to **Photo** mode.

 **NOTE:** The printer supports FAT32 data format. Files stored in NTFS should be converted to FAT32 data format.


---



## Printing Photos







### Viewing or Printing Photos


1. Insert a memory card or USB key.

The printer automatically switches to **Photo** mode.





2. Press the **Select** button  to access the **Photo Card Mode** menu.

3. Press the up or down **Arrow** button  to scroll to **Browse** and **Print Photos**, and then press the **Select** button .

4. Press the left or right **Arrow** button   to scroll through the photos on the memory card or USB key.
5. Press the **Select** button  to select a photo for printing.
6. Press the up or down **Arrow** button   to specify the number of copies.
7. Press the **Start** button .

 **NOTE:** Only photos in JPG format can be directly printed from the memory card or USB key. If you want to print photos stored on the memory card or USB key in a different file format, the photos must be transferred to your computer before printing.

## Saving Photos to Your Computer








1. Insert the memory card or USB key. The printer automatically switches to the **Photo** mode.
2. Press the up or down **Arrow** button   to scroll to **Save Photos to Computer**, and then press the **Select** button .
3. Press the **Start** button .

The **Memory Card Manager** launches on your computer.








4. Follow the instructions on the **Memory Card Manager** dialog box on how to transfer the photos to your computer.


## Viewing a Slide Show

You can view all the photos stored on a memory card or USB key through a slide show.

1. Insert a memory card or USB key. The printer automatically switches to **Photo** mode.
2. Press the **Select** button  to access the **Photo Card Mode** menu.
3. Press the up or down **Arrow** button   to scroll to **View Slideshow**, and then press the **Select** button .
4. Press the up or down **Arrow** button   to select the speed of the slide show, and then press the **Select** button .


## Printing All Photos






1. Insert the memory card or USB key. The printer automatically switches to **Photo** mode.
2. Press the **Select** button  to access the **Photo Card Mode** menu.
3. Press the up or down **Arrow** button   to scroll to **Print All Photos**, and then press the **Select** button .
4. Press the up or down **Arrow** button   to choose the number of photos that will be printed on a page, and then press the **Select** button .

 **NOTE:** Only images in JPG and a limited set of TIFF formats can be printed directly from the memory card or USB key. If you want to print photos stored on the memory card or USB key in a different file format, the photos must be transferred to your computer before printing.












## Printing a DPOF Selection

If your camera supports DPOF, you can specify which photos to print, and how many of each, while the memory card is still in the camera. The printer recognizes these settings when you insert the memory card into the printer.






 **NOTE:** If you specified a paper size in the DPOF selection, make sure the size of the paper loaded is not smaller than the size you specified.

1. Insert a memory card. The printer automatically switches to **Photo** mode.
  2. Press the up or down **Arrow** button   to scroll to `Print Camera Selections`, and then press the **Select** button .
  3. Press the **Select** button  to display the DPOF selection you specified.  
  
A preview of the print job appears.
  4. Press the **Start** button  to print the photos.
- 

## Altering Photos Before Printing

1. Insert a memory card or USB key. The printer automatically switches to **Photo** mode.
2. Press the **Select** button  to enter the **Photo Card Mode** menu.
3. Press the up or down **Arrow** button   to scroll to `Browse and Print Photos`, and then press the **Select** button .
4. Press the left or right **Arrow** button   to scroll to the photo you want to edit, and then press the **Select** button .
5. Press the **Menu** button .
6. From the **Photo Menu**, press the up or down **Arrow** button   to scroll to `Edit Photo`, and then press the **Select** button .





The menu items appear beside the photo you want to edit.




7. Press the up or down **Arrow** button   to scroll through the menu items.
  8. Press the left or right **Arrow** button   to scroll through the options for each menu item.
  9. Press the **Back** button .
- 

## Printing Microsoft Office Files

1. Turn on your computer and printer and make sure they are connected.
2. Insert a memory card into a card slot or a USB key into the PictBridge port.

The printer automatically switches to **Print Files** mode if there are only Microsoft Office files stored on the memory card or USB key. Only Microsoft Office files that have filename extensions \*.DOC, \*.XLS, and \*.PPT. are recognized.

 **NOTE:** The printer automatically switches to **Photo** mode if there are photos stored on the memory card or USB key. Press the **Back** button  to exit the **Photo** menu, press the up or down **Arrow** button   to scroll to `Print Files`, and then press the **Select** button .

3. Press the  button to access the **Print Files Mode** menu.
4. Press the up or down **Arrow** button  to scroll to the file that you want to print.
5. Press the **Start** button .



# Specifications

- [Overview](#)
- [Environmental Specifications](#)
- [Power Consumption and Requirements](#)
- [Fax Mode Capabilities](#)
- [Print and Scan Mode Capabilities](#)
- [Operating System Support](#)
- [Memory Specifications and Requirements](#)
- [Media Types and Sizes](#)
- [Cables](#)

## Overview

Memory	<ul style="list-style-type: none"><li>32 MB SDRAM</li><li>4 MB FLASH</li><li>4 MB Fax</li></ul>
Connectivity	USB 2.0 high-speed
Duty cycle (average)	5,000 pages per month
Printer life	<ul style="list-style-type: none"><li>Printer: 18,000 pages</li><li>Scanner: 18,000 scans</li><li>ADF: 18,000 scans</li></ul>

## Environmental Specifications

### Temperature/Relative Humidity

Condition	Temperature	Relative humidity (non-condensing)
Operation	61° to 90° F	8 to 80%
Storage	34° to 140° F	5 to 80%
Shipping	-40° to 140° F	5 to 100%


## Power Consumption and Requirements


Rated AC input	90–255 V
Rated frequency	47 Hz to 63 Hz
Minimum AC input	90 VAC
Maximum AC input	255 VAC
Maximum input current	1.0 A
Average power consumption	
Standby mode	< 10 W

## Fax Mode Capabilities

When you scan to fax, your document will scan in at 200 dpi (dots per inch). You can fax black and white documents.

For faxing to work properly, the printer must be able to access a computer connected to an active analog telephone line.

 **NOTE:** If you are faxing over a telephone line connected to a DSL modem, install a DSL filter to avoid interference with the analog fax modem signal.

 **NOTE:** ISDN (integrated service digital network) and cable modems are not fax modems and are not supported for faxing.

## Print and Scan Mode Capabilities

Your printer can scan from 72 to 19,200 dpi. Although your printer has this capability, Dell™ recommends using the preset resolutions.

Print and scan resolution	Scan resolution	Print resolution	
		Photo/Glossy paper	All other media
Draft	150 x 150 dpi	600 x 600 dpi	300 x 600 dpi
Normal	300 x 300 dpi	1200 x 1200 dpi	600 x 600 dpi
Photo	600 x 600 dpi	4800 x 1200 dpi	1200 x 1200 dpi

## Operating System Support

The printer supports:

- Windows XP Professional x64
- Windows XP
- Windows 2000
- Windows Vista

## Memory Specifications and Requirements

Your operating system must meet the minimum system requirements.

Operating System	Processor speed (MHz)	RAM (MB)	Hard disk
Windows XP Professional x64	AMD Athlon 64, AMD Opteron, Intel Xeon with Intel EM64T support, or Intel Pentium 4 with Intel EM64T support	256	1.5 GB
Windows XP	Pentium II 300	128	500 MB
Windows 2000	Pentium II 233	128	500 MB
Windows Vista	800 MHz	512	20 GB (15 GB free space)

---

## Media Types and Sizes

Media type:	Sizes supported:	Load up to:
Plain paper	<ul style="list-style-type: none"><li>• Letter: 8.5 x 11 inches (216 x 279 mm)</li><li>• A4: 8.27 x 11.69 inches (210 x 297 mm)</li><li>• Legal: 8.5 x 14 inches (216 x 355.6 mm)</li></ul>	150 sheets
Banner paper	<ul style="list-style-type: none"><li>• A4 Banner</li><li>• Letter Banner</li></ul>	20 sheets
Envelopes	<ul style="list-style-type: none"><li>• 9 Envelopes: 3 7/8 x 8 7/8 inches</li><li>• 10 Envelopes: 4 1/8 x 9 1/2 inches</li><li>• 6 3/4 Envelopes: 3 1/4 x 6 1/2 inches</li><li>• 7 3/4 Envelopes: 3 7/8 x 7 1/2 inches</li><li>• A2 Baronial Envelopes: 111 x 146 mm</li><li>• B5 Envelopes: 176 x 250 mm</li><li>• C5 Envelopes: 162 x 229 mm</li><li>• C6 Envelopes: 114 x 162 mm</li><li>• DL Envelopes: 110 x 220 mm</li><li>• Chokei 3 Envelopes: 120 x 235 mm</li><li>• Chokei 4 Envelopes: 90 x 205 mm</li><li>• Chokei 40 Envelopes: 90 x 225 mm</li><li>• Kakugata 3 Envelopes: 216 x 277 mm</li><li>• Kakugata 4 Envelopes: 197 x 267 mm</li><li>• Kakugata 5 Envelopes: 190 x 240 mm</li><li>• Kakugata 6 Envelopes: 162 x 229 mm</li></ul>	10 envelopes
Greeting cards, index cards, postcards, or photo cards	<ul style="list-style-type: none"><li>• Photo/Post card: 4 x 6 inches</li><li>• Index card: 3 x 5 inches</li></ul>	25 cards
Photo/glossy or matte paper	<ul style="list-style-type: none"><li>• 8.5 x 11 inches (216 x 279 mm)</li><li>• A4: 8.27 x 11.69 inches (210 x 297 mm)</li><li>• 4 x 6 inches (101.6 x 152.4 mm)</li></ul>	50 sheets
Iron-on transfers	<ul style="list-style-type: none"><li>• 8.5 x 11 inches (216 x 279 mm)</li><li>• A4: 8.27 x 11.69 inches (210 x 297 mm)</li></ul>	10 mm stack
Transparencies	<ul style="list-style-type: none"><li>• 8.5 x 11 inches (216 x 279 mm)</li><li>• A4: 8.27 x 11.69 inches (210 x 297 mm)</li></ul>	50 transparencies
Custom size paper	The paper must fit the following dimensions: <ul style="list-style-type: none"><li>• Width: 3.0 – 8.5 inches (76 – 216 mm)</li><li>• Length: 5.0 – 17.0 inches (127 – 432 mm)</li></ul>	150 sheets

---

## Cables

Your printer uses a Universal Serial Bus (USB) cable (sold separately).



# Copying



- [Copying Documents](#)
  - [Collating Copies](#)
  - [Copying Photos](#)
  - [Copying a Two-sided Document](#)
  - [Making a Duplex Copy](#)
  - [Changing Copy Settings](#)
- 

## Copying Documents



### Using the Operator Panel

1. Turn on the printer.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load your original document.



4. Press the **Menu** button  to change copy settings.
5. Press the **Start** button .

The copy is made in the currently specified copy selection (Color or Black).

 **NOTE:** If you press the **Start** button  without specifying a copy selection, the copy is printed in color by default.


### Using the Computer

1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load your original document.




4. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click ® **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
5. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

6. Select the number of copies (1–99), and then specify the color setting from the **Copy** drop-down menu.

 **NOTE:** You must make more than one copy before you can collate documents.

7. Click **See More Copy Settings** to customize your copy.
8. Click the **Advanced** button.

The **Advanced Copy Settings** dialog box opens.

9. On the **Print** tab, select the **Collate Copies** check box.
10. Click **OK**.
11. When you are finished customizing your settings, click **Copy Now**.







---


## Collating Copies







### Using the Operator Panel

1. Turn on your printer.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load your original document.



4. From the main menu, press the up or down **Arrow** button   to scroll to **Copy**, and then press the **Select** button.
5. Press the up or down **Arrow** button   to scroll to **Copies**, and then press the left or right **Arrow** button   to specify the number of copies (1–99).

 **NOTE:** You must make more than one copy before you can collate documents.

6. Press the up or down **Arrow** button   to scroll to **Collate**, and then press the left or right **Arrow** button   to scroll to **On**.
7. Press the **Select** button .
8. Press the **Start** button .


## Using the Computer


1. Turn on your computer and printer, and make sure they are connected.
2. Load the paper. For more information, see [Loading Paper](#).
3. Load your original document.



4. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click ® **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
5. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  6. Select the number of copies (1–99), and then specify the color setting from the **Copy** drop-down menu.

 **NOTE:** You must make more than one copy before you can collate documents.

7. Click **See More Copy Settings** to customize your copy.
8. Click the **Advanced** button.

The **Advanced Copy Settings** dialog box opens.

9. On the **Print** tab, select the **Collate Copies** check box.






10. Click **OK**.
  11. When you are finished customizing your settings, click **Copy Now**.
- 

## Copying Photos

### Using the Operator Panel

1. Turn on the printer.
2. Load photo/glossy paper with the print side facing down. For more information, see [Loading Paper](#).
3. Load your original photo.



4. Press the up or down **Arrow** button  to scroll to **Copy**, and then press the **Select** button .
5. From the **Copy Mode** menu, press the up or down **Arrow** button  to scroll to **Content Type**.
6. Press the left or right **Arrow** button  to scroll to **Photo**.
7. Press the **Start** button .

### Using the Computer


1. Turn on your computer and printer, and make sure they are connected.
2. Load photo/glossy paper with the print side facing down. For more information, see [Loading Paper](#).
3. Load your original photo.





4. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.








For *Windows Vista*:


- a. Click ® **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
5. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  6. Click **Preview Now**.
  7. Adjust the dotted lines to fit around the portion of the image you want to print.
  8. Select the number of copies (1–99), and then specify the color settings from the **Copy** drop-down menu.
  9. Click **See More Copy Settings** to customize your copy.
  10. When you finish customizing your settings, click **Copy Now**.
- 

## Copying a Two-sided Document

1. Load the original document into the ADF.



2. From the main menu, press the up or down **Arrow** button   to scroll to **Copy**, and then press the **Select** button .
3. From the **Copy Mode** menu, press the up or down **Arrow** button   to scroll to **2-Sided Copies**.
4. Press the left or right **Arrow** button   to scroll to **2-Sided Original, 1 Sided Copy** (if you do not have the

optional duplex unit) or 2-Sided Original, 2-Sided Copy (if you have the optional duplex unit), and then press the **Select** button .


5. Press the **Start** button .

When the original document exits from the ADF, follow the instructions on your LCD.

---










## Making a Duplex Copy

Purchase and install an optional duplex unit to automatically perform duplex copies on your document. With an optional duplex unit, there is no need to manually re-orient the sheets. It picks the paper and allows the printer to print on the side that is still blank.

 **NOTE:** Use letter size or A4 plain paper for making duplex copies. Do *not* make duplex copies on envelopes, card stock, or photo paper.

1. Load the original document into the ADF.



2. From the main menu, press the up or down **Arrow** button   to scroll to **Copy**, and then press the **Select** button .
  3. From the **Copy Mode** menu, press the up or down **Arrow** button   to scroll to 2-Sided Copies.
  4. Press the left or right **Arrow** button   to scroll to 1-Sided Original, 2-Sided Copy (if you are copying a one-sided document) or 2-Sided Original, 2-Sided Copy (if you are copying a two-sided document), and then press the **Select** button .
  5. Press the **Start** button .
- 

## Changing Copy Settings

### Using the Operator Panel

If you are using your printer as a standalone copier, you can change the copy settings from the **Copy Mode** menus on the operator panel. For more information about settings, see [Copy Mode](#).

### Using the Computer

1. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click ® **Programs**.
- b. Click **Dell Printers**.

c. Click **Dell Photo AIO Printer 966**.

2. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

3. Select the number of copies (1–99) and color setting from the **Copy** drop-down menu.

4. Click **See More Copy Settings** to:

- Choose a copy quality.
- Select the paper size.
- Select the original document size.
- Lighten or darken your document.
- Reduce or enlarge your document.

5. Click the **Advanced** button to change options such as paper size and quality.

6. To make any changes, click the following tabs:

Click this tab:	To:
Print	<ul style="list-style-type: none"><li>• Select the paper size and type.</li><li>• Select borderless printing options.</li><li>• Select the print quality.</li><li>• Collate copies.</li><li>• Print the last page first.</li></ul>
Scan	<ul style="list-style-type: none"><li>• Select the color depth and scan resolution.</li><li>• Auto-crop the scanned image.</li><li>• Adjust the sensitivity of the auto-crop tool.</li><li>• Set the size of the area to be scanned.</li></ul>
Image Enhancements	<ul style="list-style-type: none"><li>• Straighten images after scan (deskew).</li><li>• Sharpen your blurry images.</li><li>• Adjust the brightness of your image.</li><li>• Adjust the color correction curve (gamma) of your image.</li></ul>
Image Patterns	<ul style="list-style-type: none"><li>• Smooth the conversion of a gray image to a black and white dot pattern.</li><li>• Remove image patterns from magazines or newspapers (descreen).</li><li>• Reduce the background noise on your color document.</li></ul>

7. Click **OK**.

8. When you are finished customizing your settings, click **Copy Now**.

# Appendix

- [Dell Technical Support Policy](#)
  - [Contacting Dell](#)
  - [Warranty and Return Policy](#)
- 

## Dell Technical Support Policy

Technician-assisted technical support requires the cooperation and participation of the customer in the troubleshooting process and provides for restoration of the Operating System, application software and hardware drivers to the original default configuration as shipped from Dell, as well as the verification of appropriate functionality of the printer and all Dell-installed hardware. In addition to this technician assisted technical support, online technical support is available at Dell Support. Additional technical support options may be available for purchase.

Dell provides limited technical support for the printer and any Dell-installed software and peripherals. Support for third-party software and peripherals is provided by the original manufacturer, including those purchased and/or installed through Software & Peripherals (DellWare), ReadyWare, and Custom Factory Integration (CFI/DellPlus).

---

## Contacting Dell

You can access Dell Support at [support.dell.com](http://support.dell.com). Select your region on the WELCOME TO DELL SUPPORT page, and fill in the requested details to access help tools and information.

You can contact Dell electronically using the following addresses:

- World Wide Web

[www.dell.com/](http://www.dell.com/)

[www.dell.com/ap/](http://www.dell.com/ap/) (Asian/Pacific countries only)

[www.dell.com/jp/](http://www.dell.com/jp/) (Japan only)

[www.euro.dell.com](http://www.euro.dell.com) (Europe only)

[www.dell.com/la/](http://www.dell.com/la/) (Latin American and Caribbean countries)

[www.dell.ca](http://www.dell.ca) (Canada only)

- Anonymous file transfer protocol (FTP)

[ftp.dell.com](http://ftp.dell.com)

Log in as user: anonymous, and use your email address as your password.

- Electronic Support Service

[mobile\\_support@us.dell.com](mailto:mobile_support@us.dell.com)

[support@us.dell.com](mailto:support@us.dell.com)

[la-techsupport@dell.com](mailto:la-techsupport@dell.com) (Latin America and Caribbean countries only)

[apsupport@dell.com](mailto:apsupport@dell.com) (Asian/Pacific countries only)

[support.jp.dell.com](mailto:support.jp.dell.com) (Japan only)

[support.euro.dell.com](mailto:support.euro.dell.com) (Europe only)

- Electronic Quote Service

[apmarketing@dell.com](mailto:apmarketing@dell.com) (Asian/Pacific countries only)

[sales\\_canada@dell.com](mailto:sales_canada@dell.com) (Canada only)

---

## Warranty and Return Policy

Dell Inc. ("Dell") manufactures its hardware products from parts and components that are new or equivalent to new in accordance with industry-standard practices. For information about the Dell warranty for your printer, refer to the *Owner's Manual*.

# Scanning

- [Scanning Single-page Documents or Photos](#)
  - [Scanning Multiple Photos](#)
  - [Scanning Multiple-page Documents](#)
  - [Scanning Across a Network](#)
  - [Setting the Computer Name and PIN](#)
  - [Editing Scanned Text Using Optical Character Recognition \(OCR\)](#)
  - [Editing Scanned Images](#)
  - [Saving an Image on Your Computer](#)
  - [E-Mailing a Scanned Image or Document](#)
  - [Enlarging or Reducing Images or Documents](#)
  - [Changing Scan Settings](#)
- 

## Scanning Single-page Documents or Photos


1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document or photo.



3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:


- a. Click **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  5. From the **Send scanned image to:** drop-down menu, select the program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add the program to the list.

6. Click **See More Scan Settings** to customize your scan.

7. When you finish customizing your settings, click **Scan Now**.
- 

## Scanning Multiple Photos


 **NOTE:** Some programs do not support multiple-page scanning.

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original photo.




3. Click **Start**® **Programs** or **All Programs**® **Dell Printers**® **Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click ® **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

5. From the **Send scanned image to:** drop-down menu, select the program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add your program to the list.

6. Click **See More Scan Settings** to customize your scan.
7. Click the **Advanced** button.

The **Advanced Scan Settings** dialog box opens.

8. On the **Scan** tab, select the **Scan multiple items before output** check box.
9. Click **OK**.
10. When you finish customizing your settings, click **Scan Now**.


After you scan the first page, a prompt appears requesting the next page.

11. Place the next photo on the scanner glass, and click **Yes**. Repeat until you finish scanning all photos.
12. Click **No** when asked for another page.

The program opens with the multiple photos scanned.

---

## Scanning Multiple-page Documents


 **NOTE:** Some programs do not support multiple-page scanning.

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.




3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

5. From the **Send scanned image to:** drop-down menu, select the program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add your program to the list.

6. Click **See More Scan Settings** to customize your scan.
  7. When you finish customizing your settings, click **Scan Now**.
- 

## Scanning Across a Network




1. Make sure your computer is attached to the network.

 **NOTE:** Dell™ printers can only be attached to a network using a Dell Network Adapter (sold separately).


2. Turn on your computer and printer, and make sure they are connected.
3. Load your original document.







4. From the main menu, press the up or down **Arrow** button   to scroll to *Scan*, and then press the **Select** button .



The printer automatically detects if it is connected to a network. If it is connected to a network, the **Host Selection** screen appears. If it is not connected to a network, the **Scan Mode** menu appears.

5. From the **Host Selection** screen, choose the computer to which you want to send the document, and then press the **Select** button .

 **NOTE:** The computer must have the printer software installed. Use the *Drivers and Utilities* CD to install the printer software.

6. Enter the four-digit PIN specified for the host computer.

 **NOTE:** You can view or change the PIN or the name of the computer to which you want to send your scan. For more information, see [Setting the Computer Name and PIN](#). The PIN is not required by default; it is only requested if the PIN has been set.

7. Press the **Select** button .
8. Make any necessary changes to your scan settings, and then press the **Start** button .

The scan opens on the computer you selected.


---

## Setting the Computer Name and PIN

Set a scan-to-network PIN to restrict users from sending a scanned document to your computer. You can also specify a name for your computer which you need to select when scanning across a network.

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
2. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  3. Click **Maintain/Troubleshoot**.
  4. From the **Maintain/Troubleshoot** window, click **Maintain or fix quality problems**.

The **Printing Preferences** dialog opens.

5. From the **Maintenance** tab, click **Network Support**.


6. From the **Dell Networking Options** dialog, click **Change your PC name and PIN for network scanning**.
7. Follow the instructions on the screen.
8. When you have specified a computer name or a PIN, click **OK**.

---

## Editing Scanned Text Using Optical Character Recognition (OCR)

OCR software converts a scanned image to editable text within a word-processing program. A copy of OCR software was provided with your printer and should have installed at the same time as your printer software.

 **NOTE:** If you downloaded your printer drivers and software from the Dell website, OCR software was not included.


 **NOTE:** For customers using Japanese or Simplified Chinese, ensure you have OCR software installed on your computer.

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.



3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.


For *Windows Vista*:

- a. Click  **Programs**.
- b. Click **Dell Printers**.
- c. Click **Dell Photo AIO Printer 966**.

4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

5. From the **Send scanned images to:** drop-down menu, select the text-editing program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more** in the drop-down menu. On the next screen, click **Add** to locate and add your program to the list.

6. Click **See More Scan Settings** to customize your scan.
7. Click the **Advanced** button.

The **Advanced Scan Settings** dialog box opens.

8. On the **Scan** tab, ensure the **Convert scanned item to text (OCR)** check box is selected.
9. Click **OK**.
10. When you finish customizing your settings, click **Scan Now**.

The scanned text opens in the program you selected.

---


## Editing Scanned Images

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.




3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

5. From the **Send scanned image to:** drop-down menu, select the program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add your program to the list.

6. Click **See More Scan Settings** to customize your scan.
7. When you finish customizing your settings, click **Scan Now**.

When the image has finished processing, it opens in the program you selected.

8. Edit the image using the tools available in your program. You may be able to:
  - Remove red eye
  - Crop your image
  - Add text to your image
  - Adjust the brightness and contrast of your image

For more information, refer to the documentation that came with your graphics program.

---


## Saving an Image on Your Computer

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.



3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  5. From the **Productivity Tools** section, click **Save an image on my computer**.
  6. Follow the instructions on your screen to save an image on your computer.

---


## E-Mailing a Scanned Image or Document


1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.



3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.  
The **Dell All-In-One Center** opens.
  5. From the **Productivity Tools** section, click **E-mail an image or document**.
  6. Follow the instructions on the screen to prepare the document for e-mail.
  7. Click **Next**.
  8. Open your e-mail program, write a note to accompany the attached document, and then send it.

 **NOTE:** If you have questions about attaching documents to e-mail, consult the Help for your e-mail program.

---


## Enlarging or Reducing Images or Documents

1. Turn on your computer and printer, and make sure they are connected.
2. Load your original document.




3. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.
  - b. Click **Dell Printers**.
  - c. Click **Dell Photo AIO Printer 966**.
4. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

5. Click **Preview Now**.

 **NOTE:** If the size of the scan (found in the upper right corner of the preview window) appears in red, you do not have the system resources available to perform the scan at the resolution or size you have selected. To correct this problem, reduce either your resolution or the size of your scan area.

6. From the **Productivity Tools** section, select **Enlarge or reduce an image**.
  7. Follow the instructions on the screen to select the size of your new image.
  8. When you finish customizing your image, click **Scan Now**.
- 

## Changing Scan Settings

### Using the Operator Panel

You can change the copy settings from the **Scan Mode** menu on the operator panel. For more information about settings, see [Scan Mode](#).

### Using the Computer

1. Click **Start® Programs** or **All Programs® Dell Printers® Dell Photo AIO Printer 966**.

For *Windows Vista*:

- a. Click  **Programs**.


b. Click **Dell Printers**.

c. Click **Dell Photo AIO Printer 966**.

2. Select **Dell All-In-One Center**.

The **Dell All-In-One Center** opens.

3. From the **Send scanned images to:** drop down menu, select the program you want to use.

 **NOTE:** If the program you want to use is not listed, select **Search for more...** in the drop-down menu. On the next screen, click **Add** to locate and add the program to the list.

4. Click **See More Scan Settings** to:

- Select what kind of document is being scanned.
- Select a scan quality.

5. Click the **Advanced** button to change options such as paper size and quality.

6. To make any changes, click the following tabs:

Click this tab:	To:
Scan	<ul style="list-style-type: none"><li>• Choose a color depth.</li><li>• Select a scan resolution.</li><li>• Adjust the sensitivity of the auto-drop tool.</li><li>• Set the area to be scanned.</li><li>• Use the OCR program to convert scanned items to text.</li><li>• Indicate that you are scanning multiple items.</li><li>• Update the list of applications to send scans to.</li><li>• Update the default fax driver.</li></ul>
Image Enhancements	<ul style="list-style-type: none"><li>• Straighten images after scan (deskew).</li><li>• Sharpen your blurry images.</li><li>• Adjust the brightness of your image.</li><li>• Adjust the color correction curve (gamma) of your image.</li></ul>
Image Patterns	<ul style="list-style-type: none"><li>• Smooth the conversion of a gray image to a black and white dot pattern.</li><li>• Remove image patterns from magazines or newspapers (descreen).</li><li>• Reduce the background noise on your color document.</li></ul>

7. Click **OK**.

8. When you are finished customizing your settings, click **Scan Now**.

# Licensing Notice

[BSD License and Warranty statements](#)

[GNU License](#)

The printer resident software contains:

- Software developed and copyrighted by Dell and/or third parties
- Dell modified software licensed under the provisions of the GNU General Public License version 2 and the GNU Lesser General Public License version 2.1
- Software licensed under the BSD license and warranty statements
- Software based in part on the work of the Independent JPEG Group.

The Dell modified GNU licensed software is free software; you can redistribute it and/or modify it under the terms of the licenses referenced above. These licenses do not provide you any rights to the Dell- or third-party-copyrighted software in this printer.

Since the GNU licensed software that the Dell modifications are based upon is supplied explicitly without warranty, use of the Dell modified version is similarly provided without warranty. See the warranty disclaimers in the referenced licenses for additional details.

---

## BSD License and Warranty statements

Copyright (c) 1991 The Regents of the University of California. All rights reserved.

Redistribution and use in source and binary forms, with or without modification, are permitted provided that the following conditions are met:

1. Redistributions of source code must retain the above copyright notice, this list of conditions and the following disclaimer.
2. Redistributions in binary form must reproduce the above copyright notice, this list of conditions and the following disclaimer in the documentation and/or other materials provided with the distribution.
3. The name of the author may not be used to endorse or promote products derived from this software without specific prior written permission.

THIS SOFTWARE IS PROVIDED BY THE AUTHOR ``AS IS'' AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE AUTHOR BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

---

## GNU License

GENERAL PUBLIC LICENSE

Version 2, June 1991

Copyright (C) 1989, 1991 Free Software Foundation, Inc.

59 Temple Place, Suite 330, Boston, MA 02111-1307 USA

Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.



## Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public License is intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users. This General Public License applies to most of the Free Software Foundation's software and to any other program whose authors commit to using it. (Some other Free Software Foundation software is covered by the GNU Library General Public License instead.) You can apply it to your programs, too.

When we speak of free software, we are referring to freedom, not price. Our General Public Licenses are designed to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish), that you receive source code or can get it if you want it, that you can change the software or use pieces of it in new free programs; and that you know you can do these things.

To protect your rights, we need to make restrictions that forbid anyone to deny you these rights or to ask you to surrender the rights. These restrictions translate to certain responsibilities for you if you distribute copies of the software, or if you modify it.

For example, if you distribute copies of such a program, whether gratis or for a fee, you must give the recipients all the rights that you have. You must make sure that they, too, receive or can get the source code. And you must show them these terms so they know their rights.

We protect your rights with two steps: (1) copyright the software, and (2) offer you this license which gives you legal permission to copy, distribute and/or modify the software.

Also, for each author's protection and ours, we want to make certain that everyone understands that there is no warranty for this free software. If the software is modified by someone else and passed on, we want its recipients to know that what they have is not the original, so that any problems introduced by others will not reflect on the original authors' reputations.

Finally, any free program is threatened constantly by software patents. We wish to avoid the danger that redistributors of a free program will individually obtain patent licenses, in effect making the program proprietary. To prevent this, we have made it clear that any patent must be licensed for everyone's free use or not licensed at all.

The precise terms and conditions for copying, distribution and modification follow.

## GNU GENERAL PUBLIC LICENSE

### TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License applies to any program or other work which contains a notice placed by the copyright holder saying it may be distributed under the terms of this General Public License. The "Program", below, refers to any such program or work, and a "work based on the Program" means either the Program or any derivative work under copyright law: that is to say, a work containing the Program or a portion of it, either verbatim or with modifications and/or translated into another language. (Hereinafter, translation is included without limitation in the term "modification".) Each licensee is addressed as "you". Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The act of running the Program is not restricted, and the output from the Program is covered only if its contents constitute a work based on the Program (independent of having been made by running the Program). Whether that is true depends on what the Program does.

1. You may copy and distribute verbatim copies of the Program's source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and give any other recipients of the Program a copy of this License along with the Program.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Program or any portion of it, thus forming a work based on the Program, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

a. You must cause the modified files to carry prominent notices stating that you changed the files and the date of any change.

b. You must cause any work that you distribute or publish, that in whole or in part contains or is derived from the Program or any part thereof, to be licensed as a whole at no charge to all third parties under the terms of this License.

c. If the modified program normally reads commands interactively when run, you must cause it, when started running for such interactive use in the most ordinary way, to print or display an announcement including an appropriate copyright notice and a notice that there is no warranty (or else, saying that you provide a warranty) and that users may redistribute the program under these conditions, and telling the user how to view a copy of this License. (Exception: if the Program itself is interactive but does not normally print such an announcement, your work based on the Program is not required to print an announcement.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Program, and can be reasonably considered independent and separate works in themselves, then this License, and its

terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Program, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Program.

In addition, mere aggregation of another work not based on the Program with the Program (or with a work based on the Program) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may copy and distribute the Program (or a work based on it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you also do one of the following:

- a. Accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- b. Accompany it with a written offer, valid for at least three years, to give any third party, for a charge no more than your cost of physically performing source distribution, a complete machine-readable copy of the corresponding source code, to be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange; or,
- c. Accompany it with the information you received as to the offer to distribute corresponding source code. (This alternative is allowed only for noncommercial distribution and only if you received the program in object code or executable form with such an offer, in accord with Subsection b above.)

The source code for a work means the preferred form of the work for making modifications to it. For an executable work, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the executable. However, as a special exception, the source code distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

If distribution of executable or object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place counts as distribution of the source code, even though third parties are not compelled to copy the source along with the object code.

4. You may not copy, modify, sublicense, or distribute the Program except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense or distribute the Program is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

5. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Program or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Program (or any work based on the Program), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Program or works based on it.

6. Each time you redistribute the Program (or any work based on the Program), the recipient automatically receives a license from the original licensor to copy, distribute or modify the Program subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties to this License.

7. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Program at all. For example, if a patent license would not permit royalty-free redistribution of the Program by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Program.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system, which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

8. If the distribution and/or use of the Program is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Program under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

9. The Free Software Foundation may publish revised and/or new versions of the General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns.

Each version is given a distinguishing version number. If the Program specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Program does not specify a version number of this License, you may choose any version ever published by the Free Software Foundation.

10. If you wish to incorporate parts of the Program into other free programs whose distribution conditions are different, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

#### NO WARRANTY

11. BECAUSE THE PROGRAM IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE PROGRAM, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE PROGRAM "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PROGRAM IS WITH YOU. SHOULD THE PROGRAM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

12. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE PROGRAM AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PROGRAM (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE PROGRAM TO OPERATE WITH ANY OTHER PROGRAMS), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

#### END OF TERMS AND CONDITIONS

#### How to Apply These Terms to Your New Programs

If you develop a new program, and you want it to be of the greatest possible use to the public, the best way to achieve this is to make it free software which everyone can redistribute and change under these terms.

To do so, attach the following notices to the program. It is safest to attach them to the start of each source file to most effectively convey the exclusion of warranty; and each file should have at least the "copyright" line and a pointer to where the full notice is found.

1 April 1989

Lexmark International, Inc.

This General Public License does not permit incorporating your program into proprietary programs. If your program is a subroutine library, you may consider it more useful to permit linking proprietary applications with the library. If this is what you want to do, use the GNU Library General Public License instead of this License.

#### GNU LESSER GENERAL PUBLIC LICENSE

Version 2.1, February 1999

Copyright (C) 1991, 1999 Free Software Foundation, Inc.

59 Temple Place, Suite 330, Boston, MA 02111-1307 USA

Everyone is permitted to copy and distribute verbatim copies of this license document, but changing it is not allowed.

[This is the first released version of the Lesser GPL. It also counts as the successor of the GNU Library Public License, version 2, hence the version number 2.1.]

#### Preamble

The licenses for most software are designed to take away your freedom to share and change it. By contrast, the GNU General Public Licenses are intended to guarantee your freedom to share and change free software--to make sure the software is free for all its users.

This license, the Lesser General Public License, applies to some specially designated software packages--typically libraries--of the Free Software Foundation and other authors who decide to use it. You can use it too, but we suggest you first think carefully about whether this license or the ordinary General Public License is the better strategy to use in any particular case, based on the explanations below.

When we speak of free software, we are referring to freedom of use, not price. Our General Public Licenses are designed

to make sure that you have the freedom to distribute copies of free software (and charge for this service if you wish); that you receive source code or can get it if you want it; that you can change the software and use pieces of it in new free programs; and that you are informed that you can do these things.

To protect your rights, we need to make restrictions that forbid distributors to deny you these rights or to ask you to surrender these rights. These restrictions translate to certain responsibilities for you if you distribute copies of the library or if you modify it.

For example, if you distribute copies of the library, whether gratis or for a fee, you must give the recipients all the rights that we gave you. You must make sure that they, too, receive or can get the source code. If you link other code with the library, you must provide complete object files to the recipients, so that they can relink them with the library after making changes to the library and recompiling it. And you must show them these terms so they know their rights.

We protect your rights with a two-step method: (1) we copyright the library, and (2) we offer you this license, which gives you legal permission to copy, distribute and/or modify the library.

To protect each distributor, we want to make it very clear that there is no warranty for the free library. Also, if the library is modified by someone else and passed on, the recipients should know that what they have is not the original version, so that the original author's reputation will not be affected by problems that might be introduced by others.

Finally, software patents pose a constant threat to the existence of any free program. We wish to make sure that a company cannot effectively restrict the users of a free program by obtaining a restrictive license from a patent holder. Therefore, we insist that any patent license obtained for a version of the library must be consistent with the full freedom of use specified in this license.

Most GNU software, including some libraries, is covered by the ordinary GNU General Public License. This license, the GNU Lesser General Public License, applies to certain designated libraries, and is quite different from the ordinary General Public License. We use this license for certain libraries in order to permit linking those libraries into non-free programs.

When a program is linked with a library, whether statically or using a shared library, the combination of the two is legally speaking a combined work, a derivative of the original library. The ordinary General Public License therefore permits such linking only if the entire combination fits its criteria of freedom. The Lesser General Public License permits more lax criteria for linking other code with the library.

We call this license the "Lesser" General Public License because it does Less to protect the user's freedom than the ordinary General Public License. It also provides other free software developers Less of an advantage over competing non-free programs. These disadvantages are the reason we use the ordinary General Public License for many libraries. However, the Lesser license provides advantages in certain special circumstances.

For example, on rare occasions, there may be a special need to encourage the widest possible use of a certain library, so that it becomes a de-facto standard. To achieve this, non-free programs must be allowed to use the library. A more frequent case is that a free library does the same job as widely used non-free libraries. In this case, there is little to gain by limiting the free library to free software only, so we use the Lesser General Public License.

In other cases, permission to use a particular library in non-free programs enables a greater number of people to use a large body of free software. For example, permission to use the GNU C Library in non-free programs enables many more people to use the whole GNU operating system, as well as its variant, the GNU/Linux operating system.

Although the Lesser General Public License is Less protective of the users' freedom, it does ensure that the user of a program that is linked with the Library has the freedom and the wherewithal to run that program using a modified version of the Library.

The precise terms and conditions for copying, distribution and modification follow. Pay close attention to the difference between a "work based on the library" and a "work that uses the library". The former contains code derived from the library, whereas the latter must be combined with the library in order to run.

## GNU LESSER GENERAL PUBLIC LICENSE

### TERMS AND CONDITIONS FOR COPYING, DISTRIBUTION AND MODIFICATION

0. This License Agreement applies to any software library or other program which contains a notice placed by the copyright holder or other authorized party saying it may be distributed under the terms of this Lesser General Public License (also called "this License"). Each licensee is addressed as "you".

A "library" means a collection of software functions and/or data prepared so as to be conveniently linked with application programs (which use some of those functions and data) to form executables.

The "Library", below, refers to any such software library or work which has been distributed under these terms. A "work based on the Library" means either the Library or any derivative work under copyright law: that is to say, a work containing the Library or a portion of it, either verbatim or with modifications and/or translated straightforwardly into another language. (Hereinafter, translation is included without limitation in the term "modification".)

"Source code" for a work means the preferred form of the work for making modifications to it. For a library, complete source code means all the source code for all modules it contains, plus any associated interface definition files, plus the scripts used to control compilation and installation of the library.

Activities other than copying, distribution and modification are not covered by this License; they are outside its scope. The

act of running a program using the Library is not restricted, and output from such a program is covered only if its contents constitute a work based on the Library (independent of the use of the Library in a tool for writing it). Whether that is true depends on what the Library does and what the program that uses the Library does.

1. You may copy and distribute verbatim copies of the Library's complete source code as you receive it, in any medium, provided that you conspicuously and appropriately publish on each copy an appropriate copyright notice and disclaimer of warranty; keep intact all the notices that refer to this License and to the absence of any warranty; and distribute a copy of this License along with the Library.

You may charge a fee for the physical act of transferring a copy, and you may at your option offer warranty protection in exchange for a fee.

2. You may modify your copy or copies of the Library or any portion of it, thus forming a work based on the Library, and copy and distribute such modifications or work under the terms of Section 1 above, provided that you also meet all of these conditions:

a. The modified work must itself be a software library.

b. You must cause the files modified to carry prominent notices stating that you changed the files and the date of any change.

c. You must cause the whole of the work to be licensed at no charge to all third parties under the terms of this License.

d. If a facility in the modified Library refers to a function or a table of data to be supplied by an application program that uses the facility, other than as an argument passed when the facility is invoked, then you must make a good faith effort to ensure that, in the event an application does not supply such function or table, the facility still operates, and performs whatever part of its purpose remains meaningful.

(For example, a function in a library to compute square roots has a purpose that is entirely well-defined independent of the application. Therefore, Subsection 2d requires that any application-supplied function or table used by this function must be optional: if the application does not supply it, the square root function must still compute square roots.)

These requirements apply to the modified work as a whole. If identifiable sections of that work are not derived from the Library, and can be reasonably considered independent and separate works in themselves, then this License, and its terms, do not apply to those sections when you distribute them as separate works. But when you distribute the same sections as part of a whole which is a work based on the Library, the distribution of the whole must be on the terms of this License, whose permissions for other licensees extend to the entire whole, and thus to each and every part regardless of who wrote it.

Thus, it is not the intent of this section to claim rights or contest your rights to work written entirely by you; rather, the intent is to exercise the right to control the distribution of derivative or collective works based on the Library.

In addition, mere aggregation of another work not based on the Library with the Library (or with a work based on the Library) on a volume of a storage or distribution medium does not bring the other work under the scope of this License.

3. You may opt to apply the terms of the ordinary GNU General Public License instead of this License to a given copy of the Library. To do this, you must alter all the notices that refer to this License, so that they refer to the ordinary GNU General Public License, version 2, instead of to this License. (If a newer version than version 2 of the ordinary GNU General Public License has appeared, then you can specify that version instead if you wish.) Do not make any other change in these notices.

Once this change is made in a given copy, it is irreversible for that copy, so the ordinary GNU General Public License applies to all subsequent copies and derivative works made from that copy.

This option is useful when you wish to copy part of the code of the Library into a program that is not a library.

4. You may copy and distribute the Library (or a portion or derivative of it, under Section 2) in object code or executable form under the terms of Sections 1 and 2 above provided that you accompany it with the complete corresponding machine-readable source code, which must be distributed under the terms of Sections 1 and 2 above on a medium customarily used for software interchange.

If distribution of object code is made by offering access to copy from a designated place, then offering equivalent access to copy the source code from the same place satisfies the requirement to distribute the source code, even though third parties are not compelled to copy the source along with the object code.

5. A program that contains no derivative of any portion of the Library, but is designed to work with the Library by being compiled or linked with it, is called a "work that uses the Library". Such a work, in isolation, is not a derivative work of the Library, and therefore falls outside the scope of this License.

However, linking a "work that uses the Library" with the Library creates an executable that is a derivative of the Library (because it contains portions of the Library), rather than a "work that uses the library". The executable is therefore covered by this License. Section 6 states terms for distribution of such executables.

When a "work that uses the Library" uses material from a header file that is part of the Library, the object code for the work may be a derivative work of the Library even though the source code is not. Whether this is true is especially significant if the work can be linked without the Library, or if the work is itself a library. The threshold for this to be true is not precisely defined by law.

If such an object file uses only numerical parameters, data structure layouts and accessors, and small macros and small inline functions (ten lines or less in length), then the use of the object file is unrestricted, regardless of whether it is legally a derivative work. (Executables containing this object code plus portions of the Library will still fall under Section 6.)

Otherwise, if the work is a derivative of the Library, you may distribute the object code for the work under the terms of Section 6. Any executables containing that work also fall under Section 6, whether or not they are linked directly with the Library itself.

6. As an exception to the Sections above, you may also combine or link a "work that uses the Library" with the Library to produce a work containing portions of the Library, and distribute that work under terms of your choice, provided that the terms permit modification of the work for the customer's own use and reverse engineering for debugging such modifications.

You must give prominent notice with each copy of the work that the Library is used in it and that the Library and its use are covered by this License. You must supply a copy of this License. If the work during execution displays copyright notices, you must include the copyright notice for the Library among them, as well as a reference directing the user to the copy of this License. Also, you must do one of these things:

a. Accompany the work with the complete corresponding machine-readable source code for the Library including whatever changes were used in the work (which must be distributed under Sections 1 and 2 above); and, if the work is an executable linked with the Library, with the complete machine-readable "work that uses the Library", as object code and/or source code, so that the user can modify the Library and then relink to produce a modified executable containing the modified Library. (It is understood that the user who changes the contents of definitions files in the Library will not necessarily be able to recompile the application to use the modified definitions.)

b. Use a suitable shared library mechanism for linking with the Library. A suitable mechanism is one that (1) uses at run time a copy of the library already present on the user's computer system, rather than copying library functions into the executable, and (2) will operate properly with a modified version of the library, if the user installs one, as long as the modified version is interface-compatible with the version that the work was made with.

c. Accompany the work with a written offer, valid for at least three years, to give the same user the materials specified in Subsection 6a, above, for a charge no more than the cost of performing this distribution.

d. If distribution of the work is made by offering access to copy from a designated place, offer equivalent access to copy the above specified materials from the same place.

e. Verify that the user has already received a copy of these materials or that you have already sent this user a copy.

For an executable, the required form of the "work that uses the Library" must include any data and utility programs needed for reproducing the executable from it. However, as a special exception, the materials to be distributed need not include anything that is normally distributed (in either source or binary form) with the major components (compiler, kernel, and so on) of the operating system on which the executable runs, unless that component itself accompanies the executable.

It may happen that this requirement contradicts the license restrictions of other proprietary libraries that do not normally accompany the operating system. Such a contradiction means you cannot use both them and the Library together in an executable that you distribute.

7. You may place library facilities that are a work based on the Library side-by-side in a single library together with other library facilities not covered by this License, and distribute such a combined library, provided that the separate distribution of the work based on the Library and of the other library facilities is otherwise permitted, and provided that you do these two things:

a. Accompany the combined library with a copy of the same work based on the Library, uncombined with any other library facilities. This must be distributed under the terms of the Sections above.

b. Give prominent notice with the combined library of the fact that part of it is a work based on the Library, and explaining where to find the accompanying uncombined form of the same work.

8. You may not copy, modify, sublicense, link with, or distribute the Library except as expressly provided under this License. Any attempt otherwise to copy, modify, sublicense, link with, or distribute the Library is void, and will automatically terminate your rights under this License. However, parties who have received copies, or rights, from you under this License will not have their licenses terminated so long as such parties remain in full compliance.

9. You are not required to accept this License, since you have not signed it. However, nothing else grants you permission to modify or distribute the Library or its derivative works. These actions are prohibited by law if you do not accept this License. Therefore, by modifying or distributing the Library (or any work based on the Library), you indicate your acceptance of this License to do so, and all its terms and conditions for copying, distributing or modifying the Library or works based on it.

10. Each time you redistribute the Library (or any work based on the Library), the recipient automatically receives a license from the original licensor to copy, distribute, link with or modify the Library subject to these terms and conditions. You may not impose any further restrictions on the recipients' exercise of the rights granted herein. You are not responsible for enforcing compliance by third parties with this License.

11. If, as a consequence of a court judgment or allegation of patent infringement or for any other reason (not limited to patent issues), conditions are imposed on you (whether by court order, agreement or otherwise) that contradict the conditions of this License, they do not excuse you from the conditions of this License. If you cannot distribute so as to satisfy simultaneously your obligations under this License and any other pertinent obligations, then as a consequence you may not distribute the Library at all. For example, if a patent license would not permit royalty-free redistribution of the Library by all those who receive copies directly or indirectly through you, then the only way you could satisfy both it and this License would be to refrain entirely from distribution of the Library.

If any portion of this section is held invalid or unenforceable under any particular circumstance, the balance of the section is intended to apply, and the section as a whole is intended to apply in other circumstances.

It is not the purpose of this section to induce you to infringe any patents or other property right claims or to contest validity of any such claims; this section has the sole purpose of protecting the integrity of the free software distribution system which is implemented by public license practices. Many people have made generous contributions to the wide range of software distributed through that system in reliance on consistent application of that system; it is up to the author/donor to decide if he or she is willing to distribute software through any other system and a licensee cannot impose that choice.

This section is intended to make thoroughly clear what is believed to be a consequence of the rest of this License.

12. If the distribution and/or use of the Library is restricted in certain countries either by patents or by copyrighted interfaces, the original copyright holder who places the Library under this License may add an explicit geographical distribution limitation excluding those countries, so that distribution is permitted only in or among countries not thus excluded. In such case, this License incorporates the limitation as if written in the body of this License.

13. The Free Software Foundation may publish revised and/or new versions of the Lesser General Public License from time to time. Such new versions will be similar in spirit to the present version, but may differ in detail to address new problems or concerns. Each version is given a distinguishing version number. If the Library specifies a version number of this License which applies to it and "any later version", you have the option of following the terms and conditions either of that version or of any later version published by the Free Software Foundation. If the Library does not specify a license version number, you may choose any version ever published by the Free Software Foundation.

14. If you wish to incorporate parts of the Library into other free programs whose distribution conditions are incompatible with these, write to the author to ask for permission. For software which is copyrighted by the Free Software Foundation, write to the Free Software Foundation; we sometimes make exceptions for this. Our decision will be guided by the two goals of preserving the free status of all derivatives of our free software and of promoting the sharing and reuse of software generally.

#### NO WARRANTY

15. BECAUSE THE LIBRARY IS LICENSED FREE OF CHARGE, THERE IS NO WARRANTY FOR THE LIBRARY, TO THE EXTENT PERMITTED BY APPLICABLE LAW. EXCEPT WHEN OTHERWISE STATED IN WRITING THE COPYRIGHT HOLDERS AND/OR OTHER PARTIES PROVIDE THE LIBRARY "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE LIBRARY IS WITH YOU. SHOULD THE LIBRARY PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION.

16. IN NO EVENT UNLESS REQUIRED BY APPLICABLE LAW OR AGREED TO IN WRITING WILL ANY COPYRIGHT HOLDER, OR ANY OTHER PARTY WHO MAY MODIFY AND/OR REDISTRIBUTE THE LIBRARY AS PERMITTED ABOVE, BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE LIBRARY (INCLUDING BUT NOT LIMITED TO LOSS OF DATA OR DATA BEING RENDERED INACCURATE OR LOSSES SUSTAINED BY YOU OR THIRD PARTIES OR A FAILURE OF THE LIBRARY TO OPERATE WITH ANY OTHER SOFTWARE), EVEN IF SUCH HOLDER OR OTHER PARTY HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

#### END OF TERMS AND CONDITIONS

#### How to Apply These Terms to Your New Libraries

If you develop a new library, and you want it to be of the greatest possible use to the public, we recommend making it free software that everyone can redistribute and change. You can do so by permitting redistribution under these terms (or, alternatively, under the terms of the ordinary General Public License).

To apply these terms, attach the following notices to the library. It is safest to attach them to the start of each source file to most effectively convey the exclusion of warranty; and each file should have at least the "copyright" line and a pointer to where the full notice is found.

1 April 1990

Lexmark International, Inc.

That's all there is to it!