marantz



NR1604 SLIM DESIGN NETWORK AV RECEIVER

If you (or more likely, your partner) doesn't want big, powerful cabinets

Because, although it is super-slim it packs the same punch as its bigger

in your living room, then consider the slim-line NR1604 AV Receiver.

brothers, delivering ear-cracking, seven channel surround sound from

90W per channel. But it's not just the audio that is spectacular with the

NR1604, it delivers superior video as well, thanks to the 4k pass through

to the smaller NR1504, as it includes additional HDMI and component-

functionality without the need for an additional amp. Also, even though

it is a slim-line receiver, it also boasts the same networking facilities for

audio streaming as its bigger cousins. It gives you Internet radio, AirPlay


from your iPhone, iPad or iPod, as well as an iPod-digital-compatible USB input. Set-up is easy - with the help of the advanced GUI, Setup Assistant, Audyssey MultEQ and Microphone – so there is no need to study the

manual, just follow the on-screen instructions. It all adds up to easy-to-use slim-line elegance with a powerful punch. What more could you ask for?

video in and out ports. It also gives you multiroom / multisource

capabilities, GUI overlay and 4k scaling. And this is not the only difference







Main Features

- Dolby TrueHD and dts-HD Master Audio
- 7ch discrete power amplifier, 90 W per channel
- Dynamic Volume and Dynamic EQ
- HDMI: 6+1 in / 1out (3D, ARC, Deep Color)
- Analogue & HDMI Upconversion to 4k
- Network Audio and JPEG streaming
- MP3, WAV, AAC, FLAC, WMA, Lossless, FLAC192/24 (HD)
- Gapless Playback
- Spotify*, last.fm*, Flickr, Internet Radio support
- iPod/iPhone compatible USB, iPad charging
- New Marantz Remote App for iOS and Android devices

EAN

| EU | NR1604/N1B | 4951035050583 | Black |
|----|-------------|---------------|-------------|
| | NR1604/N1SG | 4951035050590 | Silver-Gold |
| UK | NR1604/T1B | 4951035050583 | Black |
| | NEASSATION | | |

NR1604/T1SG 4951035050590 Silver-Gold

www.marantz.eu

because music matters



NR1604

SLIM DESIGN NETWORK AV RECEIVER



| FEATURES | NR1604 |
|---|---------------------------------|
| MULTICHANNEL SURROUND | |
| DTS HD Master / DTS 5.1 / DTS ES / DTS 96/24 | •/•/•/• |
| Dolby Digital Plus / Dolby TrueHD / Dolby Digital EX / DPL IIz | •/•/•/• |
| Multichannel Stereo | • |
| Compressed audio Enhancer: MDAX2 | • |
| NETWORK | |
| DLNA Certified | • (v1.5) |
| Lossy formats MP3 / WMA / AAC | • / • / • |
| Lossless formats FLAC / ALAC / WAV | • / • / • |
| FLAC HD 192/24 | • |
| WAV 192/24 | • |
| ALAC 96/24 | • |
| Gapless playback | (FLAC, WAV) |
| Photo streaming (JPEG) | • |
| AirPlay audio streaming | • |
| Windows PlayTo / Windows 8/RT compatible | • / • |
| Internet Radio (vTuner) | • |
| Spotify* | • |
| last.fm* | • |
| Compatible with Remote APP for Smart Phones | Android/iOS |
| Ethernet | • |
| OTHERS | |
| Bluetooth audio via RX101 | optional |
| Auto speaker setup by microphone | Audyssey MultEQ |
| Audyssey Dynamic EQ / Dynamic Volume | •/• |
| Video conversion | CVBS > HDMI; |
| Videenreesing | Comp > HDMI |
| Videoprocessing | >1080p, 4k |
| HDMI path though on stand-by | • |
| 3D video pass through | • |
| Audio Return Channel | • |
| On Screen Display: Advanced GUI | • |
| GUI overlay on HDMI | • |
| Setup Assistant (English, German, French, Spanish, Italian, Dutch, Swedish, Polish, Russian) | • |
| Variable cross over | • |
| Multiroom zones | 1 |
| Optimized Bass Redirection | • |

| INPUTS/OUTPUTS | |
|---|-----------------------------|
| VIDEO | |
| Composite In / Out | 3 / 1 |
| Component In / Out | 2 / 1 |
| HDMI In / Out | 6+1 / 1 |
| AUDIO | |
| Analogue In / Out | 3 / 0 |
| Digital Optical In / Out | 1 / 0 |
| Digital Coaxial In / Out | 1 / 0 |
| Multichannel Pre Out | • (2.1) |
| Subwoofer Out | 1 |
| Zone audio preout | • |
| OTHER | |
| M-XPort for RX101 | • |
| Speaker A / B | • |
| Height speaker terninal | Speaker B or Heigth |
| Bi-amp drive (5.1 ch setting) | • |
| Multi-Room Speaker Terminal | Surround Back assignable |
| Marantz remote bus | • |
| Network: (IP-control / update) | • / • |
| Front Inputs: HDMI / USB | • / • |
| USB Audio / Made for iPod / Works with iPhone | • / • / • |
| SPECIFICATIONS | |
| Number of poweramps | 7 |
| Power Output per channel | |
| 6 ohm, 1 kHz, 1%, 1ch Drive | 90 W |
| 6 ohm, 1 kHz. 0.7%, 2ch Drive | 70 W |
| 8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive | 50 W |
| Audio Signal to Noise Ratio | 98 dB |
| FM Tuner | • |
| GENERAL | |
| Available colors: Black / Silver-Gold | • / • |
| System Remote Control | RC021SR |
| Power Consumption in W | 220 |
| Standby Consumption in W | 0.2 |
| Maximum Dimensions (W x D x H) in mm | 440 x 367 x 105 |
| Weight in kg | 8.4 |
| | |



Convenient front panel HDMI input along with a USB port



* This feature is not available in all countries.